

computing today

ISSN 0142-7210

SEPT 1979

50p


**A RACY
PROGRAM TO RUN**

Speech Recognition

Big Basic For Triton

MPU Swansong

Show Reports



8K ON BOARD MEMORY!

5K RAM, 3K ROM or 4K RAM, 4K ROM (link selectable). Kit supplied with 3K RAM, 3K ROM. System expandable for up to 32K memory.

2 KEYBOARDS!

56 Key alphanumeric keyboard for entering high level language plus 16 key Hex pad for easy entry of machine code.

GRAPHICS!

64 character graphics option — includes transistor symbols! Only £18.20 extra!

MEMORY MAPPED

high resolution VDU circuitry using discrete TTL for extra flexibility. Has its own 2K memory to give 32 lines for 64 characters.

KANSAS CITY

low error rate tape interface.

2 MICROPROCESSORS

Z80 the powerful CPU with 158 instructions, including all 78 of the 8080, controls the MM57109 number cruncher. Functions include +, -, *, /, squares, roots, logs, exponentials, trig functions, inverses etc. Range 10^{-99} to 9×10^{99} to 8 figures plus 2 exponent digits.

EFFICIENT OPERATION

Why waste valuable memory on sub routines for numeric processing? The number cruncher handles everything internally!

RESIDENT BASIC

with extended mathematical capability. Only 2K memory used but more powerful than most 8K Basics!

1K MONITOR

resident in EPROM.

SINGLE BOARD DESIGN

Even keyboards and power supply circuitry on the superb quality double sided plated through-hole PCB.

**ONLY
£275.00
+VAT**



Cabinet size 19.0" x 15.7" x 3.3". Television by courtesy of Rumblelows Ltd., price £58.62

**COMPLETE
KIT**

POWERTRAN


PSI Comp 80.Z80 Based powerful scientific computer
Design being published in Wireless World — NOW!

The kit for this outstandingly practical design by John Adams being published in a series of articles in Wireless World really is complete!

Included in the PSI COMP 80 scientific computer kit is a professionally finished cabinet, fibre-glass double sided, plated-through-hole printed circuit board, 2 keyboards PCB mounted for ease of construction, IC sockets, high reliability metal oxide resistors, power supply using custom designed toroidal transformer, 2K Basic and 1K monitor in EPROMS and, of course, wire, nuts, bolts, etc.

**SYSTEM
EXPANSION
COMING
SHORTLY!**

e.g.
8K RAM Board
8K ROM Board
Prom programmer
Printer Interface
etc.
etc.



Kit also available as separate packs: e.g. PCB, Keyboards, Cabinet, etc.

PCB size 16.0"x12.5"

Value Added Tax not included in prices

PRICE STABILITY: Order with confidence. Irrespective of any price changes we will honour all prices in this advertisement until October 31st, 1979. If this month's advertisement is mentioned with your order. Errors and VAT rate changes excluded.

EXPORT ORDERS: No VAT. Postage charged at actual cost plus 50p handling and documentation.

U.K. ORDERS: Subsequent to 15% surcharge for VAT. NO charge is made for carriage. Or current rate if changed.

SECURICOR DELIVER: For this optional service (U.K. mainland only) add £2.50 (VAT inclusive) per kit.

UK Carriage FREE

POWERTRAN COMPUTERS

(a division of POWERTRAN ELECTRONICS)

PORTWAY INDUSTRIAL ESTATE
ANDOVER HANTS SP10 3MN

ANDOVER
(0264) 64455

computing today

VOL. 1, No. 7
SEPT. 1979



ACTING EDITOR: Ron Harris B.Sc
EDITORIAL ASSISTANT: Henry Budgett.
ART DIRECTOR: Diego Rincon.
PRODUCTION: Pete Howells, Paul Edwards,
Tony Strakas.
ADVERTISING: Chris Surgenor (Manager).
EDITORIAL DIRECTOR: Halvor Moorshead

	PAGE
NEWS	5
All the latest on the newest	
SOFTSPOT	13 & 48
Readers programs for your enjoyment	
TRITON BASIC V5.1	14
A more powerful BASIC for this popular machine	
COMPUTER MUSIC	20
Connect ETI's polyphonic controller to your micro	
MICROPROCESSORS BY EXPERIMENT	25
Clock it faster and see where it gets you	
SCES REPORT	31
From across the pond we bring you the news	
READER SURVEY	37
Help us to help you	
READER OFFER: TELEPHONE CALL TIMER	41
Keep track of the pennies.	
CONVERTER PROJECT	43
Hexed with numbers, convert them!	
CONVERTER PROJECT	43
Hexed with numbers, convert them!	
ONLINE EXHIBITIONS	52
*A pictorial view of two recent London shows	
BEGINNING BASIC	56
More on Extended BASIC commands	
PRINTOUT	60
Readers views expressed	
SPEECH RECOGNITION	63
Fact or Fiction? We reveal the truth	
BRANDS	68
A high speed game in BASIC	

Cartoons 11, Next month 19, Marketplace 29, ETI 47, Books 50, T Shirts 59.

Computing Today International is normally published on the third Friday of the month prior to the cover date.
COPYRIGHT: All material is subject to world wide Copyright protection. All reasonable care is taken in the preparation of the magazine to ensure accuracy but CT cannot be held responsible for it legally. Where errors do occur a correction will be published as soon as possible afterwards.

Distributed by Argus Distribution Ltd. Printed by LSG. Limited, Lincoln.


EDITORIAL AND ADVERTISEMENT OFFICE

145 Charing Cross Road, London WC2H 0EE. Telephone 01-437 1002/3/4/5

TRITON

SINGLE BOARD PERSONAL COMPUTER

Three new exciting expandable systems designed for ease of construction and flexibility. Kits come complete with case, power supply, full keyboard, PCB. All components available separately, see catalogue. Full hardware. Programming manual available. The system is easy to expand and is well supported. Features — 2, 2.5 or 7K Basic in Eprom (see catalogue).



- Single Board
- Holds up to 8K Memory
- Cassette Interface

- Three Firmware options
- Basic in Eprom
- Plug-in Expansion Boards

Personal Computer


£286 + VAT
From

EXPANSION MOTHERBOARD

TRITON. Expand your Triton simply and easily with our new 8-slot motherboard complete with its own P.S.U. takes 8 plug-in Euro cards. Plug-in 8k RAM card and Eprom cards now available. Kit complete with PSU + 1 set connectors.

8 SLOT

Uses Standard 64-way DIN Con



£50 + VAT

8K RAM CARD


Triton 8k Static RAM card kit uses 2114L low power 4k static RAMS. On board regulation. Mem jump select.

PCB only £15 — RAMS £5.50

Kit less RAMS £31 incl 5SKTS & components

Compi Kit

£97 + VAT




8K EPROM CARD

Triton 8k Eprom card kit designed to take up to 8 x 2708 Eproms (1k x 8) as RAM card.

PCB only £15

Kit less Eproms

Eproms (blank) £9



£97
Complete kit + VAT

BI DIRECTIONAL MATRIX PRINTER

£595 + VAT

The BD80 is a low cost, 80 column line printer with microprocessor control to provide excellent reliability and performance

- 5 x 7 Matrix
- 10 lines/sec Paper Advance
- 10 Char per inch
- 112 Char/sec
- 6 lines/inch
- 84 lines per minute
- 400 Char Buffer
- Self Test
- Full ASC II Char Set
- Fully Cased




A UNIQUE PRINTER FAST AND RELIABLE

Switch selectable baud rate from 110 to 9600 on a standard V24 and RS232 Interface — Send SAE for further details. Ideal printer for Triton or any system requiring high speed, reliable, hard copy. We can supply consumables.

VIDEO MONITOR NEW

A brand new fully cased (metal) high resolution 10" video monitor with PSU for only £69 + VAT. Ideal for Triton or any home computer system. Carriage by Securior can be arranged. Send SAE for details or see our new catalogue

ONLY £69!
+ VAT



PCB CONNECTORS

Edge connectors gold contact double sided PCB connectors

Size	Price	Size	Price
22/44	£3.20	6/12	£1.62
25/50	£3.60	10/20	£1.90
28/56	£3.90	15/30	£3.00
30/60	£4.15	18/36	£3.00
35/70	£4.60	22/44	£3.00
36/72	£4.75	28/56	£3.40
40/80	£5.00	36/72	£3.90
43/86	£5.50	43/82	£4.60
50/100	£5.80	(S100 Bus)	



+ VAT

VIDEO DISPLAY INTERFACE MODULE

Completely built and tested the SFXE x 68364 card uses the industry standard SPF 96364 CRT control chip and allows ASC II parallel input of data to be output to video monitor 64 character by 16 line display full cursor control. Single 5v supply. Full details available on request (Send SAE). UHF modulator available, £2.50 extra + VAT.



£69 + VAT

COMPONENTS 74LXX

SN74LS00N	18	SN74LS54N	21	SN74LS131N	40	SN74LS194AN	85	SN74LS324N	1.80
SN74LS01N	18	SN74LS55N	21	SN74LS138N	75	SN74LS196AN	85	SN74LS325N	2.55
SN74LS02N	20	SN74LS56N	21	SN74LS139N	75	SN74LS196N	1.20	SN74LS326N	2.55
SN74LS03N	18	SN74LS563N	1.50	SN74LS145N	120	SN74LS197N	1.20	SN74LS332N	1.20
SN74LS04N	20	SN74LS573N	35	SN74LS148N	175	SN74LS221N	1.25	SN74LS333N	1.65
SN74LS05N	26	SN74LS575N	46	SN74LS151N	85	SN74LS240N	2.20	SN74LS356N	65
SN74LS06N	20	SN74LS575N	46	SN74LS153N	60	SN74LS241N	1.90	SN74LS368N	65
SN74LS09N	22	SN74LS578N	36	SN74LS154N	160	SN74LS242N	1.90	SN74LS367N	65
SN74LS10N	18	SN74LS578N	36	SN74LS156N	125	SN74LS243N	1.95	SN74LS368N	65
SN74LS11N	26	SN74LS581N	40	SN74LS157N	60	SN74LS244N	2.10	SN74LS373N	1.75
SN74LS12N	25	SN74LS586N	1.10	SN74LS157N	60	SN74LS245N	2.60	SN74LS375N	1.70
SN74LS13N	55	SN74LS589N	40	SN74LS158N	99	SN74LS247N	1.25	SN74LS375N	1.70
SN74LS14N	89	SN74LS590N	65	SN74LS160N	115	SN74LS248N	1.95	SN74LS377N	1.75
SN74LS15N	26	SN74LS591N	95	SN74LS161N	115	SN74LS249N	1.30	SN74LS378N	1.32
SN74LS16N	20	SN74LS592N	95	SN74LS162N	115	SN74LS250N	1.45	SN74LS379N	1.40
SN74LS21N	26	SN74LS593BN	65	SN74LS163N	90	SN74LS253N	1.25	SN74LS381N	3.65
SN74LS22N	26	SN74LS595AN	20	SN74LS164N	150	SN74LS257N	1.40	SN74LS386N	57
SN74LS26N	39	SN74LS596N	1.75	SN74LS165N	170	SN74LS268N	95	SN74LS390N	1.80
SN74LS27N	39	SN74LS597N	1.75	SN74LS166N	170	SN74LS269N	1.45	SN74LS393N	1.50
SN74LS28N	39	SN74LS109N	39	SN74LS168N	1.95	SN74LS270N	1.45	SN74LS394N	1.50
SN74LS30N	25	SN74LS112N	39	SN74LS169N	1.95	SN74LS261N	3.50	SN74LS396N	1.70
SN74LS33N	27	SN74LS113N	44	SN74LS170N	250	SN74LS262N	39	SN74LS398N	2.75
SN74LS34N	27	SN74LS114N	220	SN74LS171N	44	SN74LS263N	39	SN74LS399N	1.60
SN74LS37N	29	SN74LS122N	79	SN74LS174N	116	SN74LS264N	39	SN74LS400N	1.25
SN74LS38N	29	SN74LS123N	90	SN74LS175N	105	SN74LS265N	39	SN74LS401N	1.25
SN74LS40N	25	SN74LS124N	150	SN74LS181N	25	SN74LS283N	1.80	SN74LS447N	1.25
SN74LS42N	79	SN74LS125N	150	SN74LS190N	1.75	SN74LS290N	1.80	SN74LS409N	1.95
SN74LS43N	79	SN74LS126N	150	SN74LS193N	1.75	SN74LS293N	1.80	SN74LS468N	95
SN74LS48N	95	SN74LS127N	150	SN74LS192N	1.45	SN74LS296N	1.20	SN74LS469N	95
SN74LS49N	1.09	SN74LS133N	39	SN74LS193N	1.75	SN74LS298N	1.20	SN74LS470N	2.20



BLASTA PROM

Enjoy wiping out your PROMS? Well you can now erase up to 104 EPROMS simultaneously with a new unit from Microsystem Services. Complete with a built in timer unit and indica-

tors it will either accept whole boards or individual EPROMS. The UV tubes have a life of 2000 hours and thereafter they start to lose efficiency but can still be used. More details from Microsystem Services at Duke Street, High Wycombe, Bucks. Tel. 0494-41661.

HARDING HELP

An urgent release has come our way from A.J.Harding (Molimerx) the TRS-80 Software house. Apparently the CTR-80 recorder can cause severe problems with your tapes, rendering them unuseable. The cure appears to be to put a 1A 50V

diode across the brown motor wire, plus to plus-minus to minus. Harding's will undertake to repair any scrambled tapes that they have supplied, for a limited period, but you must include postage to cover costs. A.J.Harding live at 28 Collington Avenue, Bexhill on Sea, East Sussex.

FLOPPY CONTROL FROM INTEL

A new single board Universal Floppy Disk Controller, the iSBC-204 has been launched by Intel. As standard it can control two drive surfaces but can be expanded to four. Using DMA and programmable track access it can read, write, verify and


search with most single density soft secured standard or mini drive units.

Also announced recently is a reference card for owners of iSBC 80/20 single board computers, with a wide variety of useful information. For more details on both products contact Intel at 4 Between Towns Road, Cowley, Oxford OX4 3NB.

BURSTING OUT

Small business systems are the ideal companion for Cave Tab's Model 2444 table top burster. It can cope with most types of paper stock, cards and cheques at up to 200 feet per minute.

The unit can also handle multi-part forms and both static eliminator and slitter are available as add-on's. Total price is around £1,150. Cave Tab are at Teuter Road, Moulton Park, Northampton NN3 1PZ, Telephone 0604-48125.




PRINT IT BOTH WAYS

A bi-directional 40 column printer is beginning to make its mark in this country. Available from both Microdigital and Personal Computers the Trend-

com 100 is a low cost roll printer. Complete with its own micro the unit uses either black or blue thermal paper and is available with a variety of interfaces, Apple, PET or RS232. Using a five by seven dot matrix and ten characters per inch it will print at 40 characters per second. The basic parallel interface is in ASCII format and is TTL compatible with strobe and busy signals.

Supplied complete with integral power supply it will cost around £243 and Apple or PET interfaces are about £43.



NEW LOW BOOK PRICES AT MICRODIGITAL

Microprocessors: from chips to systems — R. Zaks — £7.95
 Microprocessor interfacing techniques — R. Zaks — £7.95
 Practical solid circuit design. Olesky — £5.20
 Some common BASIC programs — A. Osborne — £6.30
 Understanding solid state electronics. Texas Instruments — £2.40
 Microprocessor systems design. Klingman — £14.00
 Designing with TTL integrated circuits. Texas Instruments — £24.80
 Fundamentals and applications of digital logic circuits — S. Libes — £6.36
 Semiconductor circuit elements — T. Towers and S. Libes — £5.56
 TTL cookbook — D. Lancaster — £7.50
 CMOS cookbook — D. Lancaster — £7.95
 T. V. Typewriter cookbook — D. Lancaster — £7.50
 Cheap video cookbook — D. Lancaster — £5.10
 Microcomputer problem solving using PASCAL — K. L. Bowles — £7.84
 PASCAL User Manual and Report — Jensen and Wirth — £5.52
 Best of BYTE vol. 1 — Helmers et al. — £8.95
 Best of Creative Computing vol. 1 — AHL et al. — £6.95
 Best of Creative Computing vol. 2 — AHL et al. — £6.95
 Scelbi-Byte Primer — Helmers et al. — £9.95
 The Best of Micro — Tripp et al. — £6.95
 The First West Coast Computer Faire proceedings — J. C. Warren — £9.56
 The Second West Coast Computer Faire proceedings — J. C. Warren — £9.56
 Basex — P. Wame — £6.40
 Superwumpus — J. Emmerichs — £4.80
 Garcia's Circuit Cellar — S. Garcia — £6.40
 Bar Code Loader — K. Budnick — £1.60
 Tracer: A 6800 debugging program — J. Hemenway — £4.80
 RA6800ML: An M6800 Relocatable Macro-assembler — J. Hemenway — £20.00
 The 8080A Bugbook. Microcomputer interfacing and programming — P. R. Rony et al. — £7.95
 8080 machine language programming for beginners — R. Santore — £5.10

Scelbi "8080" software gourmet guide and cookbook — Scelbi computer consultants — £7.95
 8080/8085 Software design — C. A. Titus, P. R. Rony et al. — £7.50
 Practical microcomputer programming: The Intel 8080 — W. J. Weller et al. — £17.56
 Scelbi's 8080 standard monitor £9.95
 Scelbi's 8080 standard editor £9.95
 Scelbi's 8080 standard assembler £15.95
 Scelbi computer consultants
 8080 Assembly language programming — L. Leventhal — £7.95
 An Editor/Assembler system for 8080/8085 based computers — W. J. Weller — £11.96
 Scelbi 8080 Galaxy game — Scelbi computer consultants — £7.95
 Z-80 instruction handbook — Scelbi — £3.95
 Practical microcomputer programming: the Z80 — W. J. Weller — £23.96
 Sargon Z80 Chess Program — D. and K. Spracklen — £9.50
 The Z80 microcomputer handbook — W. Barden — £6.95
 A-80 Programming for logic design — A. Osborne — £5.95
 Z-80 Programming manual — Mostek — £4.50
 Sorcerer Technical manual — £8.95
 Practical microcomputer programming: the M6800 — W. J. Weller et al. — £17.56
 Scelbi 6800 Gourmet guide — Scelbi computer consultants — £7.95
 Programming the 6800 microprocessor — Bob Southern — £8.00
 6800 Assembly language programming — L. Leventhal — £7.95
 Using the 6800 microprocessor — E. Poe — £6.25
 APL — an interactive approach — Gilman and Rose — £9.50
 Microprogrammed APL implementation — R. Zaks — £14.75
 A guide to SC/MP programming — Drury — £4.00
 Artat and computer — R. Leavit — £3.96
 Illustrating Basic — a simple programming language — D. Alcock — £2.25
 Basic computer games — D.H. Ahi — £5.50
 Game playing with BASIC — D. Spencer — £5.56
 Starship simulation — R. Garrett — £5.10
 Game playing with computers — D. Spencer — £13.56
 57 Practical programs and games in BASIC — K. Tracton — £6.36
 Chess and computers — D. Levy — £7.16
 Chess skill in man and machine — P. Frey — £11.84

Phone in your
Access/Barclaycard
Number on
051-236-0707
or complete
this order
form

PLEASE
SEND ME:

I ENCLOSE:

CHEQUE/POSTAL ORDER NO.

BARCLAYCARD NO.

ACCESS CARD NO.

NAME

ADDRESS

COMPLETE AND POST TO



MICRODIGITAL LTD. 25 BRUNSWICK STREET
LIVERPOOL L2 0BJ Tel: 051-236 0707

POWER-one D.C. POWER SUPPLIES

Now, like Intel, Motorola and National you can buy Power-One open frame power supplies and enjoy quality and reliability at LOW LOW prices. Over 70 different models to choose from including floppy disc drive supplies as well as single, double, triple and quad output.



Single Output

5V at 2.7A w/OVP	£18.50
5V at 5.4A w/OVP	£41.50
12V at 6A	£87.50
15V at 5.4A	£87.50

Dual Output

±12 to 15V at 1.5A	£41.00
±18 to 24V at 0.4A	£32.50
±5V at 5.4A w/OVP	£78.00

Floppy Disc Drive Supplies

— with connectors and cables for Shugart drives if required.

CP-249 — drives one mini drive	£33.00
CP-323 — drives two mini drives	£80.00
CP-205 — drives one Shugart or equivalent 8" drive	£58.00
CP-206 — drives two SA800	£76.00

Triple Output

5V, 9-15V, -5, -12, -15V at 1.8A to 10.8A	From £41.00 to £137.00
---	------------------------

Discount available to bona-fide educational establishments. Quantity discounts start at five units. Trade enquiries welcome. Send large SAE for full catalogue and price list.



COMPUTERS LTD.,

133 Woodham Lane, New Haw, Weybridge, Surrey
KT15 3NJ. Tel: 093 23 45421. Telex: 8813487.

Newtronics

Computer div' of H.L. Audio Ltd.



The Newtronics Keyboard Terminal is a low cost stand alone Video Terminal that operates quietly and maintenance free. It will allow you to display on a monitor 16 lines of 64 characters or 16 lines of 32 characters on a modified TV (RF Modulator required).

The characters can be any of the 96 ASC11 alphanumerics and any of the 32 special characters, in addition to upper-lower case capability it has scroll up features and full X-Y cursor control. All that is required from your microcomputer is 300 baud, RS232-C or 20ma loop, serial data, plus a power source of 8v DC and 6.3v AC. The steel cabinet is finished in IBM Blue-Black. And if that is not enough the price is only **£135.55** + VAT as a Kit, or **£175.00** + VAT assembled and tested. Plus £2.00 P & P.

Price does not include Video Monitor

To order phone or write to:—

NEWTRONICS 138 KINGSLAND ROAD, LONDON E2 8BY
TEL: 01 739 1582

Access/Barclaycard accepted.

CLUB FORUM

Several more connections to our Club Survey have appeared in the mailbag over the last month. The Southampton Amateur Computer Club (SACC) is based at Southampton University. The correct address is The Secretary SACC, c/o P.G.Dorey, Department of Physiology, University of Southampton, Southampton SO9 3TU. The President, Paul Maddison, can be contacted on Winchester 4433 ex 6955. UK Membership is £3 or £2 for students and OAP's and this includes subscription to Benchmark, the club magazine. The club is also linked to the Southampton University Amateur Computer Club. Club meetings are held on the first Wednesday of the month at 7.30pm, starting in October, and are held at Seminar Room 2, Medical Sciences Building, Bassett Crescent East, Southampton.

The Thames Valley ACC has also requested an update on their club. The primary contacts are now Brian Quarm, Hon Sec, on Camberley 22186 or Brian Steer, Meeting Organiser, on Slough 20034. Mr Chris Wallwork is the Publicity Secretary and may be contacted at Oak Cottage, Echinswell, Nr. Newbury, Berkshire. Membership fees have not yet been set but last year was £1 + 50p per meeting. Meetings are held on the first Thursday of each month and they have visiting speakers, outside visits and also cater for special interest groups. As a footnote they are holding a Junk sale on the first Thursday in September with bring and buy stalls, contact them for the venue.

COMMODORE MOVE

As of July the first CBM have occupied new headquarters at 181 Leith Road, Slough, Berkshire. Telephone Slough 71229 and 71162. With this move they

Next on the list is the Oxfordshire Microcomputer Club, formerly the Oxford and District AMC. The primary contact here is Stephen Bird, 139 The Moors, Kidlington, Oxford OX5 2AF, telephone 08675-6703 after 6pm except Wednesdays. They have a membership of 20 and for the Kidlington and Witney areas the meet is on Wednesday nights at 7.30. Membership fees are £5 for April '79 to March '80. A monthly newsletter is published, mainly software. The club also incorporates the Oxfordshire ACC and the Oxfordshire TRS-80 and Z80 user groups. Other meeting points are St. Johns College Oxford, c/o St. Johns Micro Society on alternate Thursdays and for Oxford Polytechnic students contact Paul Duffey at the college for Tuesday meetings during term time.

Finally, believe it or not, I have received a letter from the Burlington-Dnes School Computer Club. They would like to start a magazine for schools computing in the London area, especially for those that have a 380Z Research Machines or use the ILEA RSTS system. Anyone wishing to help should get in touch with the club at the school, Danes Building, Du Cane Road, Hammersmith W12 0UT. Any charge for the magazine will be to cover the cost of production.

Owing to the reader survey in this issue which we hope will bring in some more news of clubs we are holding back the next survey until the Winter. So if you want to be included let me know, address your mail to Club Forum, Computing Today, 145 Charing Cross Road, London WC2H 0EE.

have disposed of the Eaglescliffe factory and hope to be able to supply a better and more centralised service. No indication has been given as to the fate of the shop in Euston Road.

GIVE YOUR PET A TOOLKIT

We have received a new piece of firmware for the Commodore PET from Petsoft called the Basic Programmers Toolkit. It is available as either a plug-on extra for old ROM machines or as a plug-in IC for new ROM ones. Based on a 2K ROM with machine code programs it gives you all those useful utilities at a single command. Facilities provided include automatic line

numbering, bulk deletion, re-numbering, HELP, trace and single step, automatic program building from tapes, dump, find and unlist. The last command makes your program listing secure, it cannot be accessed!

Available in September from Petsoft it will cost £75 for plug-on and £55 for the IC. A full review of the product will be published in next month's issue but from our preliminary tests it looks to be a very powerful and useful addition to any PET.



FAST MODEM


Borer Electronics have added a 9600 Band Modem to their range. Called the 96 LSI it provides a 4800 Band fall-back speed for poor quality lines. Using custom MOS/LSI circuitry and bit slice techniques it

provides an economical full duplex system. An advanced multiplexer can be incorporated to give four full duplex controls per channel allowing dial up access or half duplex links. For more info contact Borer at Fishponds Close, Wokingham, Berkshire RG11 2QL or ring Wokingham 783372.

TECS GET POST OFFICE APPROVAL

Remember the home computer system that we reviewed in our May edition which could handle Teletext? Well we mentioned at the time that the firm who were making it were seeking PO approval to use the system on Prestel, the TV/Telephone informatics service. The PO have now given type approval to the system and Technalogs will be able to supply systems from the

beginning of September. The system will be using aerial input to your TV so no modifications are needed. They will also be able to convert any previously supplied TECS system to Prestel subject to test. Prices range from the basic kit at £360 to a fully configured Prestel editor terminal at about £2000. For more information on this system contact Technalogs at 8 Egerton Street, Liverpool, Merseyside or ring on 051-724-2695.





PETSOFT 1st AGAIN!



CURSOR The

Cassette Magazine for Pet owners

Each issue contains at least five brand new programs. Plus, editorial coverage, new product announcements, reviews and programmers hints. £36 for ten issues mailed direct to you.



76 PROGRAMS

for only **£15**

Specially adapted for the PET from Adam Osborne and Associates best-selling book "Some Common Basic Programs". 76 essential mathematical and Financial programs on one cassette.



PET PROGRAMMERS TOOLKIT ...

AVAILABLE OCT.

10 powerful routines that greatly enhance PET BASIC, all on a single plug-in ROM chip. New commands include Re-number, Trace, Help, Find, Unlist, Delete, Append, Auto and Dump.

£55+V.A.T. for 16 and 32k PETS

£75+V.A.T. for 8k PETS with old ROMS



150

Pet Programs
in the
new Catalogue

including: Word Processor	£25
Assembler	£25
Critical Path	£15
Micro Chess	£14
French Vocab	£10
Music	£10
Debtors Letters	£15
Backgammon	£8
Restaurant Finder	£5
Payroll	£25
Program Development Aid System	£15
Stock Control	£15
Mailing List	£15
PET BASIC Tutorial	£15
Games Pack	£7

PLUS V.A.T.



PETACT

POWERFUL

Business Packages ...

PURCHASE ACCOUNTING

Handles Purchase Ledger, prepares a list of outstanding balances and prints remittance advices

SALES ACCOUNTING

All the facilities for maintenance of Sales Ledger, prepares list of outstanding balances and prints statements. Cassette systems from £225+V.A.T. Disk versions from £350 includes training course.

PLUS

STOCK CONTROL
PAYROLL,
NOMINAL LEDGER
and
MANAGEMENT
INFORMATION



Petsoft programs are available on cassette or disk for all models of the COMMODORE PET.

See them at over 200 computer stores, or contact us direct.

CREDIT CARD orders are accepted by telephone.

PET is the trademark of **commodore** who recommend PETACT Business Systems



Petsoft Part of the **ACT**
Computer Group

Radcliffe House, 66-68 Hagley Road,
Edgbaston, Birmingham B16 8PF

Telephone 021-455 8585 Telex 339396


My name is

I live at

Postcode

Please rush me a copy of your new catalogue of software for the Pet

COMPUTING TODAY 1979



UPDATED DIGITIZER

Terminal Display Systems have recently introduced the Bit Pad One. Described as a general purpose digitizer the new unit contains both the control electronics and the tablet in one unit. The size is 395mm square and 41mm high. Using the magnetostriction principle to give reliable operation through a range of materials it is available with a variety of interfaces, RS232, 8 bit parallel and IEEE-488. The unit can be used in one of three modes, Point mode for single co-ordinate, Switched mode for multiple sampling and Continuous mode. For more details contact TDS at Hillside, Whitebirk Estate, Blackburn, Lancs BB1 5SN or ring 0254-662244.

HARD AND SOFT APPLES

Keen Computers are now stocking the USCD Pascal Operating System for the Apple II. Comprising an Editor, Compiler and Assembler it allows full use to be made of this language for business, scientific and educational purposes. New Apple hardware includes Supertalker, a hardware speech synthesiser, Apple Clock and Romplust. The Apple Clock is also available from Personal Computers. Keen are at 5 The Poultry, Nottingham. Tel 0602-583254 and Personal Computers are at 194-200 Bishopsgate, London EC2M 4NR. Tel 01-283 3391.

ANOTHER STAR ARISES

Star Devices of Newbury, whose touch keyboard we reviewed in April, have released a new, improved version. The device features 7 bit parallel ASCII output with optional parity and positive and negative strobes. Each of the 128 ASCII codes has a unique key and the code is displayed on a row of seven LED's. The PCB lettering has been replaced by back printing on the pads. All the options for serial output, RS232 or 20 mA, open collector, active low and on board regulation have been retained as has the auto scan and bleep facility. The price stays the same too at £37.50 plus VAT. For more details contact Star Devices at PO Box 21, Newbury, Berkshire or ring Newbury 40405.

TRS-80 SOFTWARE NEWS

A neat little booklet arrived the other day from 3 Line Computing. Priced at £1, it contains a text editor program called Textman, complete with listing, a review of Newdos+ and a game called Tank Battle, again with a complete listing. As well as all this they have included some useful routines, an editorial and a list of other available software.

Full marks for both effort and presentation must be given to the authors Tim Hill and Fred Brown as this must rate as one of the best software services I have yet seen. For further details contact them at 421 Endike Lane, Hull HU6 8AG.



THETA III from PICODYTE



Z80 COMPUTER SYSTEM

Memory expansion to 64k or with paging to 256k. Either 2 or 3 integral BASF Mini Diskette Drives. Integral 12" CRT 24 x 80 with detachable keyboard. Serial RS232/20ma and parallel I/O ports.

System software available: CP/M, USCD Pascal, BASIC, FORTRAN, Micro-C, PL/M, COBOL, OPUS and TEMPO.

Optional multiprocessor configurations with custom character sets and graphics, alternative mass storage options and choice of industry standard backplanes.

Dual Disk System £2,900.

PICO OYTE

65 VICEROY CLOSE
BRISTOL ROAD
BIRMINGHAM B5 7UT
021-440-5631

PROMBOX 12 UV PROM ERASER

NEW



£63.89

includes P & P
Add VAT at 15%
Ex-stock

FEATURES:

- Simple Operation
- Erase time variable from 5 to 50 minutes
- Sliding tray can accommodate up to 12 UV Eproms
- Safety interlock prevents accidental exposure

Send cheques/official orders to:


GP INDUSTRIAL ELECTRONICS LTD.

Dept. CT

SKARDON WORKS, SKARDON PLACE, NORTH HILL
PLYMOUTH PL4 8EZ. TEL. 0752 28627

New Low-Cost ASCII Keyboards-Ex Stock Delivery.

KB771 — Latest addition to the range — ideal for the VDU-builder 71 Keystations incorporating separate numeric/cursor control pad and installed in a custom-built steel enclosure with textured enamel finish. Case dimensions: 17 1/4" x 7 1/2" x 3 1/2". Total weight: 4Kg.



Price £95.00 (mail order total £115.00) 25-way D-Type connector for KB771 £4.25 (mail order total £5.46).

NEW KEYTOP/ KEYSWITCH KITS — ASCII CHARACTER SET BRAND NEW SURPLUS

Pack of 58 keytops and keyswitches comprising 49 "Qwerty" set TTY format + 9 Edit/Function keys.

PRICE: £15.00 (mail order total £18.98)

NEW SHUGART FLOPPY DISC DRIVES

SA400 Minifloppy — 110KB capacity, 35 tracks, transfer rate 125Kbits/sec. AV access time, 550msec. Power requirements +5VDC + 12VDC.

PRICE: £195.00

SA800 Floppy — 400 KB capacity, 77 tracks, transfer rate 250Kbits/sec. AV access time 260msec. Power requirements +24DC + 5VDC — 5VDC.

PRICE: £395.00

KB756 56-keystations, mounted on PCB
KB756MF, as above, fitted with metal mounting frame for extra rigidity

Optional Extras:

KB15P Edge Connector £3.25
KB701 Plastic Enclosure £12.50
KB702 Steel Enclosure £25.00
KB710 Numeric Pad £8.00
KB2376 Spare ROM £12.50

Encoder £12.50

DC-512 DC/DC Converter £7.50

£14.95

£9.20

Mail order total

£49.50 £58.65

£55.00 £64.98

£3.25 £4.31

£12.50 £15.24

£25.00 £30.48

£8.00 £9.78

£12.50 £14.95

£7.50 £9.20

Quantity discounts available



All the above keyboards are fully TTL-compatible, providing the full 128 ASCII character set, and requiring +5V — 12V Power Supply. Full technical data and circuit diagrams supplied.

SEAELECTRO PATCH BOARDS

Programme boards for switching and interconnecting input/output circuits. 11 x 20 XY matrix. Interconnection is by means of shorting Skip and component holding pins (not included). Dimensions: 7 1/2" x 5 1/4" x 1".

PRICE: £12.50 (mail order total £14.58)

Reconditioned EDITING VDU SAVE £100!

HAZELTINE H-2000A
NOW ONLY £395.00
HAZELTINE H-2000B
NOW ONLY £495.00

- ★ Teletype Compatible
- ★ 12" Diagonal Screen
- ★ TTY Format Keyboard
- ★ 27 Lines of 74 characters
- ★ 64 ASCII Character Set
- ★ 5 x 7 Dot Matrix
- ★ 5 Switch-selectable Transmission Speeds up to 9600 baud.

Superb specification includes full edit capability, direct cursor addressing, standard V.24 (RS232) interface. 90 days' warranty.

- ★ Switch-selectable Parity
- ★ Standard CCITT V.24 Interface
- ★ Direct Cursor Addressing
- ★ Full Edit Capability
- ★ Detachable Keyboard
- ★ Printer Port
- ★ 90-day Warranty


We also specialise in: DEC minis — PDP8 and PDP11 processors, add-on memory, peripherals and spares. Hard copy terminals — ASR33 and KSR 33 Teletypes, Data Dynamics 390, Texas Silent 700. Send for complete lists.

A copy of our trading conditions supplied on request.



Electronic Brokers


49/53 Pancras Road London NW1 2QB Tel: 01-837 7781 Telex 298694



24 TUNE DOOR CHIMES

DOOR TUNES £16.44 + VAT.

Waddington's Videomaster announce a doorbell that doesn't go Brrringg, Ding Dong or Buzzzz. Instead it plays 24 different classical and popular tunes. It will play the tune you select for your mood, the season or the visitor you are expecting to call. Door tunes is not only great fun and a wonderful ice breaker, but is also very functionally and beautifully designed to enhance your home. There is something for Christmas, something for your continental visitors or your relations from the states, and even something for the Queen. Door tunes is easy to install and has separate controls for volume, tone and tempo.



T.V. GAMES

PROGRAMMABLE £29.50 + VAT. COLOUR CARTRIDGE T.V. GAME.

The TV game can be compared to an audio cassette deck and is programmed to play a multitude of different games in COLOUR, using various plug-in cartridges. At long last a TV game is available which will keep pace with improving technology by allowing you to extend your library of games with the purchase of additional cartridges as new games are developed. Each cartridge contains up to ten different action games and the first cartridge containing ten sports games is included free with the console. Other cartridges are currently available to enable you to play such games as Grand Prix Motor Racing, Super Wipeout and Stunt Rider. Further cartridges are to be released later this year, including Tank Battle, Hunt the Sub and Target. The console comes complete with two removable joystick player controls to enable you to move in all four directions (up/down/left/right) and built into these joystick controls are ball serve and target fire buttons. Other features include several difficulty option switches, automatic on screen digital scoring and colour coding on scores and balls. Lifelike sounds are transmitted through the TV's speaker, simulating the actual game being played. Manufactured by Waddington's Videomaster and guaranteed for one year.



EXTRA CARTRIDGES

ROAD RACE - £8.87 + VAT.

Grand Prix motor racing with gear changes, crash noises

SUPER WIPEOUT - £9.17 + VAT.

10 different games of blasting obstacles off the screen

STUNT RIDER - £12.16 + VAT.

Motorcycle speed trials, jumping obstacles, leaping various rows of up to 24 buses etc.

NON PROGRAMMABLE TV GAMES

6 Game - COLOURSCORE II - £13.50 + VAT.

10 Game COLOUR SPORTSWORLD £22.50 + VAT.

CHESS COMPUTERS

STAR CHESS - £56.09 + VAT.

PLAY CHESS AGAINST YOUR PARTNER.

using your own TV to display the board and pieces. Star Chess is a new absorbing game for two players, which will interest and excite all ages. The unit plugs into the aerial socket of your TV set and displays the board and pieces in full colour for black and white on your TV screen. Based on the moves of chess it adds even more excitement and interest to the game. For those who have never played, Star Chess is a novel introduction to the classic game of chess. For the experienced chess player, there are whole new dimensions of unpredictability and chance added to the strategy of the game. Not only can pieces be taken in conventional chess type moves, but each piece can also exchange rocket fire with its opponents. The unit comes complete with a free 18V mains adaptor, full instructions and twelve months guarantee.



CHESS CHALLENGER 7 - £85.65 + VAT. PLAY CHESS AGAINST THE COMPUTER.

The stylish, compact, portable console can be set to play at seven different levels of ability from beginner to expert including "Mate in two" and "Chess by mail". The computer will only make responses which obey international chess rules. Castling, on passant, and promoting a pawn are all included as part of the computer's programme. It is possible to enter any given problem from magazines or newspapers or alternatively establish your own board position and watch the computer react. The positions of all pieces can be verified by using the computer memory recall button.


Price includes unit with wood grained housing, and Staunton design chess pieces. Computer plays black or white and against itself and comes complete with a mains adaptor and 12 months guarantee.

OTHER CHESS COMPUTERS IN OUR RANGE INCLUDE:

CHESS CHAMPION - 6 LEVELS £82.87 + VAT.

CHESS CHALLENGER - 10 LEVELS - £143.06 + VAT.

BORIS - MULTI-LEVEL TALKING DISPLAY £165.28 + VAT.



ELECTRONIC CHESS BOARD TUTOR £19.75 inc. VAT.


A special bulk purchase of these amazing chess teaching machines enables us to offer them at only £19.75 less than half recommended retail price. The electronic chess tutor is a simple battery operated machine that can actually teach anyone to play chess and improve their game right up to championship level. This machine is not only for total beginners but also for established players wanting to play better chess. Unit contains the electronic chessboard with 32 chess pieces, a 64 page explanatory booklet and a set of 32 progressive programme cards including 6 beginners cards, 16 check mate positions, 9 miniature games, 5 openings, 3 end games, 28 chess problems and 2 master games.

DRAUGHTS COMPUTERS

CHECKER CHALLENGER 2 LEVELS £43.98 + VAT. 4 LEVELS £80.09 + VAT.

The draughts computer enables you to sharpen your skills, improve your game, and play whenever you want. The computer incorporates a sophisticated, reliable, decision-making microprocessor as its brain. Its high level of thinking ability enables it to respond with its best counter moves like a skilled human opponent. You can select offence or defence and change playing difficulty levels at any time. Positions can be verified by computer memory recall. Machine does not permit illegal moves and can solve set problems. Computer comes complete with instructions, mains adaptor and twelve months guarantee.

PLAY DRAUGHTS/CHECKERS AGAINST THE COMPUTER



FOR FREE BROCHURES - SEND S.A.E

For FREE illustrated brochures and reviews on TV and chess games please send a stamped addressed envelope, and state which particular games you require information on.

Callers welcome at our shop in Welling - demonstrations daily - open from 9am-5.30pm Mon-Sat (9am-1pm Wed).

To order by telephone please quote your name, address and Access/Barclaycard number.

Postage and Packing FREE

AJD DIRECT SUPPLIES LIMITED, Dept. CT6 102 Bellegrove Road, Welling, Kent DA16 3DD. Tel: 01-303 9145 (Day) 01-850 8652 (Evenings)

OUR 1979 CATALOGUE

including the first edition of

STOP PRESS

- ★ Latest low prices
- ★ Fascinating new items
- ★ Special offers — a bargain on their own
- ★ Lowest prices ever for TTL
- ★ Free 45p worth of vouchers

**RAM
4116
16K x 1 250ns
£10.36
8 for £75.36**

**C.P.U.
8080
£5.84**

**EPROM
1702
£5.93**

**CATALOGUE
40p**

**EPROM
2708
£8.38**

CHROMASONIC electronics

DEPT. ET1 7, 56 FORTIS GREEN ROAD
MUSWELL HILL, LONDON N10 3HN
TELEPHONE: 01-883 3705/2289

USE OUR "ORDER RING" LINES

VAT INCLUSIVE PRICES. P&P 25p

MUSHROOM

4K INTEGER BASIC FOR NASCOM I

Full variable handling allows for integer and string (textual) variables from A0 to Z9, arranged as scalars or 1 or 2 dimensional arrays. Supports extensive string manipulation, logic, I/O and user CALL commands. Fast line search increases speed to make this very powerful BASIC ideal for real time applications and interactive games.

SUPPORTS

ABS
AND
ASC
CALL
CHRS
DATA
DIM
EXOR
FOR
GET
GOSUB
GOTO

HDPOS
IF
INPUT
LEFTS
LEN
LET
LIST
LOAD
MIDS
NEW
NEXT
NOT

ON GOTO
ON GOSUB
OR
PEEK
POKE
POS
PRINT
PUT
READ
REM
RESTORE
RETURN

RIGHT\$
RND
RUN
SAVE
SGN
SIZE
STEP
STOP
TAB
TO
TRACE

£13.50 on cassette with comprehensive manual.
Please specify monitor used.

MUSHROOM

7, BENTINCK AVENUE,
TOLLERTON,
NOTTINGHAMSHIRE

Heads, Tails Or Draw

Gives the odds A against B. If a draw is not required change step 50.

```
10 INPUT "ODDS:"A,"AGAINST"B
20 X=RND(A),Y=RND(B)
30 IF X>Y PRINT "HEADS"
40 IF Y>X PRINT "TAILS"
50 IF X=Y PRINT "DRAW"
60 GOTO 10
```

or:

```
50 IF X=Y GOTO 20
```

Golf Game

This program displays the trajectory of a golf ball aimed at a hole placed in a random position. A parabolic bounce has been simulated and the hole can only be hit on a bounce. The input Y is the stroke from 3 to 10 depending on how far away the hole is. The program has been made deliberately difficult. This can be made easier by changing step 20 to $F=2*RND(22);VDU F,15$. To speed up the game omit step 100.

```
10 VDU 0,12; FOR X=1 TO 100; NEXT X
20 F=980+RND(44);VDU F,15
30 A=961; INPUT Y (How hard the ball
                    is hit,3 to 10)
40 FOR W=1 TO 5
50 C=-1,D=-64, Z=Y
60 FOR X=1 TO (2*Y)+2
70 VDU A,18; B=A
80 A=A+2+(Z*D),Z=Z+C
90 IF Z=0 C=1,D=64
100 FOR S=1 TO 30; NEXT S
110 VDU B,32
120 IF Z-1=Y GOTO 140
130 NEXT X
140 Y=Y/2
150 IF A=F VDU F,121; PRINT "HOLE IN
    ONE";GOTO 170
160 NEXT W
170 FOR S=1 TO 1000;NEXT S;GOTO 10
```

Double Die

This displays the throw of two dice. To obtain the next throw press any key and carriage return.

```
10 VDU 0,12; C=275
20 FOR X=1 TO 2; A=RND(6), B=A
30 IF B>=2 B=B-2
40 IF B>=2 GOTO 30
50 IF B=1 VDU C,16
60 IF A>1 VDU C-132,16;VDU C+132,16
70 IF A>3 VDU C-124,16;VDU C+124,16
80 IF A>5 VDU C-4,16; VDU C+4,16
90 C=C+610;NEXT X
100 INPUT X; GOTO 10
```

Word Race

Three worms scuttle across the screen. The computer indicates win and draws. Something to take bets on.

```
10 VDU 0,12
20 A=321,B=641,C=961,T=0
30 Y=A;GOSUB 130;A=A+D
40 Y=B;GOSUB 130;B=B+D
50 Y=C;GOSUB 130;C=C+D
60 IF A=376 PRINT "A WINS";T=T+1
70 IF B=696 PRINT "B WINS";T=T+1
80 IF C=1016 PRINT "C WINS";T=T+1
90 IF T>1 PRINT "DRAW"
100 IF T=0 STOP
110 NEXT X
130 FOR Z=Y TO Y+7 STEP 2
140 VDU Z,113 VDU Z+1,114
150 NEXT Z
160 D=RND(2);D=D-1
170 VDU Y,32;RETURN
```

Maths Quiz

For those of you with jaded mental arithmetic due to excessive use of pocket calculators this program will help rejuvenate those dormant braincells. Range of numbers input lets you select the level of the quiz. (12 for kiddies and morons and 100 for intellectuals).

```
10 PRINT"MATHS QUIZ"; INPUT"RANGE OF
    NUMBERS"X
20 INPUT"ADDITION(A) SUBTRACTION(S)
    MULTIPLICATION(M) DIVISION(D)" K
30 IF K=A GOTO 70
40 IF K=S GOTO 100
50 IF K=M GOTO 130
60 IF K=D GOTO 160
70 P=RND(X),Q=RND(X),Y=P+Q
80 PRINT P,"PLUS",Q; INPUT "="Z
90 GOSUB 190; GOTO 70
100 Q=RND(X), Y=RND(X), P=Q+Y
110 PRINT P,"MINUS",Q; INPUT "="Z
120 GOSUB 190; GOTO 100
130 P=RND(X), Q=RND(X), Y=P*Q
140 PRINT P,"TIMES",Q; INPUT "="Z
150 GOSUB 190; GOTO 130
160 Y=RND(X), Q=RND(X), P=Y*Q
170 PRINT P, "DIVIDED BY",Q; INPUT "="Z
180 GOSUB 190; GOTO 160
190 IF Z=Y PRINT "CORRECT"; RETURN
200 PRINT "WRONG. THE ANSWER IS",Y;
    RETURN
```


We examine the facilities of the new Triton V5.1 BASIC Interpreter

The extended BASIC Interpreter contains several new commands which greatly increase the power of the Interpreter. These extensions enhance the editing features, improve the exit, allow stop and start of printout, and give the programmer greater access to all areas of memory and input output ports. They also allow the BASIC to interface with machine code subroutines.

Direct Command Extensions

The control C exit from the BASIC Interpreter has been extended to improve it. When control C is used during program execution, control is returned to the BASIC Interpreter rather than the Monitor. When control C is used during program coding or editing, control is then returned to the Monitor. Two extra control commands have been added to the keyboard routine. These are:

- Control S can be used to stop BASIC printout.
- Control Q is used to restart the BASIC printout again.
- During Control S, Control C can be used to exit to the Monitor.

Example

Enter the following program into Triton:—

```
10 FOR I = 1 to 10000
20 PRINT I
```



```
30 NEXT I
RUN
```

Now, while the program is printing on the screen, press the control and the S key together. This should stop the printout. To start the printing again press the control and the Q key and it should start. Now press control S again and when it stops press control C to exit to the monitor.

Edit

EDIT allows the programmer to EDIT a line of BASIC code. EDIT 100 will print statement 100 and place the cursor on the first character of the statement after the statement number. By typing in new characters, the old statement can be changed by replacement.

Not all characters have to be changed, by using control I and control H the cursor can be forward and backward spaced along the line to the required characters.

Example

Enter the following code

```
100 ABCDEFGHIJ
then EDIT 100
the Interpreter will print
100 ABCDEFGHIJ
```

The cursor is under the A. Now type in 123456, followed by LIST. The interpreter will print

TRITON BASIC

Our Triton running a BASIC program under the Humbug V5.1 monitor.

Now EDIT
This time type control I three times followed by ABCD
Return and LIST again. The Interpreter will print
100 123456
100 again
100 123ABCD

This example shows replacement with shorter code and partial replacement with extra code. It is also possible to delete characters using the Delete Key, insert by using the Escape key, followed by the character to insert, and to terminate the Edit part of the way along the line without deleting the rest of the line, by using control]

Example

Enter the following code

```
100 ABCDEFGHIJ
```

then EDIT 100

Now press the Delete key twice, this should delete the characters A and B.

Now press control I twice and position the cursor under the E

Now press the Escape key followed by W

This will place the W between the D and E

Now press Return followed by LIST

The line should now read

```
100 CDW
```

Repeat all the above instructions except after inserting the W press control] instead of Return.

The line should now read

```
100 CDWEFGHIJ
```

This example shows deletion and insertion and how the EDIT command can be used to change characters in the middle of a statement without completely retyping it.

Command Extensions

Five new commands have been added to the BASIC Interpreter together with spare commands and dummy entries to enable further user extensions.

CALL

The CALL command is used to call a machine code subroutine. CALL 8 will call the subroutine at decimal address 8. (This subroutine will clear the screen and return after the appropriate delay).

The subroutine location can be numeric, a variable or an expression.

```
10 LET A = 9432
```

```
20 CALL A + 48
```

This will call a subroutine at decimal location 9480 (For decimal to hexadecimal and hexadecimal to decimal conversions use the B monitor function).

PEEK

The PEEK command is used to copy any two bytes of memory into any of the Tiny BASIC Variables.

```
10 PEEK 8192, C
```

This statement will copy the contents of decimal Memory locations 8192 and 8193 into the variable C.

The memory address can be numeric, a variable or an expression.

Example

```
10 FOR I=0 TO 1024 STEP 16
20 FOR J=I TO I+14 STEP 2
30 PEEK J,D
40 E=O; IF D < O D=32767+D+I, E=I
50 A=D/4096, D=D-A*4096
60 B=D/256, D=D-B*256
70 C=D/16, D=D-C*16
80 IF E=I A=A+8
90 Z=C;GOSUB 200
100 Z=D;GOSUB 200
110 Z=A;GOSUB 200
120 Z=B;GOSUB 200
130 PRINT '
140 NEXT J
150 PRINT
160 NEXT I
170 STOP
200 IF Z < 10 PRINT #1,Z,;RETURN
210 VDU 0, 55+Z
220 RETURN
RUN
```

This example uses PEEK to enable BASIC to list the first part of the Monitor in a Hexadecimal Dump. Note the STEP 2 on statement 20 to index the address by 2 bytes each time.

POKE

The POKE command is used to write a numeric value, the contents of a variable or the result of an expression into any two bytes of memory (RAM).

```
10 POKE 7680,C+12
```

This statement will copy the contents of variable C plus twelve into decimal memory locations 7680 and 7681.

Example

```
10 FOR @(1) = 1 TO 26
20 POKE @(1) * 2 + 5249, @(1)
30 NEXT @(1)
40 INPUT 'ENTER ANY LETTER' @(1)
50 PRINT 'THE LETTER IS NUMBER',#1,@(1),'IN THE ALPHABET'
60 GOTO 40
RUN
```

This example uses POKE to initialize all the BASIC variables A to Z with 1 to 26.

READ

The READ command enables the BASIC user to read information from any port on his system into any of the Tiny BASIC Variables.

```
10 READ 16, @(1)
```

This statement will read a byte from port 16 and place it in the variable @(1). Note that the high order byte is zeroed and the data is placed in the low order byte.

The port number is the least significant byte of a numeric constant, a variable or an expression. The data must be read into a variable.

Example

```
10 READ O,A
20 IF A > 127 GOTO 10
30 READ O,A
```


Other BASIC Options

As well as the extra options just described, the Tiny BASIC Interpreter has four spare commands and six dummy entries in its various tables. These enable the user to test new BASIC commands before burning them into an EPROM.

Two of the spare commands are called SPRA and SPRB and are found in the main command table TAB2. They are used in BASIC by just coding

```
10 SPRA
20 SPRB
```

When these are encountered by the Interpreter, it branches to addresses in high core. For SPRA the interpreter jumps to 1FFD and SPRB to 1FFA. At these addresses there is room for three bytes to contain a jump instruction to the appropriate machine code extension. At the end of the machine code extension should be a jump to FINISH in the interpreter at address 090B.

The extensions can make full use of the interpreter routines using CALL's. Examples of the use of these routines can be obtained by examining VDU, PEEK and POKE in the BASIC listing.

Variables and expressions can follow the command as long as the machine code routine decodes these and leaves the DE register pair pointing after them.

```
10 SPRA 5,X+3
```

The parameters 5 and X+3 can be decoded using CALL EXPR in the BASIC. The two other spare commands are found in the function table TAB3. SPRC jumps to 1FF7 and SPRD jumps to 1FF4. These can be used to test new functions

```
10 B = SPRC(A,B)
```

This is an example of how SPRC could be coded.

Example

This example uses SPRC(A,B) to perform MOD(A,B). Using the P monitor function. Enter the following program:


```
1E00  CDBD09  MOD  TSTC  '(',ERR
1E03  28
1E04  13
1E05  CD5D07          CALL  EXPR
1E08  E5            PUSH  H
1E09  CDBD09          TSTC  ' ',ERR
1E0C  2C
1E0D  0A
1E0E  CD6108          CALL  PARNP
1E11  EB            XCHG
1E12  E3            XTHL
1E13  CDB008          CALL  DIVIDE
1E16  D1            POP   D
1E17  C9            RET
1E18  C33209  ERR  JMP   QWHAT
```

The using P again enter this jump instruction

```
1FF7  C3001E          JMP   MOD
```

Now enter the BASIC program

```
10 INPUT 'ENTER A NUMBER'A
20 FOR I=1 TO 10
30 B = SPRC(A,I)
40 IF B=0 PRINT #1,A'IS DIVISIBLE BY',I
50 NEXT I
60 GOTO 10
```



The guts of the Triton single board computer. The four labelled IC's centre right hold the Humbug Monitor, reviewed in June, and the Extended Tiny BASIC that we are reviewing in this article.

The dummy entries are found in TAB2, 3 and 6.

The names are coded as 7F7F7F7F and the addresses as FFFF. This enables the user with an EPROM Burner to modify these without needing new EPROMS. Do test any new routines VERY carefully before modifying your EPROMS.

```
40 IF A < 128 GOTO 30
50 A=A-128
60 B=A
70 IF A > 96 B=B-32;GOTO 90
80 IF A > 64 B=B+32
90 VDU O,B
100 GOTO 10
RUN
```

This example reads a character from the keyboard and prints it on the screen. Statements 10 and 20 check that no key is

TRITON BASIC

depressed by looping until the strobe bit (the high order bit) is off. Once this is so, the program loops on statements 30 and 40 waiting for a key to be pressed.

When a key is pressed, the strobe bit is removed and the input corrected for the shift bias of the keyboard. The character is displayed using VDU.

READ can also be used to examine the keyboard in 'Real Time'. This enables the user to write Interactive programs.

WRITE

The WRITE command enables the BASIC user to write a byte of information to any port on his system.

10 WRITE 64, D*2

This statement will write the least significant byte resulting from the expression D*2 to port 64.

The port number is the least significant byte of a numeric constant, a variable or an expression. The data must be read into a variable.

Example

```
10 PRINT 'THE TRITON LIGHT SHOW'
15 FOR J=1 TO 30
20 A=1
30 FOR I=1 TO 8
40 WRITE 3,A
50 A=A*2
60 NEXT I
65 NEXT J
70 FOR I=1 TO 500
75 FOR J=1 TO 75:NEXT J
80 WRITE 3,73
85 FOR J=1 TO 75:NEXT J
90 WRITE 3,146
95 FOR J=1 TO 75:NEXT J
100 WRITE 3,36
110 NEXT I
RUN
```

This example will run two patterns through the LED's on port 3.

Intercept Jumps

To allow the user further access to the BASIC, there are five jump instructions coded into RAM. When the BASIC gets to the end of TAB2, 3 or 6 without a match, it jumps out of the interpreter to one of these jumps before returning to the appropriate error or default routines. These jumps can be modified to jump to Machine Code routines before going to the error exit.

TAB2 jumps to address 1471
TAB3 jumps to address 1474
TAB6 jumps to address 1477

The other two jumps are for BASIC IN and BASIC OUT.

BASIC OUT jumps to address 147A before jumping to the monitor. BASIC IN jumps to address 147D before jumping to the monitor. If different routines are coded for these, the routines should not corrupt registers D and E. To return to BASIC use the RET instruction. Note that the jump instructions are restored in RAM only when the memory check is used.

NASCOM 1 KIT OR BUILT ★ SUPERBOARD II ON DEMO NOW ★ 2k BASIC FOR STANDARD NASCOM 1

**SUPERBOARD II
AVAILABLE NOW
AT ONLY £263.35**

COMPUKIT UK101 £303

BUILT — INCLUDES POWER SUPPLY

SORCERER, PET, APPLE II (B & W)

ALSO AVAILABLE



All prices inclusive — P & P free

N.I.C. MODELS

27 Sidney Road, London N22 4LT
01-889-9736

Please allow
up to 21 days
for delivery

COMPUSTAT

Continuous Stationery for the Micro Computer

All sizes of listing paper stocked.

Specialists in the preparation of Printed Continuous
Stationery — Design Service available —

Listing paper & OTC Stocked for the Anadex (9½") printer.

Phone or write for a quotation to Miss Michael

01-520 6038

63 ORFORD ROAD, LONDON, E17 9NJ.

MK 14 SOFTWARE

Suitable for most SC/MP configurations

MIKOM (commercial systems) Ltd.

Suppliers of software to Govt. Depts., Universities, Schools and Industry

NOW ANNOUNCE the 'MIKOM SERIES 600' — Programs to run in the 600 Bytes available on board the standard MK 14.

The MIKOM SC/MP HEX ASSEMBLER — Produces faster more efficient code than Basic, is more flexible, needs less memory and costs far less than Basic. Operates thru a hex keyboard and display — is much faster and more accurate than hand assembly — no tedious offset calculations to make — allows corrections and amendments in minutes — produces compiled code (no interpreter needed) — greatly simplifies programming — is indispensable to Professional and Amateur alike — hundreds of satisfied users.

COMPLETE WITH 21 PAGE MANUAL, INSTRUCTIONS AND CODING SHEETS
STILL ONLY £5 inclusive.

Cheque or P.O. to — MIKOM (commercial systems) Ltd., 1 Hythe Bridge Street, OXFORD. OX1 2 EW.

MIKOM SUBROUTINES — Select your own package from our very wide range of ready written subroutines including — Decimal complement and add — Decimal multiply and divide — various display formats — Decision table processors — Comparison tests — String and Block processing — Assorted tape interfaces — Block move instructions — Insert processing — and many others.

MIKOM COMMERCIAL PROGRAMS — Payroll suite; wage slips, PAYE, overtime, bonus, weekly summary sheet, coin analysis, etc. — weekly cash accounts — VAT and yearly accounts — % mark-up — stock keeping and taking — sales and invoicing — and many more all complete with documents and instructions.

MIKOM GAMES — The fabulous 'Mars Mission' test your skill as a navigator and astronaut — Try a game of Golf or Cricket — a very realistic greyhound derby, run your own tote — Have a flutter at roulette — a trip to the moon (and back if you're good or lucky enough!) — Clay pigeon shoot, experts can pull two barrels — all complete with score or log sheets.

THE MIKOM HEX KEYBOARD — Plug compatible with the MK 14 — Burgess micro switches for performance and long life — integral reset key — splash proof, easy to clean — light yet positive feel with audible click — sturdy easy to mount panel — easily modified to fit most kits — makes fast accurate keying easy — only £16 all inclusive.

THE MIKOM CABINET — Handsome real wood veneer, Oak, Mahogany or Teak — accommodates any kit — sleek ergonomic design — display window for up to 8 x 3/4 — positive form location on writing surface — overall size approx. 42 x 42 x 27 cms. — £24 inclusive.

FOR FURTHER DETAILS OF ANY OF THE ABOVE PLEASE SEND LARGE S.A.E. stating particular requirements and memory available.

WEST LONDON'S MICRO CENTRE

- Demonstrations
- Installation
- Systems design
- Programming
- Maintenance
- Finance

Authorised dealers for:—

PET	£460
Apple II.	£830
Nascom-1	£165
Nascom-2	£295

plus

- Floppy disk units
- Memory expansion
- Printers
- Printer interfaces
- Business software
- Games

***Come along and try a
Computer at***

Adda Computers, 17-19 The Broadway,
Ealing, London W5. Telephone: 01-579 5845/6
Open 09.00-18.00 Monday to Friday
10.00-16.00 Saturdays

adda

we add up to a great deal.

SDS-100



Technical Features

- 32,000 (or 64,000) Bytes of Random Access Memory
- 1,000,000 Bytes of Active, On-line Diskette Storage
- 12 inch Video Display Screen (24 lines of 80 characters)
- Capacity for 8,000 Bytes of Programmable Read Only Memory
- Full Upper and Lower Case Keyboard with Numeric Pad and Cursor Controls
- Z80 Central Processing Unit
- Parallel and Serial Input/Output Ports for peripheral equipment
- Key Lock Switch
- Video Blinking, Underlining, Reverse and Protected Field Enhancements
- Compatible with the Total System Business Software as well as C-Basic, Disk Fortran, Cobol and CP/M Disk Operating System

Complete with CP/M Operating System £4,260

PICO OYTE

65 VICEROY CLOSE
BRISTOL ROAD
BIRMINGHAM B5 7UT
021-440-5631

TEXTIE MK III word processor

For NASCOM 1 with B-BUG or T4 and a
Minimum of 8K Nasco RAM Expansion

: Powerful features :

- * WORD-WRAP ROUND ON VDU & PRINTER (automatically creates New Line)
- * LINE LENGTH ADJUST - VDU & PRINT
- * PRINTER MARGIN ADJUST
- * SCROLL THROUGH 147 LINE BUFFER
- * "LATERAL OFFSET" (moves VDU scan sideways for wider pages!)
- * POWERFUL EDIT FACILITIES
- * SELECTIVE & RELOCATABLE ERROR CHECKED CASSETTE READ AND WRITE
- * LATCHABLE SHIFT, CURSOR, ETC., ETC.

**ORDER TEXTIE MK III
TODAY DIRECTLY FROM
THE SOFTWARE PUBLISHING COMPANY
8A CHURCH SIDE, MANSFIELD, NOTTS
Telephone: (0623) 29237**

On Cassette with documentation and
listing Textie MK III sells at 10.00
(ten pounds) inc P/P Access Welcome
PLEASE STATE WHICH MONITOR YOU USE

This advertisement was entered, edited and printed using Textie
Mk III in the Nascom 1

computing today

WHAT TO LOOK FOR IN THE
OCTOBER ISSUE 21ST SEPTEMBER

LITTLE PEOPLE LOOSE IN CT?

Gnome Rule for microsystems? Is the ELF dwarfed by more batch systems with bigger expansion of chest and memory? Can any system costing as little as this really kick sand in the keyboard of the big boys and survive with no harm to its ROMs?

Vital questions such as these — and many more scintillating issues — are answered in next months CT review of the ELF II system.

TRITON TAKEN INTO ACCOUNT(S)

Yes folks you too can escape the bailiffs. No longer be haunted by heavy handed hammering on your portals at midnight because you spent the gas money on seed for the budgie. No more disguised creeping past the milkman because his money went on the electricity bill.

Keep track of your spending. Do you accounts on that Triton you bought with the money the missus put aside for a new carpet. It could save you the cost of the Triton in no time at all.

All you gotta do now is nick 50p for CT from the kiddies moneybox

A PROGRAM TO GROW EARS BY

Of all the planets in the Universe, Earth holds the Galactic Record for the highest number of Star Trek Programs produced in one decade. Only a little known asteroid circling Vega IV has anywhere the same magnitude rating (10).

It was way back in October 1979 though that the famous Computing Today magazine produced what is still the definitive version today. And all in 2½K as well! (present day GOTO commands use 5K remember) Copies of this program are still available from Trantor library at 1M5 credits. Of course those fortunate enough to have ancestors who bought the original

TOOLKIT FOR PET?

The most frustrating thing about yer average home micro, for anyone who has used mini's or mainframes, is the lack of utility type programs. You can get some on tapes or disks but not actually in the machine.

Well, Petsoft have done it again. They let me have the first "Toolkit" for a PET, it does all those useful little jobs like renumbering for you. In our October issue we reveal all about this superb piece of firmware.




Photo 1. The Arak VIII polyphonic keyboard controller.

Use your micro to control ETI's Arak VIII polyphonic keyboard controller. How? Read on! Tony Keane will explain all

The generation and manipulation of music is one of the most interesting applications of the computer. This article explains one method of doing this using the ARAK VIII as an interface, (see July edition of ETI).

The ARAK VIII is an eight channel polyphonic keyboard controller, primarily developed for use with music synthesizers, which gives out the necessary control voltages and gate signals for controlling a set of voices (to be explained). It also has an interface so that a computer connected to the unit can read all the notes being pressed, or write pitch and gating data to the voices.

How It Can Be Done

There are two basic ways that a computer can generate music. The first method is to generate all the waveforms within the computer and output them as a continuous set of samples through a D-A convertor. The problem is that these samples must come out every 25 μ s or faster which doesn't give much time to calculate each sample. The average microprocessor system would be unable to cope with one channel using this method let alone eight.

This leaves the second method which is simply to control the voices previously mentioned by providing the necessary control voltages and gate signals, which takes very little computer time.

What Is A Voice?

The standard interconnection of circuit modules shown in

COMPUTER MUSIC




Fig.1. Block diagram of a "voice".

Fig. 1 has become known as a voice. Correct adjustment of each module will allow the synthesis of almost any musical instrument, including a lot of instruments that don't exist.

The raw sound for the voice comes from the voltage controlled oscillator which will have a selection of output waveforms such as sawtooth, square or sine waves. This waveform is given a new tonal quality by the voltage controlled filter, and an envelope shape by the voltage controlled amplifier and transient generator combination. The voice is triggered and gives out a sound when the gate input goes high. The sound dies away when the gate input goes low. The rate at which the sound builds up and dies away is set on the transient generator. The other transient generator shown in the diagram allows a similar thing to be done with the tonal quality.

The pitch of the voice is altered with a control voltage normally scaled such that one volt will change the pitch through one octave. The tonal quality can be kept constant by injecting this same control voltage into the filter.

Real Time Clock

It is possible to create the necessary time length for each note to be played (crotchet, quaver etc.) using software time delays. This is however very inefficient since the times are generally greater than 1/10th of a second during which the computer would be totally tied up. The best method is to use a real time clock, which is simply an oscillator having the same period as the shortest note to be played (probably a

demi-demi-semi quaver). The computer uses multiples of this clock period to measure out the correct time for each note. A further advantage is that simply adjusting the clock frequency will change the play back rate of the music.

The Arak VIII As An Interface

Fig. 2 shows how the Arak VIII fits into the system. Data appears at the interface each time one scan of the keyboard has been completed. During data block (see Fig. 3) each of the eight channels are sequentially placed on the interface. The notes being pressed are represented by a 6 bit code called the note code, 000000 being the lowest note on the keyboard. This code is increased by one for each increase of one semitone.

All the computer has to do to read data from the keyboard is sample the states of the gate output and note code on the falling edge of data valid. The data valid signal can either be polled by the computer or used as an interrupt. Since the data comes out at a relatively low rate the interrupt method will give greater efficiency as the program can continue running between the data valid pulses.

When notes on the keyboard are pressed the voices will be activated and give out the corresponding sound. If the computer pulls the enable input high the note code and gate data lines go tri-state allowing the computer to inject its own data to control the voices.

The control voltages are stored in analog form and therefore require refreshing at least every tenth of a second.




Fig.2. Example of interfacing to three "voices".

COMPUTER MUSIC




Fig.3. Computer interface timing signals.

The gate data is however stored in a digital latch, and does not require refreshing. The data sample pulse in Fig. 3 shows when data for channel 2 is transferred from the interface to the output channels. To ensure that the data is correctly transferred data must be held constant during the data sample period for each channel.

Software

Software for music generation can be constructed at several levels of complexity. The most basic software simply makes one voice play a tune. The notes are stored sequentially in a section of the computers memory starting at location B. Two 8 bit memory locations are necessary for each note, the first representing the pitch and the second the length of time the note is to be played for. The flow chart in Fig. 4 shows how to sequence the data out of the memory using the real time clock as a time reference.

The memory locations that contain the note data can either be loaded by hand after the sheet music has been con-

verted into the correct binary coding or a program can be written which times each note relative to the real time clock and loads them into the memory as the music is being played on the keyboard, a sort of digital recording. Any mistakes that are made during the recording can be edited afterwards using software that allows the insertion and removal of notes.

Another way of loading up the memory is to allow the computer to compose its own music. The type of music obtained in this manner is entirely dependant on the musical constraints built into the software. No constraints will give music that is random in pitch and time, whereas with the right constraints the music can be made to conform to the normal harmonic and melodic structures.

Another dimension to the music can be added by giving the computer control of all the parameters in the voices so that it can adjust things such as attack, decay, filter cutoff, waveshape, volume etc.

With a large enough set of voices it is possible to reproduce a symphony or concerto provided you have enough memory.

Full details of Arak VIII are available from Arak Sound Ltd, Preston House, High Street, Crowthorne, Berks.

Fig.4. Sequencing data from computer memory to play a tune.





Photo 2. The rear panel of the controller showing the sockets for connection to external equipment.

Why wait for a kit computer when you can buy a fully built & tested Superboard III off the shelf?

Ohio Scientifics


SUPERBOARD III

Full 8K basic and 4K user RAM
Power supply and R.F. Converter P.O.A.

Built and tested

Now only **£188** + VAT

(Delivery within 7 days)



The machine can be economically expanded to assist in your business, remotely control your home, communicate with other computers and perform many of the tasks via the broadest lines of expansion accessories in the microcomputer industry. This machine is super easy to use because it communicates naturally in BASIC, an English-like programming language. So you can easily

instruct it or program it to do whatever you want, but you don't have to. You don't because it comes with a complete software library on cassette including programmes for each application stated above. Ohio Scientific also offers you hundreds of inexpensive programs on read-to-run cassettes. Program it yourself or just enjoy it, the choice is yours.

Features

- Uses the ultra powerful 6502 microprocessor
- 8K Microsoft BASIC-in-ROM
- Full feature BASIC runs faster than currently available personal computers and all 8080-based business computers.
- 4K static RAM on board expandable to 8K
- Full 53-key keyboard with upper-lower case and user programmability
- Kansas City standard audio cassette interface for high reliability
- Full machine code monitor and I/O utilities in ROM
- Direct access video display has 1K of dedicated memory (besides 4K user memory), features uppercase, lower case, graphics and gaming characters for an effective screen resolution of up to 256 by 256 points. Normal TV's with overscan display about 24 rows of 24 characters, without overscan up to 30 x 30 characters.

Extras

- Available expander board features 24K static RAM (additional mini-floppy interface, port adapter for printer and modem and OSI 48 line expansion interface.
- Assembler/editor and extended machine code monitor available.

Commands

CONT	LIST	NEW	NULL	RUN	
Statements					
CLEAR	DATA	DEF	DIM	END	FOR
GOTO	GOSUB	IF...GOTO	IF...THEN	INPUT	LET
NEXT	ON...GOTO	ON...GOSUB	POKE	PRINT	READ
REM	RESTORE	RETURN	STOP		

Expressions

Operators

-, +, *, /, ↑, NOT, AND, OR, >, <, <>, >=, <=, =
RANGE 10^{-32} to 10^{+32}

Functions

ABS(X)	ATN(X)	COS(X)	EXP(X)	FRE(X)	INT(X)
LOG(X)	PEEK(I)	POS(I)	RND(X)	SGN(X)	SIN(X)
SPC(I)	SQR(X)	TAB(I)	TAN(X)	USR(I)	

String Functions

ASC(X\$)	CHR\$(I)	FRE(X\$)	LEFT\$(X\$,I)	LEN(X\$)	MID\$(X\$,I,J)
					VAL(X\$)
				RIGHT\$(X\$,I)	STR\$(X)

Plus variables, arrays and editing facilities.

Fully built and tested. Requires only +5V at 3 amps and a videomonitor or TV and RF converter to be up and running.

What the magazines say

"A useful machine.....represents value for money"
Computing Today June '79

"The Superboard represents good value with plenty of potential"
Practical Computing June '79

"Certainly one of the most exciting (computers) on the present market"
Practical Electronics June '79

Dealer Enquiries welcome at Morgan St. address

Watford Electronics
33/35, Cardiff Road,
Watford, Herts.
Tel: Watford 40588/9

Videotime Products
56, Queens Road,
Basingstoke, Hants RG21 1REA
Tel: 0256 56417

Lotus Sound
4, Morgan Street,
London E3 5AB
Tel: 01-981 3993

Happy Memories

21L02 450 ns 83p 2114 450 ns £5.27 4116 300 ns £7.93
21L02 250 ns £1.01 2114 250 ns £5.75 2708 450 ns £7.72

TRS-80 16K Memory Upgrade Kit: £74.54

S100 16K 250ns Static RAM Kit: £207.64 With 4K £86.25 8K £126.71

Low Profile) Pins: 8 14 16 18 20 22 24 28 40
DIL Sockets) Pence: 11 12 13 18 19 21 23 30 40

Our new shop is now open at the address below. We shall be stocking a wide range of items to interest all those of you who are building or plan to build your own micro computer, why not pay us a visit? We are open from Mon to Sat 10 to 6 and often much later.

We stock a range of books covering fundamentals through to advanced topics (Like games)

We are NASCOM dealers for the South Coast.

Do-it-yourself with our range of wire wrapping aids and materials from the O.K. corral, or Box-it-yourself with a Vero enclosure after Soldering-it-yourself with Antex

Our stocks are rapidly increasing; please write or call for latest lists of available products. We welcome your suggestions for stock lines. What do you find difficult to obtain? (We know about buffers)

Please add 20p p&p to all orders less than £10 in value. Cheques or P.O.s payable to 'Happy Memories'. Access or Barclaycard orders may be telephoned 24hrs a day.



Prices quoted include VAT at 15%. Please adjust for any change in rate.



**19 Bevois Valley Road, Southampton,
Hants. SO2 0JP Tel: (0703) 39267**

TRS 80 SOFTWARE

from the leaders in innovative software

We were first for the TRS 80 with Re number Basic

We were first with Level III

We were first with the Howe Monitors 1, 2 and 3.

We were first with Newdos

And we are going to go on being first
SEND SAE FOR LIST

A. J. HARDING
(MOLIMERX)

28 Collington Ave.,
Bexhill, E. Sussex.
Tel. (0424) 220391



BUY A **Only £79.95**
microcomputer **+ VAT**
for less than
some TV games

- *Power Supply (6.3v AC) for ELF 11 £5.00
- *ELF 11 Deluxe Steel Cabinet (IBM Blue) £23.01
- *Giant Board Kit System/Monitor, Interface to/cassette, RS232, TTY, etc. £35.00
- *4K Static RAM board kits (requires expansion power supply) £89.44
- *Expansion power supply (required when adding 4K Rams) £19.00
- *ASC11 Keyboard Kits 96 printable characters, etc. £50.58
- *ASC11 D/lux steel cab (IBM Blue) £15.02
- *Kluge prototype board (build your own circuits) £12.83
- *66 pin Gold plated connectors (EA) £4.00
- *ELF Light pen writes/draws on TV screens £6.50
- *Video graphics board 32/64 characters by 16 lines on TV/monitor screens £69.95
- *ELF 11 Tiny basic on cassette £13.50
- *ELF 11 Bug/monitor powerful systems monitor/editor £13.50
- *T. Pitmans short course in programming manual (nil VAT) £4.00
- *T. Pitman short course on tiny basic manual (nil VAT) £4.00
- *RCA 1802 users manual (nil VAT) £4.00
- *On cassette test editor: assembler, disassembler (EA) £16.95

Save 10% and buy all three together.

All units can be supplied wired and tested

Send S.A.E. for comprehensive brochure

Add 15% VAT to all prices shown, plus £2, p & p over £20.

ELF 11 BOARD WITH VIDEO OUTPUT

STOP reading about computers and get your "hands on" an, ELF 11 and Tom Pitman's short course. ELF 11 demonstrates all the 91 commands which an RCA 1802 can execute, and the short course speedily instructs you how to use them.

ELF 11's VIDEO OUTPUT makes it unique among computers selling at such a modest price. ELF 11 is perfect for engineers, business, industry, scientific and educational purposes.

SPECIFICATION

- *RCA 1802 8 bit microprocessor with 256 byte RAM expandable to 64K bytes
- *RCA 1861 video IC to display program on TV screen via the RF Modulator
- Single Board with professional hex keyboard fully decoded to eliminate the waste of memory for keyboard decoding circuits
- Load, run and memory project switches
- 16 registers
- Interrupt, DMA and ALU
- Stable crystal clock
- Built in power regulator
- 5 slot plug in expansion bus (less connectors)

Name

Address

Postcode

Barclaycard/Access

To: NEWTRONICS 138 Kingsland Road,
London E2 8BY
Tel: 01-739-1582

Part 3 of our experimental series on microprocessors

This month we're going to creep a bit nearer to your actual genuine microprocessing, so that we'll have to make a few changes on the board. Remember to have the power switched off when you change anything on the circuit board — a useful extra safeguard is to short the + and — lines with a wire link. The first change this month is a minor one — remove the 250 uF which was used as C* and substitute a 25 uF in the same place (C20 to X2), with the negative connection on X2. If you had an LED connected up to monitor the clock pulse rate, you can remove it now because the clock pulse rate will be too fast to monitor in this way. The 2k7 which was the current limiting resistor for this LED can also be taken off the board. If you didn't monitor the clock pulse rate, there's nothing to change at that part of the board.

Speed Your Clock

Now with this much faster clock pulse rate, the effects of leakage should be negligible, and the 8060 should do exactly what its makers say it should. Obviously there are large differences between individual chips of the same type, which show up when such comparatively slow clock rates are used, and if you find that you have some odd effects persisting, you may have to use a smaller value of capacitance, 5 uF or less, as C* in the clock pulse generator circuit. Incidentally, the 8060 has its own built-in oscillator circuitry, but it's suitable only for fast clocking, and doesn't generate slow clock rates with a fast enough rise and fall time. We've used the 74LS132 because it has what is called Schmitt trigger inputs which can generate very fast changing waveform edges from slow-changing ones (Fig. 1).

With the alterations made and any shorting links removed, we can plug in to the power supply and prepare to go again. We can now briefly try the same routines as we used with the slow clock rate, but this time with no distractions and a lot faster.

Reset, and set all the DBS low. Cancel reset, watching for the very brief flash from DLED 4, DLED 5 (remember what these signalled?) Address 0001 is now displayed. PUSH, and release quickly, to get the brief flash of DLED 4, DLED 8 (remember?), and the system should now settle with the address 0010 displayed. If you hold PUSH down, you will see the address LEDs generating a binary count at a rate which is much slower than the clock pulse rate. You may also notice that each address is flashed twice — this is a peculiarity of the HALT instruction which you won't see repeated on other instructions. Also with PUSH continually depressed, you can see the alternate flashing of DLED 4, 5 and DLED 4, 8, making up the two parts of the HALT instruction.

With the faster clock pulse, we can make rather more sense of the DELAY instruction which can be programmed into the 8060. Reset, and arrange the data switches to 10001111. Cancel reset, and with address 0001 displayed, PUSH. Now, with address 0010 displayed, change the data switches to 00000001 and PUSH again. All the LEDs will extinguish, and the 8060 starts the delay count. At the end of the count, the next address 0011 will be displayed. Note the time for this delay cycle, and then measure the delay time when 00000010 is entered as the second byte of the instruction. When this faster clock pulse is used, there should be no outputs visible on the status LED's.

Naughty Bits?

Just to show an example of a different way of using a register, the next bit of investigation makes use of the SIN switch. Don't let it excite you, it means Serial in, and it connects to the input on pin 24 of the 8060. The serial input will place a bit into a register called the extension register, and this is done once by an instruction called Serial Input/Output (SIO). This extension register will hold 8 bits, one byte, and it right-shifts at each SIO instructions. As a bit is





Fig. 1. Clock pulses (a) pulse with slow rise and fall times, (b) effect of a slow rise time on a gate — oscillations break out during the slow rise time (this also happens during the fall time). (c) Using a Schmitt trigger gate to give very fast rise and fall times.

MPU's BY EXPERIMENT



(a)

A	B	Q
0	0	0
0	1	0
1	0	0
1	1	1

(b)

$$\begin{array}{r}
 \text{AND} \quad 1 \ 0 \ 1 \ 0 \ 1 \ 0 \ 1 \ 0 \\
 \quad \quad 1 \ 0 \ 0 \ 1 \ 1 \ 0 \ 0 \ 1 \\
 \hline
 = 1 \ 0 \ 0 \ 0 \ 1 \ 0 \ 0 \ 0
 \end{array}$$

Fig.3. AND-ing. (a) Gate and truth table (b) AND-ing pairs of bits in two bytes.

IMMEDIATE instructions. Each of these instructions is followed by a byte which represents the number that the instruction is to act on. Later in the series we'll look at how numbers from other parts of memory, or from outside the memory system, can be introduced; some of this work has to be done on the MK14.

New Instructions

The first of the IMMEDIATE instructions is LOAD IMMEDIATE, which means simply load into the accumulator register the number byte from the next position in the program memory. To do this, reset, cancel reset, and then switch up 11000100 on the data switches. This is the instruction code LDI, load immediate, on the 8060, and it must be followed by a byte of data. With this set up on the data switches, and the address 0001 showing, PUSH. Address 0010 now shows, and the 8060 is awaiting the number which is to be loaded into it. Load up a set of 1's by setting all the data switches to 1, and then PUSH again. Address 0011 will now show that the instruction has been carried out — but how can we prove it?

One partial proof is to copy the contents of the accumulator to the status register, so that at least the lowest three bits of the number can be checked. The status register contains 8 bits, of which the lowest three have outputs on flags 0, 1, 2 to which we have LED's attached. The other bits in the status register have no direct outputs, and have to be checked in different ways, as we'll see later. We can do the copying act by setting 00000111 on the data switches, followed by PUSH. The instruction byte is CAS — Copy Accumulator to Status, so that all of the status LEDs should be lit.

We can prove that the accumulator is full of 1's in another way, but this one involves losing the data (which at the moment is still stored in the accumulator, since it was only copied to status, not exchanged). There's an instruction which we've just used for exchanging the contents of the extension register with the accumulator. This will fill the extension register with 1's, which can then be shifted out by the SIO operation and counted. The procedure is as follows:

Switch SIN low, and set the data switches to 00000001. Now PUSH, so causing the registers to exchange. Now we can examine the contents of the extension register

by setting 00011001, which is the SIO instruction. PUSH, and the first 1 appears on the SOUT LED. Each of the next seven PUSH operations has the same effect, showing that there were eight 1 bits in the register, and the ninth PUSH should produce the 0 to which the SIN switch has been set, proving that we have now cleared the extension register.

There's another method of showing what's in the accumulator register which we've used before and will explain in detail later — this is the method we'll use from now on to show the accumulator contents. Load the accumulator with 1's again by using the 11000100 PUSH 11111111 PUSH sequence; this is necessary because the contents of the accumulator were exchanged with the contents of the extension register, and then shifted out. Set up 11001000, which is a STORE instruction (ST) that will cause the accumulator byte to be placed out on the data lines when a second byte follows. Use PUSH, and then set the switches to 00000001 and PUSH again. This should set all the DLED's to 1, though the DBS switches are not set this way — a proof that it's the contents of the accumulator and not the data input switches that we're looking at.

AND Now For Something

Now for something a trifle more ambitious. Reset, and then cancel reset. Set up 11000100, which is load immediate, PUSH, and follow by 10101010, PUSH. This has loaded the data number 10101010 into the accumulator. The next instruction 11010100 is AND IMMEDIATE, which instructs the 8060 to set up eight AND gates, to AND each bit in the accumulator with the corresponding bit of the next number byte which is fed in from memory. The AND operation is illustrated in Fig. 3; remember that 1 AND 1 is 1, 1 AND 0 is 0, 0 AND 0 is 0. With the AND IMMEDIATE (ANI) instruction code set up, PUSH and load the number to be ANDED, 10011001, PUSH again. The accumulator should now contain the result of the AND-ing, which should be 10001000, and we can check this by using the procedure which will soon become very familiar. Set up 11001000, PUSH, 00000001, PUSH. The readout DLED's should now display the accumulator number, 10001000, just as it ought to be.

These two instructions, load immediate and AND-immediate each take ten micro-cycles, therefore 40 clock pulses, to perform. This sometimes comes as a shock to microcomputer buffs who think that one clock pulse equals one instruction, and it also helps to explain why chips are so often updated to higher clock-pulse rates, or why two-phase clocks are sometimes used. One microprocessor, the Texas TMS9980, even has a four-phase clock. Next month, folks, more IMMEDIATE instructions.

P.E.T. NEWS

PET BOOM IN BRITAIN!

AUTHORISED PET COMMODORE DEALERS

Birmingham
Camden Electronics
021-773-8240

CPS (Data Systems)
021-707-3866

Taylor Wilson Systems
Knowle (056-45) 6192

Bolton
B & B Consultants
0204-26644

Bournemouth
Stage One Computers
0202-23570

Bradford
Ackroyd T/W &
Add M/C
0274-31835

Brentwood Essex
Direct Data Marketing
0277-229379

Bristol
Bristol Computer Centre
0272-23430

Sumlock Tabdown
0272-26685

Cambridge
Cambridge Computer
Store 0223-68155

Cardiff
Sigma Systems
0222-21515

Colchester
Dataview Ltd
0206-78811

Derby
Davidson Richards
0332-366803

Durham
Dyson Instruments
0385-66937

Edinburgh
Micro Centre
031-225-2022

Exeter
A.C. Systems
0392-71718

Grimsby
Allen Computers
0472-40568

Hemel Hempstead
Data Efficiency
0442-57137

Hove
Amplicon Micro Systems
0273-720716

Leeds
Holden 0532-459459

Liverpool
Dams Office Equipment
051-227-3301

Rockliff Bros
051-521-5830

London E2
Ragnorok Electronic
Systems 01-981-2748

**THE
PET 4K
COMPUTER
at
£450 (+VAT)
it's got to
be
Britains
best buy!**



Why the PET is the number one Personal Computer

The Self Contained PETS

The self contained PET models 2001-4 and 8 come complete with TV screen, keyboard and built-in cassette deck as well as the computer circuitry. They are simply plugged into any 13 amp mains and no special knowledge is needed for running standard programs — over 200 of which are available on cassettes.

The Big Memory PETS

The BIG MEMORY PETS contain the same main features as for the 2001-4 and 8 models except that they incorporate a full typewriter size keyboard and have larger internal memory of 16K and 32K bytes RAM respectively.

Professional Printers

High specification printers can print onto paper all the PET characters — letters, numbers and graphics. A tractor feed model has the advantage of accepting mailing labels, using standard pre-printed forms. The only connections required are an A/C lead and PET connecting leads. The PET is programmable, allowing the printer to format print and it accepts 8 1/2" paper giving up to four copies.

a total of 360K bytes are available in the two standard 5 1/4" disks. Only two connections are necessary — an A/C lead and PET interface lead.

Software and application areas for PET

There are a large number of programs that can readily be used with the PET. Personalised programming is available from many Authorised Dealers. Over 200 programs are now available from Commodore and other software suppliers for the PET. Popular program titles include Stock Control, Statistics, Payroll, Strathclyde Basic Course, Chess, Lunar Landing and Education Packs.

FOR THE SCIENTIST AND THE LABORATORY

PET has a comprehensive set of scientific functions making it a far superior tool to the best programmable calculators. PET interfaces directly with hundreds of laboratory instruments. PET is an ideal industrial and commercial controller.

FOR THE EDUCATIONAL WORLD

The extensive basic language makes PET an ideal tool for teaching computer programming. Programs can be written to "tutor" the user (pupil) in almost any discipline, including BASIC itself. And, of course, the PET can be used to take care of school records, exam results, attendance figures etc.

IN THE HOME

The PET is an extremely creative and instructive learning medium of the future for young and old alike. There are also large numbers of entertainment programmes available including chess and space games.

FOR THE COMMERCIAL USER

The Commodore PET offers for the first time a really cost effective business computer for use in Accountancy, Statistics, Stock Control, Payroll, Invoicing etc.



Phone about PET now!

**CALL YOUR LOCAL AUTHORISED DEALER or in case of difficulty contact:
COMMODORE SYSTEMS DIVISION
360 Euston Road, London. Tel: 01-388-5702**

London EC1
Sumlock Bondain
01-253-2447

London N14
Micro Computation
01-882-5104

London NW4
Da Vinci Computers
01-202-9630

London SW14
Micro Computer Centre
01-876-6609

London WS
Adda Computers
01-579-5845

London WC1
Euro-Calc 01-405-3113

London WC2
TLC World Trading
01-839-3893

Manchester
Cytek 061-832-7604
Executive Reprographic
061-228-1637

**Sumlock Electronic
Services 061-834-4233**

Matlock
Lowe Electronics
0629-2817

Morley, W. Yorks
Yorkshire Electronic
Services 0532-522181

Norwich
Sumlock Bondain
0603-26259

Nottingham
Betos Systems 0602-48108

Oxford
Orchard Electronics Ltd.
Wallingford (0491)-35529

Plymouth
J.A.D. Integrated Services
0752-62616

Preston
Preston Computer Centre
0772-57684

Reading
CSE Computers
0734-61492

Southampton
Business Electronics
0703-738248

Symtec Systems
0703-37731

Xitan Systems Ltd.
0703-38740

**Sunderland Tripoint
Associated Systems**
0783-73310

Woking
P.P.M.
Brookwood (04867)-80111

Petalect 04862-20727

Yeovil
Computerbits
0935-26522

North Scotland
Thistle Computers
Kirkwall (0856)-3140

Northern Ireland
Medical & Scientific
Lisburn (08462)-77533

CT MARKETPLACE

LCD CHRONO



We feel we've got to tell you carefully about this offer which we're introducing for the first time. Why? Because our price is so enormously lower than anywhere else you may suspect the quality.

The display is LCD and shows the seconds as well as the hours — and minutes — press a button and you'll get the date and the day of the week.

Press another button for a couple of seconds and you have a highly accurate stopwatch with hundredths of a second displayed and giving the time up to an hour. There is a lap time facility as well — and of course a back light.

Our Chrono comes complete with a high grade adjustable metal strap and is fully guaranteed.

£11.95

(Inclusive of 15% VAT and Postage).

To:
LCD Watch Offer
CT Magazine
145 Charing Cross Road,
London WC2H 0EE

Please find enclosed my cheque/PO for £11.95 (payable to CT Magazine) for my LCD Chronograph.

Name

Address

.....

.....

Please allow 28 days for delivery.

ALARM-CHRONO LCD



This new addition to our unbeatable selection of bargains is no ordinary LCD watch. It's a slim, multi-function, dual time chronograph alarm watch, no less.

This model will show hours, minutes, seconds, date, day of the week, stop watch, split time, alarm and alternate dual time zone — not all at once, of course. There is also a night light.

Hours, minutes, seconds and day of the week are displayed continuously, while the date will appear at the touch of a button. The day of the week is indicated by a flag. When used as a stopwatch, the maximum count is 0.1secs. short of thirteen hours.

£19.95

(Inclusive of 15% VAT and Postage).

To:
ALARM/CHRONO LCD WATCH Offer,
CT Magazine,
145 Charing Cross Road,
London WC2H 0EE

Please find enclosed my cheque/PO for £19.95 (payable to CT Magazine) for my Alarm/Chrono LCD watch.

Name

Address

.....

.....

Please allow up to 28 days for delivery.

EUROPE'S LARGEST SELECTION OF MICROCOMPUTER BOOKS, MAGAZINES AND SOFTWARE FOR THE HOBBYIST, EDUCATIONALIST, PROFESSIONAL AND RETAILER.

BOOKS

SUMMER HOLIDAY BONUS: for the purchase of 3 books or more, and paying by cheque, P.O. or cash, give yourself a 10% DISCOUNT!

Introduction to Microcomputers: by Osborne
Vol 0: Beginners Book £5.95
Vol 1: Basic Concepts £6.30
Vol 2: Some Real Microprocessors (without binder) £18.95
Vol 2: Some Real Microprocessors (with binder) £24.70
Vol 3: Some Real Support Devices (without binder) £11.95
Vol 3: Some Real Support Devices (with binder) £17.70
Updating subscription (6 issues) for Vol 2 £18.95
Updating subscription (6 issues) for Vol 3 £18.95
Updating subscriptions for Vol 2 & 3 £30.00
1 Updating issue (specify for Vol 2 or 3) £4.00
1 Binder (Specify for Vol 2 or 3) £5.75

6800 Programming for Logic Design £6.30
8080 Programming for Logic Design £6.30
Z80 Programming for Logic Design £6.30

More BASIC Computer Games (coming soon) £5.50
BASIC Computer Games (also see software section) £5.00
What To Do After You Hit Return £8.95
8080 Galaxy Game £6.95
SUPER-WUMPUS — A game in 6800 Assembler code & BASIC £4.25
Computer Music £6.75
Computer Rage (A Board Game) £6.95
Artist and Computer £3.95
Games with a Pocket Calculator £1.75
Games, Tricks & Puzzles for a Hand Calculator £2.49
Introduction to TRS-80 graphics £5.75
Take My Computer Please... (light hearted fiction) £3.25

Z80 Instruction Handbook £2.95
8080 Programmers Pocket Guide £1.95
8080 Hex Code Card £1.95
8080 Octal Code Card £1.95

Best of BYTE £8.95
Scelbi BYTE Primer £8.95
Best of Creative Computing Vol 1 £6.95
Best of Creative Computing Vol 2 £6.95
Best of MICRO (Issues 1-6 of Micro Magazine) £5.50

Z80 Assembly Language Programming (coming soon) £6.45
6502 Assembly Language Programming (coming soon) £6.45
Microcomputer Programming 6502 £7.95
6502 Applications Book (coming soon) £7.95
8080A/8085 Assembly Language Programming £6.45
6800 Assembly Language Programming £6.45
8080 Software Gourmet Guide and Cookbook £6.95
6800 Software Gourmet Guide and Cookbook £6.95
8080/8085 Software Design £6.75
6800 Tracer — An aid to 6800 Programme Debugging £3.95
Program Design £4.25
Programming Techniques: Simulation £4.25

PIMS — A Database Management System £5.95
Scelbi High Level Language + Supplements £15.00
Basex — A Simple Language + Compiler for the 8080 £5.50

Microprocessors from Chips to Systems £7.00
Microprocessor Interfacing Techniques £8.75
Z80 Microcomputer Handbook £7.50
TV Typewriter Cookbook £7.50
Cheap Video Cookbook £4.30
CMOS Cookbook £7.50
IC OP-AMP Cookbook £8.95
RTL Cookbook £4.25
TTL Cookbook £7.50
IC Timer Cookbook £7.50
Circuits Circuit Cellar £5.50
First Book of KIM £7.00

Introduction to Personal and Business Computing £4.95
Getting Involved with your Own Computer £4.75
Buyer's Guide to Microsoftware £2.40
How to Profit from Your Personal Computer £5.50
Microcomputer Potpourri £1.75
Hobby Computers are Here £3.95
New Hobby Computers £3.95
Understanding Microcomputers and Small Computer Systems £6.95

Instant BASIC £6.95
Basic BASIC £6.50
Advanced BASIC £6.00
My Computer Likes Me... When I Speak in BASIC £2.75
Calculating with BASIC £4.95
Users Guide to North Star BASIC £10.00
Introduction to PASCAL £3.95

Accounts Payable and Accounts Receivable £10.95
Payroll with Cost Accounting £10.95
General Ledger £10.95

Basic Software Library:
Vol 1: Business and Games Programs £17.50
Vol 2: Maths, Engineering and Statistical Programs £17.50
Vol 3: Advanced Business Programs £26.95
Vol 4: General Purpose Programs £7.95
Vol 5: Experimenters Programs £7.95
Vol 6: Miniature Business System £32.50
Vol 7: Chess/Medbi/Wdproc Programs £26.95

Some Common BASIC Programs £6.30
Computer Programs that Work (in BASIC) £2.55
32 BASIC Programs for the PET £10.10

8080 Standard Monitor £9.95
8080 Standard Editor £9.95
8080 Standard Assembler £9.95
Special Package: 8080 Assembler, Editor, Monitor £20.00
Bar Code Loader for 6800, 8080, Z80 and 6502 £1.75
Tiny Assembler for 6800 Systems £5.75
RA 6800 ML — An M600 Relocatable Macro Assembler £15.95
LINK 68 — An M6800 Linking Loader £5.50
MONDEB — An advanced M6800 Monitor Debugger £3.50

MAGAZINES

SUMMER HOLIDAY BONUS: For the purchase of 3 Magazines or more, and paying by cheque, P.O. or cash, give yourself a 10% DISCOUNT!

Magazine Subscriptions:	UK Price	Overseas Price
Subscriptions start within 3 weeks		
MICRO-6502 Journal (12 issues)	£12.50	£12.50
Personal Computing (12 issues)	£17.00	£17.00
Interface Age (12 issues)	£25.00	£25.00
Dr Dobbs Journal (10 issues)	£13.50	£13.50
Computer Music Journal (4 issues)	£11.00	£11.00
People's Computers (6 issues)	£8.50	£8.50
BYTE (12 issues)	£24.50	£24.50
Creative Computing (12 issues)	£16.50	£16.50
Kilobaud (12 issues)	£21.00	£21.00

Magazine Back Issues:	P.O.A.
Micro-6502 Journal	£1.50
Personal Computing	£1.95
Interface Age	£2.95
ROM	£1.95
Dr Dobbs Journal	£1.95
Computer Music Journal	£3.75
People's Computers	£1.95
BYTE	£2.95
Creative Computing	£1.95
Calculators and Computers	£1.95
Kilobaud (reprints only)	P.O.A.
73	£2.25
Magazine Storage Box (Holds 12)	£1.25

HOW TO ORDER

Please note our book magazine prices include postage and packing, but not insurance, if wanted add 12p for every £10. of books ordered. Make cheques, PO's etc. payable to: L.P. Enterprises.

CREDIT CARDS accepted
BARCLAYCARD VISA/ACCESS/DINERS CLUB/
AMERICAN EXPRESS
Phone: 01-553 1001 for Credit Card orders (24 hr answering service)

CONSUMER SHOW REPORT

Gerald Chevin

America where are you? A report from the States on their Consumer Show

For the most visitors to the Summer Consumers Electronics Show (SCES) staying one step ahead of the competition is the name of the game, for most people this is "the show" and they would not dream of missing it.

Dateline Chicago

The largest show of its kind in the world, the 13th annual summer CES included more than 900 exhibits in three major facilities — the Pick Congress Hotel, the McCormick Inn and three levels of McCormick Place itself. Registration was estimated at 50,000 by Wednesday closing day.

The exhibits themselves provided a fascinating look at the future — the clamour in McCormick Place arising from thousands of voices explaining products, thousands of fingers activating computer games, and thousands of TV sets running simultaneously.

There were 365 High Fidelity manufacturers exhibiting in the specially designed complex of sound rooms but, the key work seemed to be "Video". Video games, Cassettes and Discs, including X-rated movies were getting lots of attention from the retailers, and distributors who gear-up for the Autumn Season at this show.

Conventional Proceedings

Also, as a national convention the CES offered more than twenty hours of conferences and workshop seminars. One of the major speakers was Mike Toia of the Federal Communications Commissions Laboratory (FCC). He summarised a current state of the electronics industry like this: "We have a technological explosion, which means that any prediction you make will be surpassed by actualities".

Nevertheless, predictions were being made during the course of the three-day show. For example Charles Daigneault of Sharp Electronic Corporation, speaking to a group of retailers, projected 10,000 television sales for next year (USA). He also foresees multiple deluxe features, on deluxe television units as sales boost for the future. "Just what we used to call the family game room became the television room, so we will soon see a home entertainments centre, including video-cassette recorder, projection TV and Hi-Fi system".

The large growing market for video games was discussed by Donald Kingsborough of Atari Incorporated, "The rise in the age of the buyer as entire households become interested has catapulted retail sales of video games, nearly



700,000,000" he said, "in a growing market the buying influence is a family decision — our customers are 50% women", noted Kingsborough. In another area Mattel and Gerrold Electronics in October will jointly test play Cable Inc. Its purpose is to bring games and personal improvement programmes to cable television subscribers. A cable extension rented for less than ten dollars per month will enable a consumer to have a system connected to his home.

Video Discs

Magnavox launched the video disc era in December 1978, in Atlanta, and a limited number of video disc players all imported from its parent company PHILLIPS in Holland, was sold out within minutes. Magnavox soon launched production at its facilities in Tennessee, but could not make a dent in the Atlanta order backlog. In the first ninety days of sales an estimated 300 players were delivered, against firm orders for more than 1,000, and many of their reservations were accompanied by advance payment of the \$695 purchase price.

One million is a nice round figure and it seems to be a milestone for the infant home video software business, it is a number which should easily be passed this year according to even the most conservative industry estimates, software suppliers should easily sell more than one million pre-recorded family orientated tapes this year.

Adult X-rated or "Hard Core" should also sell about the same amount, not bad for a three year old business.

Video Games

At the time of the show, a very interesting situation arose. Texas-Instruments have introduced their new personal computer type number TI99/4, and were challenging the FCC with regard to their specification relating to modulator output voltage. TI were convinced that the FCC would change its ruling on the specific waver which up to now limits very strictly the level of output voltage from the RF modulator, consequently all TV game manufacturers have to comply to the FCC ruling. According to Robert Wiles of Bally the cost of this was something in the region of \$25 and if reflected on the retail price, could amount to a reduction of \$15 per game something of a dramatic figure.

There is also another major problem in relationship to television games; something like 146 different hand-held games on the market at this point. Most of the semi-conductor manufacturers facilities for producing custom chips for

various Video games have been completely absorbed by the ordering of the hand-held game manufactures consequently, it has become much more difficult to quickly get customised ROMs produced for extra games cartirdges so it would appear to be now a situation where only three major contenders. Atari already have an extremely popular home video computer game and plenty of software to go with it, Bally who announced their intentions to definitely stay in the TV games market, and a new-comer Mattell with their television which would appear to be the most sophisticated games system/home computer available (USA only). Since the show it can now be reported that the FCC have rejected the TI's challenge to their output voltage requirements, and the situation is now as before. Some of the features of the Texas Instrument's home computer are listed below:—

Console

CPU: 9900 Family, 16-bit microprocessor, plus 256-byte scratchpad **RAM MEMORY:** Total combined memory capacity: 72K bytes. Internal ROM memory supplied: 26K bytes. External ROM memory' (Solid State Software Command Modules) Up to 30K bytes each. RAM memory supplied: 16K bytes.

KEYBOARD: Staggered Qwerty, full travel style layout. Overlay for second functions.

SOUND: 5 octaves, 3 simultaneous tones plus noise generator. from 110 Hz to beyond 40,000 Hz.

The compucruise system for monitoring your cars thirst, speed, performance and just about anything else you want to know!

VIDEO RESOLUTION: 192 x 256

POWER: 110V, 60 Hz, 20W. Wall mounted console transformer.

SIZE: 25.9 x 38.1 x 7.1 cm (10.2 x 15.0 x 2.5 in).

WEIGHT: Less than 2.3kg. (5lbs)

DISPLAY: 13" color monitor. 24 lines of 32 characters.

OPTIONAL ACCESSORIES

Solid Stage Speech TM Synthesizer: Approx. 250 English words built in. Accessible from TI BASIC. Accommodates add-on-word modules to broaden vocabulary.

REMOTE CONTROLS: Eight-position with side-mounted action button.

Solid State Software TM Command Modules:

Variety of financial, educational and entertainment programs in rugged, reliable plug-in modules. Modules contain up to 30K bytes of extra ROM.

Hand Held Games


As previously mentioned, with something like 146 different hand-held games available, it is interesting to note that 'Simon' is still the most popular selling game in the USA. One of the most innovative new entries was the MICROVISION, a hand-held mini video game with its own built-in screen, Microvision comes with 'Block-Buster', really break-out in your hand, after you crash through the third row of bricks the ball speeds up and the game becomes a real challenge. Other plug-in ROM cartridges available for Microvision involve Bowling, Pinball, Connect-four, Star-Trek, Phaser-Strike and Mind-Buster, in all seven game cartridges are available to be played on the self-contained LCD screen. Another game, Sensor, is an electronic word game which combines the challenge and excitement of Scrabble with

3 FUNCTION COMPUTERIZED CRUISE CONTROL ENABLES DRIVER TO PRESELECT CRUISING SPEED. ENGAGE AT TRAFFIC FLOW, AND RESUME AT LAST SPEED BEFORE DISENGAGEMENT - OPERATES INDEPENDENTLY OF OTHER FUNCTIONS.

HIGH IMPACT HEAT RESISTANT ABS CASE IS MOUNTABLE FLUSH IN DASH, ON OR BELOW DASH. ALL HARDWARE PROVIDED FOR MOST INSTALLATIONS.

BRIGHT FIVE DIGIT BLUE FLUORESCENT DISPLAY CAN BE EASILY SEEN IN DAYLIGHT WHEN LED DISPLAYS ARE UNREADABLE.

BACKLIGHTED KEYBOARD



YOUR COMPUCRUISE IS SMART! IF YOU PUSH THE WRONG BUTTON IT WILL LET YOU KNOW BY DISPLAYING "ERROR".

DEPRESSING "M" KEY COMMANDS COMPUTER TO DISPLAY EITHER ENGLISH OR METRIC UNITS.

CALIBRATE FUNCTION ALLOWS OPERATOR TO COMMAND COMPUTER TO AUTOMATICALLY COMPENSATE FOR CHANGES IN WHEEL AND TIRE SIZES. ALSO TO CLIMATIZE FUEL SENSOR FOR INACCURACY DUE TO TEMPERATURE AND ALTITUDE.

Typical Accuracy:	
Clock	30 Sec/Month
Speed	1/2 MPH Max.
Distance	less than 1%
Fuel Functions	5%
Cruise Control	± 2 MPH

CONSUMER SHOW REPORT

computerised electronics, the object of Sensor is to guess your opponents (or the computers) word in the fewest turns. It can play with two people too. One player punches a word into the computer and the second player deduces the word, letter by letter as the computer flashes clues to the position and accuracy of the guessed letter. A "space age" sound signals a correct deduction. When a player deduces the complete word electronic jingles announce the triumph.

The "Big Trak" toy is a tractor and trailer unit, program controllable of course. Using its own length as a measure of the distance covered it can have up to sixteen program steps. This means that you can move both forward and backward up to ninety nine times the length of the toy. But that's not all! An auto repeat makes it do it again, and you can turn left or right at any angle up to a complete circle. All the operator has to do is estimate the distance of each section on the course he wishes to travel, program the system and let it go.

By using the eight programming commands and the variety of movements available you should be able to spend endless hours of fun chipping the paint from furniture and walls around the house. Be warned, it's coming to England!

As well as possessing all this sophisticated control Big Trak also carries a variety of sound and light "weapons" to knock out the baddies with and can dump loads from its trailer at command. Now is the time to invest in a carpet sweeper!

Automobile Accessories


Compucruise is an on-board navigational computer for automobiles, lorries, vans and recreational vehicles. It features cruise control, a fuel management system, a trip computer

and a multi-functioned quartz crystal time counter, plus many other functions.

The system uses a microprocessor that can be programmed to step through any sequence of commands: add, subtract, save data, display the results. But digital computers require single pieces of on-off pulses (bits) to work. A spinning drive shaft hardly conforms to this requirement, so transducers (Sensors) are used to convert the mechanical motion into a useable electrical signal.

The most important sensor is called the speed transducer. In the Compu-cruise system, four magnets are glued and taped to the drive shaft. As you move the drive shaft turns, allowing a magnet to pass in front of the coil. When it does, a small voltage pulse is induced in the coil, representing a full or partial turn. Since the drive shaft revolves in proportion to the movement of your car, a specific number of pulses will represent a specific distance.

How much distance? That depends on such things as the Rear axle ratio and tyre size. But that is where the computer power of the microprocessor comes in: before using any of these systems, you make a simple calibration. At the beginning of a measured mile, you push a button. That tells the computer to begin at zero. Then, as you travel the mile stretch, the computer counts the pulses. At the end of the mile, push the button again. The number of accumulated pulses are then stored as a reference base. If, for example, the computer counted eight hundred pulses for the measured mile, it knows that 400 represent one half mile 1,600 mean two miles, and so on, for any distance you travel and all this will automatically take tyre size and other variables into account, since they were part of the original calibration.





The Intellivision home entertainment unit from Mattel. It plays games as well as using software packages for education and home management.

O.K, the computer now knows how far you have gone, but it must also know your speed to do any useful work. To determine it accurately, the system computes it. Since the speed or — RATE — is equal to how long it took you to go a certain — DISTANCE — and the distance is known from the calibration, all that is needed to calculate the speed is the TIME ($R = D \div T$).

For that a quartz digital clock is used, it is simply a circuit that switches on and off at a precise rate, thousands of times a second. Other digital circuits within the clock divide the time down into thousandths, hundredths and tenths, and finally single pulses per second.

The computer can use any of these time bases as a "window" — a single moment in time to count distance pulses from the transducer. If, for instance it counts four pulses during a one tenth of a second window, that is equal to forty pulses per second; two hundred pulses per minute; one hundred and forty four thousand pulses per hour. And, from the original distance calibration, each pulse represented one foot of movement, then you would be moving 144,000 feet per hour or 27.3 miles per hour.

If all that has you confused, don't worry, the computer does it all automatically — every second — and shows the results on a digital display. But that's not all!

Besides the speed transducer, the Compucruise uses a fuel flow transducer, it too uses pulses that indicate the amount of fuel passing through to the carburettor. And once calibrated by entering in the amount of fuel you have consumed at your next fill-up, along with the capacity of your fuel tank, it is capable of carrying out just some of the following functions:—

- The fuel used since fill-up in gallons or litres,
- The fuel to arrival in gallons or litres,
- The fuel until empty in gallons or litres,

The current fuel consumption per hour in gallons or litres,

The average fuel consumption for a trip in gallons per hour or litres per hour.

The current fuel efficiency miles per gallon,

The current fuel efficiency in litres per hundred kilometres,

The average fuel efficiency for the trip in miles per gallon or litres per hundred kilometres.

Other functions it is capable of determining are by the use of sensors, outside, and inside temperature, in either Fahrenheit or Centigrade and Battery voltage. Another big plus is the computerised cruise control. It is more than a simple speed maintaining device. It establishes and maintains pre-selected road speed. You can tell the computer how fast you want to travel and it takes over. It also features a resume and traffic flow adjustment. Spectrum Marketing will be handling the Compucruise unit and their address is listed at the end of the article.

Translator Wars

Texas Instruments, as expected, introduced the first talking language translator. The language translator would retail for about \$250. TI expects to ship about 100,000 units in 1979, with first shipments designated for September. The translator can produce thousands of spoken phrases by linking together its vocabulary of about 500 spoken words. Its display only vocabulary is about 1,000 words. English and Spanish modules, priced at about \$50 each will be available in September, the French and German modules are scheduled to follow in the fourth quarter. Japanese and Chinese will be ready in early 1980; according to TI.

Basically, it has five different features:—

CONSUMER SHOW REPORT




A giant version of the Texas Instruments translator.

- 1) Phrase — gives you instant access to the most commonly used expressions and statements.
- 2) Phrase Link — lets you build up over a thousand things to say with fill-in blank statements and questions.
- 3) Translate — gives you translations for words entered in letter by letter.
- 4) Learn — helps you build vocabulary in sixteen useful categories such as food, travel, medical etc.
- 5) Memory Learn — drills you on pronunciation and translation of words you select.

However, this winter at the Last Vegas CES show Craig and Lexicon introduced the first "Language Translator" calculators. They are back with improved models, but will have a hard time catching up with Texas Instruments entry into the field. Craig is up-grading its new M.100 language translator to the status of a personal computer with a range of new software, some offering programs on Diet, Taxes and other non-translation topics. Included are capsules on First Aid, Bar Tending, Caloric content of food, Income Tax and Word Games.

The firm is also adding several new language capsules, including double capacity units in German, French, Spanish and Italian — all with 2,400 word capacity. Cherry Leisure, whose address appears at the end of this article, are handling the Craigs' M.100 language translator.

The Windert Watch Company have taken time out of the realm of the abstract. The Company's new talking watch, new at this show, is a first to break the sound barrier with the watch and clock that literally tells time in four languages. The "voice master" is the only such product on the market, and will be ready for selected stores before Christmas. By January 1980, the solar powered multi-functioned watch,



The internals of the Compucruise unit.

which will retail at about \$100 will be available nationwide.

The watch will announce hours, minutes, and seconds and can also pronounce an alarm message. The voice is flat and uninspiring. But we were assured that the demonstration model had only 16K of ROM whilst the final version will have 64K of ROM and the voice will be much more human then. Though diction and intonation should improve, the message remains the same: "Times up go, go, go" a snooze feature says "Now it is five minutes past" (the alarm time) "It is now ten minutes past" (the alarm time). The talking clock speaks four different languages: the watch can speak one of four. Both watch and clock will have LCD readout.

Once again the sheer electronic enthusiasm and paraphernalia were completely overwhelming, every aspect relating to consumer electronics. There is a general trend in High Fidelity products for example, to become much more remote control orientated this was demonstrated admirably by Sony, Hitachi and the Belgium company Barco.

Most manufacturers are rushing products through to enable them to have a hold on Christmas, the most lucrative time. Most of the show was apparently orientated around the Orient; Japanese companies really dominated the show in terms of stand space, and products available. But the American public seemed totally undaunted by this invasion and we look forward to seeing another pot-pourri of consumer electronics in January, 1980.

Spectrum Marketing,
Spectrum House,
48, Cambridge Road,
Barking, Essex.

Contact: Mike Alter.

Cherry Leisure U.K. Ltd.,
387, High Road,
Willesden,
London NW10.

Contact: Tony Varnals

WHICH BRITISH SYSTEM CAN OFFER THE FOLLOWING:

- ★ COLOUR — Aerial Input, Alphanumeric and Graphics
- ★ CEEFAX — BBC Television Teletext service
- ★ ORACLE — IBA Television Teletext service
- ★ BASIC — ROM — Resident Interpreter
- ★ MONITOR — Motorola 6800 Machine Code
- ★ VIEWDATA — Instant Information service

TECS:

TECHNALOGICS EXPANABLE COMPUTER SYSTEM

Prices start at
around £360



Rack Mounting and Tabletop Versions (illustrated).
The logical development everyone has been waiting for.
Please send large sae for details to:

TECHNALOGICS (DEPT. CT)

8 EGERTON STREET, LIVERPOOL
L8 7LY

PET 2001 SORCERER APPLE II

HIRE

FROM MICRODIGITAL

Now you can hire before you buy at no extra cost, at last you can be sure that the machine you buy, is the machine that best suits your needs. You may hire a microcomputer system for as little as £5.00 a day, peripherals available include, floppy disk units, colour and monochrome TV's, cassette recorders, etc.

Each machine is supplied with a selection of relevant software. Delivery is free if within the Merseyside area, otherwise charged at cost.

N.B.

The hire charges can be deducted from the cost of a new machine, no matter which machine you eventually purchase.

Please send for our free Price List.
25 Brunswick Street, Liverpool L2 0BJ
For further details and booking
Ring: 051-227 2535 (Paul Fullwood)



Gentlemen, the Petdisk has landed

£499

(single disk)

The U.K.-designed and manufactured Novapak disk system for Commodore's PET*, first seen at Compec '78, is (after extensive industrial evaluation), now available to the domestic user. Its unique saddle configuration continues the integrated design concept of your PET, with no trailing wires or bulky desk-top modules.

*Novapak may be used with any available RAM plane.

*May be used with latest versions of PET.

*Data transfer takes place at 15,000 char/sec — effectively 1,000 times faster than cassette!

*Storage capacity is 125 K/bytes (unformatted) on 40 tracks per diskette side.

*Dual index sensors permit dual-side recording for 250 K/bytes per diskette.

*Easy operation full-width doors prevent media damage.

*System expandable to ½ Mbyte on-line storage (4 drives).

*Dual head and 2D versions provide 2 Mbytes on-line.

*Industry Standard IBM 3740 recording format for industry-wide media compatibility offered only by NOVA-PAK.

*Dedicated Intel 8048 microprocessor and 1771 FDC minimise PET software overhead.

*Local hardware and software support available, including applications, packages for small business use.

The sophisticated Disk Operating System is disk-resident, which allows for future DOS-enhancements without hardware alterations. PDOS supports multiple file handling, allocating disk space dynamically to each as and when necessary. Any file may occupy from 1 to 600 sectors as required, at up to 16 non-contiguous locations on the disk. PDOS may be used alone, or within a BASIC program and offers user-specified password security for any file. Multiple access-modes simplify BASIC program construction, and the user may generate tailored DOS modules.

Novapak dual-disk system complete with PDOS and BASIC demonstration programs on disc £899 + VAT.

Available from the manufacturer or selected dealers.

Terms: 50% with order, balance on delivery.

Full cash with order is subject to 5% discount.

VAT-FREE Export arranged (Must be shipped by us).

analog electronics

47 Ridgeway Ave,
Coventry
Tel: (0203) 417761

READER SURVEY

Its time for good men (and women) to show us what you're made of. Or at least who you are and what you are. Computing Today is still a young magazine, and as such has a lot to learn about itself. The most important of which is how well you — our readers — think of us.

Overleaf you will find that most dreaded of pages — a form to fill in. Please don't pass on by but rather take your pen and wield it bravely in the name of a better CT! This is the chance you always wanted to tell us exactly what we should do with CT — editorally of course. Without your guidance how are we to know what you want from us?

Go on — spend a little time and ink on our behalf — improve your environment — make CT a better place to be and the world a safer place to live!



CT Survey
Modmags Ltd
145 Charing Cross Road
London WC2H 0EE

READER SURVEY

1) Please rate the following articles on a scale of 1 (awful) to 9 (brilliant). If you didn't read the feature, please score 0.

	SCORE	READ FULLY	SCANNED OVER	COMMENTS?
SCES SHOW REPORT				
TRITON BASIC				
NEWS				
COMPUTER MUSIC				
MPUs BY EXPT				
HEX CONVERTOR				
SOFTSPOT				
WORD PROCESSORS				
SPEECH RECOGNITION				
BRANDS				
CARTOONS				
BEGINNING BASIC				

Asterisk the single best feature in your estimation.

In addition please make any comments you would like to in the space provided. (Go on — don't be shy!)

ISSUE ISSUES

2) Do you consider yourself a regular reader?
If yes — how long?

Yes/No

3) If you've been a reader since No. 1, how does CT now compare with CT then?
Circle appropriate comment.

Much better Slightly better No different
Slightly worse Much worse Oh my God!

4) How long do you keep your past copies of CT?
1 month 3 months 6 months

5) How did you become a reader of CT?

By accident (?) Friends copy Advertisement
Other (please specify)

6) How many people read your copy?

PROJECTS

7) Have you ever built a project from CT?
If yes which — please list

1.
2.
3.
4.
5.
6.

8) Do you like the idea of projects in CT?

Yes/No

18) Is there anything you'd like to see appear as an offer in CT?

19) Have you every bought any goods from CT mail order?

Yes/No

If yes how was the service you received?

Good Fair O.K. Poor Bad Bloody Awful

Any problems? (Please specify below)

ADVERTISING

20) Do you read the advertisements in CT?
Frequently Occasionally Never

Yes/No

21) Have you ordered goods as a direct result of an advertisement in CT?

22) Have you any comments on advertisements in CT?

23) Are you employed in the computer field?

Yes/No

24) If so

(a) Does your employment entail the purchase recommendation on the purchase use of computers or associated hardware?

(b) Indicate the categories with which you are concerned giving, if possible, your company's annual expenditure in each

Microcomputers

Minicomputers

Peripherals

Software

Other (please state)

25) If you own/intend to purchase a microcomputer for the purpose of home use only please state your approx total expenditure

(a) In the last 12 months

(b) Planned for the next 12 months

READER PROFILE

These are personal questions which you may find objectionable. Please feel free to tell us to mind our business in that case. Answering them would help us greatly, however, and your co-operation would be appreciated. All info treated strictly as statistics and in confidence.

- 9) If there anything you would especially like to see as a project in CT?
Please specify.
- 10) In general, if there is a kit available for a project would you purchase that rather than assembling the components yourself?
Yes/No
- 11) Do you construct using P.C.Bs?
If yes, do you etch your own?
Yes/No
- 12) In general again, do projects constructed from CT work first time?
Yes/No
- 13) Do you as part of your job use a computer
If yes please indicate the areas which you work.
Business/Scientific/Research/Program Development/Hardware Develop/Education/other.
Please specify

- 26) How old are you?
27) Sex (Male/Female/Undecided)
28) Total annual income £
29) Do you hold any of these credit cards?
Barclaycard Access American Express
30) To what level were you in full time education?
C.S.E. 'O' Level 'A' Level
O.N.C. H.N.C. Degree

- 31) Does your course involve computing?
If yes please indicate area/areas covered
Hardware/Software/Design/Systems/other (specify)
Yes/No

- 14) Do you use a computer at home, or have access to a computer through friends/club etc. Yes/No

- 15) If you own or have access to a computer for personal use what machine is it:
PET/TRS-S0/Apple/Nascom/Research Machines/MK 14/Acorn/Sorcerer/Horizon/Tecs/77-68/
Triton/Superboard/AIM 65/Other (Please specify)

- 32) Do you find the computer facilities at your college useful?

- 16) If you have a "homebrew" machine for personal use please indicate the CPU
Z80/8080/6800/6502/9900/other (please specify)

- 17) Are you using, or hope to acquire, any peripherals. Please indicate which ...

PRINTER
DISK
MORE MEMORY
MODEM
SPEECH SYNTHESISER
GRAPHICS UNIT

OWN HOPE TO BEG BORROW OR STEAL

- 33) What machine/machines are available, briefly please

34) What do you like about CT?

35) and dislike?

36) Any suggestions for improvement?

37) Do you belong to a computing club?

Yes/No

38) Was you club featured in our July Club Survey?

Yes/No

39) If no please give brief details eg name and number of 1^o contact so we can update our list

40) On an arbitrary scale of 100 with CT scoring 50, please rate the competition against us.

	READ				RATING
	REGULAR	OFTEN	USED TO	NEVER	
RADIO CONSTRUCTOR					
WIRELESS WORLD					
TELEVISION					
VIDEO					
PRACTICAL COMPUTING					
PRACTICAL WIRELESS					
PRACTICAL ELECTRONICS					
PERSONAL COMPUTER WORLD					
BYTE					
ELEKTOR					
EVERYDAY ELECTRONICS					
COMPUTING TODAY					50
HOBBY ELECTRONICS					
E.T.I.					

On an arbitrary scale of 100 with E.T.I. scoring 50, please rate the competition against us.

Thank you for your time and patience.

TELEPHONE CHARGE CLOCK

SPECIAL OFFER

Have you any idea how much phone calls actually cost you?

You can work it out, of course, but do you ever bother? Bet you don't. The final cheque-book-splitting figure depends on the time of day, distance and how long you spend discussing the philosophical ramifications of decreased bacon sandwich availability in Colchester (or the weather).

You can save yourself a lot of calculation or guesswork by sending only £15.95 for the Monitel Telephone Charge Clock.

The unit sits underneath your telephone, plugs into any electrical socket and, when you're not using it, serves as a smart digital clock. It even comes in all the seven standard telephone colours.

It comes already programmed with Post Office charge bands. Moreover, it adjusts automatically to peak, standard and cheap rate periods and the charge includes VAT.

The clock takes its instructions from a punched card. When the rates change, Monitel will automatically supply a new card.

Win £50

When you get your Charge Clock, have a look at the punched card. Monitel are offering a prize of £50 for the first person to send us a punched card correctly programmed to operate a UK Monitel according to the following imaginary tariff structure:

Unit — 4.5p; Peak rate Monday-Friday 10 am-2 pm; Standard rate Monday-Friday 8 am-10 am and 2 pm-7 pm and Saturday 10 am-2 pm; Cheap rate other times.

Times	Peak	Standard	Cheap
L	30	60	90
a	20	40	60
b	10	20	30

ONLY
£15.95

(Rec. retail price £19.95)

inc. vat & postage



To: Telephone Charge Clock Offer
CT Magazine
145, Charing Cross Road
London WC2H 0EE

Please find enclosed £15.95 for my Telephone Charge Clock.


Name

Address

Colour

Offer closes Sept. 31st. Please allow 14 days for delivery.

* SPECIAL OFFER * SPECIAL OFFER * SPECIAL OFFER * SPECIAL OFFER * SPECIAL OFFER



Are you hexed with number systems? Build this '1'

In many digital systems information is handled in groups rather than as individual bits. These groups are called words and they vary in size according to the needs of the particular job. If it is necessary to display or calculate using the normal decimal digits, a four digit binary word (four bit word) would be needed to represent each single decimal number. A four-bit binary word gives 16 possible different combinations. For a decimal number we only need ten, so the largest six combinations are ignored.

The number 0 is represented as 0000, 1 as 0001, 2 as 0010, 3 as 0011, 4 as 0100 and so on. This is called binary coded decimal or BCD and is used in many digital applications such as digital frequency meters, digital multi-meters, calculators, etc.

As the job required of the digital system becomes more complicated, word lengths are increased. This gives the circuit the ability to handle more complex numbers by manipulating single words. The most common word length in microprocessors is eight bits. The eight bit word is called a byte and contains 256 different combinations. In the bigger microprocessor and smaller computers a word length of 16 is used, while full-scale computers use word lengths of 32 or even 64 bits! This is all very fine for computers, but for mere mortals like ourselves calculating with 64 digit numbers can become a little tiring!

This project was designed to assist the newcomer in getting used to the hexadecimal and binary number systems. It can also be used by those working out opcode (micro-processor instructions) from binary numbers.

Some mini-computers and microprocessors, such as the 2650, have their instructions written in the form of binary numbers, with some of the digits missing. Depending upon the particular variation of the instructions required, the

missing 0s and 1s are filled in. When the total binary word has been formed it must be converted into hexadecimal form for keying into the microprocessor. A relatively large program for a microprocessor might have one or two thousand opcodes to be evaluated — this is one application where the binary to hex converter could be put to good use.

Construction

The entire trainer is made on a single printed circuit board and construction is fairly non-critical.

Start by mounting the resistors on the PCB. Next, mount the capacitors, with the exception of the big 470 uF electrolytic. Be sure to orientate the tantalum capacitors correctly. If they are not marked with a +ve symbol they will probably be the type marked with coloured bands and a dot. With the dot facing towards you and the leads pointing down the positive lead is usually the one on the right. The IC's and displays should be soldered onto the board using reasonable care not to overheat the pins. Make sure they are orientated correctly also. If they are installed incorrectly and the board is powered up, they will probably be destroyed. The pads for the IC's are relatively close together and care should be taken to avoid bridging solder to adjacent pads.

The LED's and diodes can be fitted next and once again make sure these are put in the right way around.

The voltage regulator IC should be mounted onto a heatsink and secured to the PCB by a single nut and bolt. Insulation between the regulator and heatsink is not needed but some type of thermal paste compound should be used.

Mount the regulator first and then solder its leads onto the board, this avoids straining these solder joints. Fit the remaining electrolytics and wire links. Often cut-off resistor leads can be used for these links. All that remains is to fit and wire the switches and power sockets. The board requires an external DC supply, the regulator makes sure the IC's get the correct voltage. The DC supplied to the board should be greater than about seven volts.

HEX CONVERTER

HOW IT WORKS

As this voltage increases, the regulator dissipates much of the excess power in the form of heat and this is why the heatsink is necessary. On 12 V the regulator on the prototype gets quite hot, but not excessively. The board requires 450 mA worst case, so some of the bigger battery eliminators should do the job well. The socket for the power input can be a bit tricky to work out. The centre point on the socket is usually negative. Solder a wire from the centre terminal to the negative pad on the PCB. This is the pad not connected to the diode. The positive terminal on the socket is the terminal connected to the outside of the plug. This should be connected to the PCB pad that connects to the diode. If in doubt, connect the battery eliminator into the socket and check with a multimeter.

Almost any type of toggle switch will work in this project. Find a set of contacts that are open when the switch is in the up position, and wire these to the PCB pads as shown in the diagram.

Using It

Before applying power to the board check the capacitors, LEDs and IC orientations. When the board has been completely checked it can be tried out. Place all the switches in the up position and apply power. Immediately the seven segment displays should show '00'. As the toggle switches are changed the LEDs will light and the displays should change to indicate the correct hexadecimal number corresponding to the binary number shown on the LEDs.

The heart of the circuit consists of the two 9638 ICs. These are BCD to hexadecimal seven segment decoder-drivers. On receipt of a low on the clock input-pin 3, they load the binary word present on their inputs into latches, decode them into hexadecimal numbers and drive the appropriate segments in the FND500 displays. The binary number is reloaded into the input latches each time the clock input is taken low.

The 555 timer IC is operating as an astable multi-vibrator and generates a pulse used to trigger the clock input. The repetition rate is around 5 kHz, determined by the two 1k resistors connected to pin 7 and the 0.1 uF capacitor connected to pin 5 of the timer.

The inputs of the 9368's are connected via 1k pull-down resistors to zero volts to ensure the inputs stay low when the toggle switches are in the open position. When the binary number is selected, by closing the appropriate toggle switches, these input lines are taken high.

LED's are used to display the binary number and are connected to the toggle switches via 220R current limiting resistors.

A 7805 voltage regulator IC has been included on the board to allow the circuit to be run from a variety of DC supply voltages.






Fig.1 The circuit diagram for the converter.




The photo shows the switch wiring method used.

Fig.2 Component overlay. See Fig.3 for switch connection details.



HEX CONVERTER



The Hexadecimal Number System

We've already mentioned that a four bit binary word had sixteen different combinations. If we defined sixteen characters and let them be equal to these sixteen combinations we would write any four bit binary word using a single character.

This is the basis of the hexadecimal number system. The first ten digits are the same as in BCD, i.e: the normal decimal numbers. The six extra combinations not used in the BCD system are given the characters A, B, C, D, E and F. The number sequence would therefore be 1, 2, 3, 4, 5, 6, 7, 8, 9, a, b, c, d, e, f and would then continue 10, 11, ... 18, 19, 1A, 1B, 1C, 1D, 1E, 1F, 20, ... and so on.

A byte can be written as a two digit hex (hexadecimal) number, which is considerably shorter and more convenient. Nevertheless the relationship between binary and hexadecimal is not obvious at first and converting from binary to hex can become a tedious business, especially if the binary numbers are getting rather large.

Fig.3 Switch wiring. Note that the wires are soldered onto the PC pads provided for this purpose.

Owing to the size of the PCB being bigger than that of the page we are unable to print it in this issue. Foil patterns are available from our offices, please send an SAE to us marked "FOIL PATTERNS" for your copy.

PARTS LIST

Resistors

R1-R8, 17, 18 1k Ω
R9-R16 220R

Capacitors

C1, 2 100n polyester
C3, 4 6u8 16V tantalum
C5 470u 25V electrolytic

Semiconductors

IC1, 2 9368
IC3, 4 FND500
IC5 555
IC6 7805

D1 EM401 or equivalent

LED1-LED8 red LEDs (TIL 209)

Miscellaneous

SW1-SW8 SPST toggle
SK1 9V power socket

BUYLINES

The IC's and seven segment displays used in the project should be generally available but we understand that Technomatic have supplies if you encounter any difficulties. They are at 17 Burley Road, London NW10 1ED.

THE NEW STANDARD IN MICROCOMPUTER POWER

SIMPLICITY. SOPHISTICATION.

 **apple II PLUS**
AT
MICRODIGITAL



Apple II Plus

APPLE-II PLUS will change the way you think about computers. That's because it is specifically designed to handle the day to day activities of education, business, financial planning, scientific calculation, and entertainment. APPLE-II PLUS is appealing and comfortable (like other appliances that make your life easier), and it brings to personal computing a new level of power through hardware and software sophistication.

The APPLE-II PLUS is faster, smaller and more powerful than its predecessors, and it's easier to use too, because of advanced, built in features like:

*PALSOFT

A fast, extended 10K BASIC with 9-digit precision and graphics extensions.

*HIGH RESOLUTION GRAPHICS

On a matrix of 280X192 individually addressable points.

*AUTO-START ROM

With power on boot of application programs, reset protection and improved screen editing.

*INTERNAL MEMORY EXPANSION TO 64K BYTES

For big system performance at a low cost.

*EIGHT EXPANSION SLOTS

To let the system grow with your needs.

Apple Pascal

APPLE PASCALTM is the new extension to microcomputer power.

PASCALTM incorporating UCSD PASCALTM, offers extended features in a complete interactive package employing today's most sophisticated structured programming language. It provides advanced capabilities that boost performance and cut development time for large business, scientific, and educational programs.

This software package provides the most powerful set of tools yet available for the microcomputer programmer.

*EDITOR

A fast, screen-oriented editor for program development and word processing applications.

*COMPILER

Standard PASCAL plus full set of extensions for strings, disc files, graphics and system programming. Hi-res graphics "Turtlegraphics": as originated at MIT. INIT turtle, PENCOLOR, TURNT, TURN, MOVE, TEXT GRAF.

GOTOXY procedure for cursor addressing. FUNCTION Keypress tells whether character available. Library routines include: RANDOM, RANDOMIZE, PADDLE, BUTTON, TTOUT, KEYPRESS etc.

*RELOCATABLE ASSEMBLER

Permits relocatable assembly language routines to be generated and linked to Pascal programs.

*SYSTEM UTILITIES

Includes desk calculator-performs basic calculations and parameter — allows examination and modification of system environment

Floppy Disks

Gives your system immediate access to large quantities of data. The subsystem consists of an intelligent interface card, a powerful Disk Operating System and one or two mini-floppy drives.

Features

- * Storage capacity of 116 kilobytes/diskette.
- * Data transfer rate 156K Bits/second.
- * Individual file write protection.
- * Powered directly from Apple II.
- * Full disk capability with systems as little as 16K bytes of RAM.
- * Fast access time — 600 m sec (max) across 35 tracks.
- * Powerful disk operating software.
- * Load and store files by name.
- * BASIC program chaining.
- * Random or sequential file access.

Floppy Disk Subsystem		
Nett	Vat	Total
425.00	63.75	488.75
Second disk drive and connecting cable		
375.00	56.25	431.25

Parallel Printer Interface Card

Allows you to connect almost any popular printer to your Apple. A BASIC program can produce hard-copy output as easily as it prints to the TV monitor screen. Command interpretation and printer control details are handled by the firmware built into the card, to eliminate user programming requirements.

Nett	Vat	Total
110.00	16.50	126.50

Communications Interface Card

Allows your Apple to "talk" (though a modem) with other computers and terminals over ordinary telephone an load programs over the phone, send messages to remote terminals or access your office computer from the comfort of your home.

Nett	Vat	Total
110.00	16.50	126.50

High Speed Serial Interface Card

Allows Apple to exchange data with printers, plotters and computers in serial format at up to 19.2 K Baud.

Nett	Vat	Total
110.00	16.50	126.50

Speechlab Voice Recognition Card

Allows the Apple to recognise a spoken vocabulary of up to 32 user-selected words. The computer can be programmed to perform any task desired upon recognition of a key word.

Nett	Vat	Total
165.00	24.75	189.75

Prototyping Card

Provides the User with a means of building up experimental circuitry for the Apple computer. The 2 1/4" x 7" double-sided board includes a hole pattern that accepts all conventional integrated circuits and passive components. Documentation includes a complete system bus description to aid the interface designer.

Prototyping Card		
Nett	Vat	Total
18.00	2.70	20.70

Carrying Case

The Apple is truly portable and this padded vinyl, leather look case protects your Apple in transit and makes it easier to carry.

Carrying Case		
Nett	Vat	Total
25.00	3.75	28.75

Apple Pascal System

A recommended configuration for developing and using Pascal application programs.

	Nett	VAT	Total
APPLE-II PLUS, 48K RAM	960	142.50	1092.50
FLOPPY DISK system	425	63.75	488.75
PASCAL extension card			Ring for price.

Apple Software Bank Vols. 1-5 (5 disks) FREE

Other Prices

	Nett	VAT	Total
8 x 4116 RAMS 16k Bytes	100	15.00	115.00
Joystick	20	3.00	23.00
Diskettes	3	0.45	3.45
10 C13 Cassettes	4.44	0.66	5.10
Dolphins B.D.80	595	89.25	684.25
TRENCOM-100 incl. interface	295	44.25	339.25
AXIOM micro Printers	349	52.35	401.35
AXIOM graphics Printers	699	104.85	803.85

Books

	Nett	VAT	Total
Apple operators manual	5.50		
Applesoft extended			NO VAT ON THESE ITEMS
Basic manual	4.00		
Basic tutor	4.00		
6502 programming manual	7.50		
6502 hardware manual	7.50		

PART EXCHANGE

Pet owners', trade up to an Apple at MICRODIGITAL. We can allow up to £300 for your old PET against the cost of a new Apple II.

MICRODIGITAL

25 BRUNSWICK STREET, LIVERPOOL L2 0BJ.
Mail Order: 051-236 0707 Other Departments: 051-227 2535



electronics today

international

What to look for in the Oct issue: On sale Sept 7th

SPEECH COMPRESSOR

For anyone out there using the airwaves, this ingenious circuit will enable you to increase your average power to peak power ratio considerably — thereby "upping" your talk power! And it doesn't use RF compression either.

REACTION TESTER

Single PCB construction with auto-start and random interval times built in. Readout is in 1/100 secs on two "jumbo" LED displays. All adds up to a pretty nifty little game does it not? Don't be slow picking up ETI next month!

LM 10 APPLIED

Next month Ray Marston attempts to fill the issue with applications — some of which you couldn't ever have dreamed of — for his new champion chip, the amazing LM 10. See how close he gets to making it in the October issue of ETI.

CABLE TESTER

No it is not as simple as it sounds. You should know us better than that by now. This little unit will test any type of audio hook-up wiring — or indeed any conceivable cable. Each wire is tested, in sequence, for open-circuit or short to earth (or other wires), and then visual indication of the state of each is provided. OK?

Audiophile amp

Now you've all seen magazine projects for hi-fi amplifiers before. We've done several ourselves! However, we believe that NO-ONE — not even ETI — has produced a design anywhere near this quality before. Specifications include a noise figure of 83dB for the phono input, and a pre-amp distortion of 0.015%.

The power amp produces over 60W at 0.04% THD with particular attention having been paid to "open-loop" performance such that TID is negligible. Hum and noise — 110dB for the power amp. Listening tests played a huge part in settling the final design too.

The system is modular such that either the pre-amp or power amps can be utilised separately. Put them together and you have the best sounding magazine amplifier ever! Full details next month.

Analog delay

Since the advent of CCD (charge coupled devices) you could be forgiven for believing that all other methods of obtaining a time delay on a signal have curled up and died.

This is simply not so, and next month Tim Orr takes time off from String Thing to explain this largely unknown flourishing field.

RADIO CONTROLLED


Of course you've all built our radio control project out there haven't you? No? ... Oh.

Well the reason why not could simply be that you haven't seen this article yet. Written by Geoff Chapman — one of the few real experts in the field, it illustrates the different types of model that can be operated by R/C and how to get them operational!

Full of the kind of detail you'd spend years of lost patience gathering.

Fig 1. The flowchart for the Hangman game.

In its present format this program will play the game of Hangman with two people. One person is required to enter the word to be guessed and the other tries to guess it before he is "Hanged". The program has been written in PET BASIC but can be easily modified to run on any machine that uses a memory mapped display. Memory requirements are about 2K for the program. Because our printer is unable to handle the PET graphics several points must be noted about the cursor movements.



Line 100: The '3' is the CLR character.
 Line 180: Insert HOME, 12 DOWN.
 Line 220: Insert HOME, 5 DOWN.
 Line 270: Insert HOME, 2 DOWN, 1 RIGHT.
 Line 310: Insert HOME, 2 DOWN, 3 RIGHT.
 Line 350: Insert HOME, 2 DOWN, 5 RIGHT.
 Line 390: Insert HOME, 2 DOWN, 7 RIGHT.
 Line 430: Insert HOME, 2 DOWN, 9 RIGHT.
 Line 470: Insert HOME, 2 DOWN, 11 RIGHT.
 Line 890: Insert HOME, 2 DOWN, 1 RIGHT.
 Line 990: Insert HOME, 16 DOWN.

Room has been left at the start of the program, i.e. before Line 100 for the user to add in a random choice of words so that only one person plays the game at a time.

Fig 2. The program listing for the BASIC game of Hangman.

```

100 PRINT"ENTER A SIX LETTER WORD IN FORMAT"
110 PRINT"LETTER 1,2,3,4,5,6"
120 INPUT A$,B$,C$,D$,E$,F$
130 Q=0
140 PRINT"3I HAVE A SIX LETTER WORD"
150 PRINT
160 PRINT
170 PRINT"##### "
180 PRINT"ABCDEFGHIJKLM"
190 PRINT
200 PRINT"N O P Q R S T U V W X Y Z"
210 G=0:U=0
220 PRINT"WHAT IS YOUR LETTER"
230 INPUT V$
240 IF V$=A$ THEN260
250 GOTO280
260 U=U+1
270 PRINT" ";A$
280 IF V$=B$ THEN300
290 GOTO320
300 U=U+1
310 PRINT" ";B$
320 IF V$=C$ THEN340
330 GOTO360
340 U=U+1
350 PRINT" ";C$
360 IF V$=D$ THEN380
370 GOTO400
380 U=U+1
390 PRINT" ";D$
400 IF V$=E$ THEN420
410 GOTO440
420 U=U+1
430 PRINT" ";E$
440 IF V$=F$ THEN460
450 GOTO480
460 U=U+1
470 PRINT" ";F$
480 IF V$="A" THEN M=0
490 IF V$="B" THEN M=2

```

```

500 IF V$="C" THEN M=4
510 IF V$="D" THEN M=6
520 IF V$="E" THEN M=8
530 IF V$="F" THEN M=10
540 IF V$="G" THEN M=12
550 IF V$="H" THEN M=14
560 IF V$="I" THEN M=16
570 IF V$="J" THEN M=18
580 IF V$="K" THEN M=20
590 IF V$="L" THEN M=22
600 IF V$="M" THEN M=24
610 IF V$="N" THEN M=80
620 IF V$="O" THEN M=82
630 IF V$="P" THEN M=84
640 IF V$="Q" THEN M=86
650 IF V$="R" THEN M=88
660 IF V$="S" THEN M=90
670 IF V$="T" THEN M=92
680 IF V$="U" THEN M=94
690 IF V$="V" THEN M=96
700 IF V$="W" THEN M=98
710 IF V$="X" THEN M=100
720 IF V$="Y" THEN M=102
730 IF V$="Z" THEN M=104
740 POKE(33248+M),32
750 IF U>G THEN940
760 U=G
770 Q=Q+1
780 IF Q=1 THEN POKE33172,100:POKE33173,100
790 IF Q=2 THEN POKE33173,76:POKE33133,101
800 IF Q=3 THEN POKE33093,101:POKE33053,101
810 IF Q=4 THEN POKE33053,79:POKE33054,99
820 IF Q=5 THEN POKE33055,80
830 IF Q=6 THEN POKE33095,118:POKE33096,117
840 IF Q=7 THEN POKE33135,78
850 IF Q=8 THEN POKE33136,77
860 IF Q=9 THEN POKE33175,78
870 IF Q=10 THEN POKE33176,77:GOTO890
880 GOTO220
890 PRINT" ";A$;" ";B$;" ";C$;" ";D$;" ";E$;" ";F$
900 POKE33099,25:POKE33100,15:POKE33101,21:POKE33102,39:
    POKE33103,18
910 POKE33104,5
920 POKE33106,4:POKE33107,5:POKE33108,1:POKE33109,4
930 GOTO990
940 IF U=6 THEN970
950 G=U
960 GOTO220
970 POKE33099,25:POKE33100,15:POKE33101,21
980 POKE33103,23:POKE33104,9 :POKE33105,14
990 PRINT"DO YOU WANT TO PLAY AGAIN?"
1000 GET J$:IF J$="" THEN1000
1010 IF J$="Y" THEN1030
1020 END
1030 CLR
1040 GOTO100

```


computing today

technical book service

What Is A Microprocessor ?

2 Cassette tapes plus a 72 page book deal with many aspects of microprocessors including Binary and Hexadecimal counting, Programming etc. **£10.75.**

NEW:

Adams, C. BEGINNERS GUIDE TO COMPUTERS AND MICROPROCESSORS WITH PROJECTS **£5.60**

Understanding building programming and operating your own microcomputer.

NEW:

Albrecht, B. BASIC FOR HOME COMPUTERS. A self teaching guide **£4.75**

Shows you how to read, write and understand basic programming language used in the new personal size microcomputers.

Albrecht B. BASIC. A self teaching guide (2nd edition) **£4.50**

Teach yourself the programming language BASIC. You will learn how to use the computer as a tool in home or office and you will need no special maths or science background.

Alcock, D. ILLUSTRATING BASIC **£2.60**

This book presents a popular and widely available language called BASIC, and explains how to write simple programs.

Altman, I. MICROPROCESSORS **£10.65**

Gives a general overview of the technology design ideas and explains practical applications.

Altman, L. APPLYING MICROPROCESSORS **£12.00**

Follow volume which takes you into the second and third generation devices.

Aspinall, D. INTRO TO MICROPROCESSORS **£6.40**

Explains the characteristics of the component.

NEW:

Barden, W. Z-80 MICROCOMPUTER HANDBOOK **£7.65**

Barden, W. HOW TO BUY AND USE MINI-COMPUTERS AND MICROCOMPUTERS **£7.75**

Discusses these smaller computers and shows how they can be used in a variety of practical and recreational tasks in the home or business.

Barden, W. HOW TO PROGRAM MICRO-COMPUTERS **£7.00**

This book explains assembly language programming of microcomputers based on the Intel 8080, Motorola MC6800 and MOS Technology MCS6502 microprocessor.

Barna, A. INTRODUCTION TO MICRO-COMPUTERS AND MICROPROCESSORS

£7.50

Provides the basic knowledge required to understand microprocessor systems. Presents a fundamental discussion of many topics in both hardware and software.

Bibbero, R. J. MICROPROCESSORS IN INSTRUMENTS AND CONTROL **£12.45**

Introduces the background elements, paying particular regard to the dynamics and computational instrumentation required to accomplish real-time data processing tasks.

Lancaster, D. TV TYPEWRITER COOK-BOOK **£7.75**

An in-depth coverage of tv typewriters (tv's) the only truly low cost microcomputer and small display interface.

Lancaster, D. CHEAP VIDEO COOK-BOOK **£6.50**

Lesea, A. MICROPROCESSOR INTERFACING TECHNIQUES **£8.50**

NEW:

Leventhal. INTRO TO MICROPROCESSORS **£16.70**

NEW:

Lewis, T. G. MIND APPLIANCE HOME COMPUTER APPLICATIONS **£4.75**

NEW:

Libes, S. SMALL COMPUTER SYSTEMS HANDBOOK **£5.75**

The Primer written for those new to the field of personal home computers.

NEW:

Lippiatt. ARCHITECTURE OF SMALL COMPUTER SYSTEMS **£4.35**

NEW:

Moody, R. FIRST BOOK OF MICRO-COMPUTERS **£3.85**

(the home computer owners best friend).

McGlynn, D. R. MICROPROCESSORS — Technology, Architecture & Applications **£8.40**

This introduction to the 'computer-on-a-chip' provides a clear explanation of the important new device.

McMurrin, PROGRAMMING MICRO-PROCESSORS **£5.50**

A practical programming guide that includes architecture, arithmetic/logic operations, fixed and floating point computations, data exchange with peripheral devices, computers and other programming aids.

NEW:

Nagin, P. BASIC WITH STYLE **£4.00**

Programming Proverbs. Principles of good programming with numerous examples to improve programming style and producing.

NEW:

Ogden. SOFTWARE DESIGN FOR MICRO-COMPUTERS **£7.00**

NEW:

Ogden. MICROCOMPUTER DESIGN **£7.05**

Peatman, J. B. MICROCOMPUTER BASED DESIGN **£20.40**

This book is intended for undergraduate courses on microprocessors.

NEW:

Bursky, D. MICROCOMPUTER BOARD DATA MANUAL £5.40

Bursky, D. MICROPROCESSOR DATA £5.40

Includes complete description of the processor. Support circuits, Architecture, Software, etc.

Coan, J. S. BASIC BASIC £7.50

An introduction to computer programming in BASIC language.

Coan, J. S. ADVANCED BASIC £7.30

Applications and problems.

NEW:

Duncan. MICROPROCESSOR SOFTWARE ENGINEERING £13.50

NEW:

Freiberger, S. CONSUMERS GUIDE TO PERSONAL COMPUTING AND MICRO-COMPUTERS £5.50

NEW:

Frenzel, L. GETTING ACQUAINTED WITH MICROPROCESSORS £7.10

This is an invaluable book for those who want to know more about hobby and personal computing.

Gilmore, C. M. BEGINNERS GUIDE TO MICROPROCESSORS £4.75

Gosling, R. E. BEGINNING BASIC £3.25

Introduces BASIC to first time users.

Graham, N. MICROPROCESSOR PROGRAMMING FOR COMPUTER HOBBYISTS £7.00

Haviland, N. P. THE COMPULATOR BOOK £6.20

Building super calculators and minicomputer hardware with calculator chips.

Heiserman, D. L. MINIPROCESSORS FROM CALCULATORS TO COMPUTERS £4.85

Hilburn, J. L. MICROCOMPUTERS, MICROPROCESSORS, HARDWARE, SOFTWARE AND APPLICATIONS £16.95

Complete and practical introduction to the design, programming operation, uses and maintenance of modern microprocessors, their integrated circuits and other components.

Klingman, E. MICROPROCESSOR SYSTEMS DESIGN £16.95

Outstanding for its information on real microprocessors, this text is both an introduction and a detailed information source treating over a dozen processors, including new third generation devices. No prior knowledge of microprocessors or microelectronics is required for the reader.

Kemeny, J. G. BASIC PROGRAMMING £6.10

A basic text.

Korn, G. A. MICROPROCESSOR AND SMALL DIGITAL COMPUTER SYSTEMS FOR ENGINEERS AND SCIENTISTS £19.00

This book covers the types, languages, design software and applications of microprocessors.

Rao, G. U. MICROPROCESSOR AND MICROPROCESSOR SYSTEMS £20.50

A completely up-to-date report on the state-of-the-art of microprocessors and microcomputers written by one of the leading experts.

Rony, P. H. THE 8080A BUGBOOK: Micro-computer Interfacing & Programming £8.15

The principles, concepts and applications of an 8-bit microcomputer based on the 8080 microprocessor IU chip. The emphasis is on a computer as a controller.

Scelbi. 6800 SOFTWARE GOURMET GUIDE AND COOKBOOK £8.80

Scelbi. 8080 SOFTWARE GOURMET GUIDE AND COOKBOOK £8.80

Scelbi. UNDERSTANDING MICROCOMPUTERS £8.60

Gives the fundamental concepts of virtually all micro-computers.

NEW:

Schoman, K. THE BASIC WORKBOOK £3.70

Creative techniques for beginning programmers.

NEW:

Sirion, D. BASIC FROM THE GROUND UP £6.00

Soucek, B. MICROPROCESSORS AND MICROCOMPUTERS £18.80

Here is a description of the applications programming and interfacing techniques common to all microprocessors.

NEW:

Spracklen, D. SARGON £9.75

A computer chess program in Z-80 assembly language.

NEW:

Tracton. 57 PRACTICAL PROGRAMS & GAMES IN BASIC £6.40

Programs for everything from Space war games to Blackjack.

Waite. M. MICROCOMPUTER PRIMER £6.25

Introduces the beginner to the basic principles of the microcomputer.

Ward. MICROPROCESSOR / MICRO-PROGRAMMING HANDBOOK £6.00

Authoritative practical guide to microprocessor construction programming and applications.

NEW:

Veronis. MICROPROCESSOR £12.85

Zaks, R. INTRODUCTION TO PERSONAL AND BUSINESS COMPUTING £8.50

Zaks, R. MICROPROCESSORS FROM CHIPS TO SYSTEMS £8.50


Note that all prices include postage and packing. Please make cheques, etc, payable to Computing Today Book Service (Payment in U.K. currency only please) and send to:

Computing Today Book Service,
P.O. Box 79,
Maidenhead, Berks.

**A pictorial
view of
the 1979
Microcomputer
show held
last month
in London**






This is Prestel




Top to bottom: A view of the crowded and overheated hall. The TECS system in its various formats, PO approval has been given for Prestel, see News. Another Nascom system, with thoughtful viewer.

ONLINE EXHIBITIONS

Right: An ELF II displaying its graphics potential. Not quite what you might think, this is the UK 101. Another ELF, this time with case and full ASCII keyboard see our review next month.



Above and left: A DEC intelligent terminal running on a Plessey systems sixteen bit machine. Intense concentration on the face of a young Nascom user.



**Word
Processing
is the
talk of
the town;
we reveal
the state
of the art**




Above, left and right are two of IBM's wordprocessor stations. Below is a section of the futuristic lower hall used for the show.




ONLINE EXHIBITIONS

Another view of the lower hall at Wembley. The "greenhouse" belonged to Dictaphone.



One of Wang's terminals, their seminar presentation raised more than a few chuckles.

A Logica VTS word processor terminal.



A Data Logic VT1303 WP station being demonstrated.

Pet Expansion



Computhink
Dual drive
minifloppy

Complete with 4K disk operating system in ROM, plugs into Expandapet memory. Adds 15 new commands to Pet's Basic to give full disk extended Basic. Loads 8K in 2.6 seconds. Automatic reorganisation of free space. Utility Disk

£833 + V.A.T.

Expandapet memory

Powered by Pet's own powersupply and mounted internally in 5-10 minutes without special tools.

16K..... **£261** + V.A.T.

24K..... **£320** + V.A.T.

32K..... **£374** + V.A.T.

All units are fully built and tested.

Apple II



Apple II was the original with full colour high resolution microcomputer Basic, and it is still the best. With a very wide range of expansion available, including disk drive, interface cards, voice recognition card, light pen and many others.

Apple II has been well tried and approved by the public (over 200,000 sold) because of its thoroughly professional design and high quality engineering. You cannot get better value for money. Please send us a large s.a.e. for further details.

With 16K user RAM only **£820** + V.A.T.

16K upgrade kit **£85** + V.A.T.

LOTUS SOUND

4 MORGAN STREET
LONDON E3 5AB

TELEPHONE: 01-981 3993
TELEX: 261426 ATN. LOTUS SOUND

Extend your BASIC with our series

We will start off this month by looking at last month's homework, which may have increased the aspirin intake of some of you. The problem required that you write a program which will ask for the name of a month to be input, accept an answer as a string and then search through the input string for the occurrence of the letter R.

Searching Strings

If an R is found, the program should say that YOU CAN EAT PORK IN your input month. If no R is found, the opposite message shall be output. The problem in effect boils down to checking through an input string to find a particular character. If the character is present, an output to this effect is given; otherwise the opposite output is printed.

Consider the following:—

```
40 PRINT "INPUT MONTH"
50 INPUT M$
130 L=LEN(M$)
140 FOR N=1 TO L
150 Q$ = MID$(M$,N,1)
160 IF Q$ = "R" THEN 200
170 NEXT N
180 PRINT "YOU CANNOT EAT PORK IN";M$
190 END
200 PRINT "YOU CAN EAT PORK IN";M$
210 END
```

Here you are asked to input the name of a month (lines 40 and 50) then a check is made to find the length of the input string (M\$) (line 130) which is assigned to variable L.

We now need to make a check character by character to test for the chosen character (R here). To do this we set up a FOR NEXT loop in N between 1 and L. We then extract the Nth character of M\$ (line 150) and assign this to Q\$. This character is then checked to see if it is an R. If it is, we branch to line 200 and PRINT:—

"YOU CAN EAT PORK IN";M\$

If the character is not an R we branch back to check the next character of M\$ (line 170).

At first sight this program appears to work quite well, but if we look at the test data specified last month then we run up against a problem. The test data was:—

- 1) MAY
- 2) OCTOBER
- 3) MARCH
- 4) ENGLAND

If these were entered we would get the following as output:

- 1) YOU CANNOT EAT PORK IN MAY
- 2) YOU CAN EAT PORK IN OCTOBER
- 3) YOU CAN EAT PORK IN MARCH
- 4) YOU CANNOT EAT PORK IN ENGLAND

Using DATA Strings

The problem as set last month doesn't require the computer

to pass judgement upon the location, but upon the month. Unfortunately, we have not given the computer any method of "knowing" whether the input string is a month or any other word, the computer just treats it as a string. If we want only months to be dealt with, then we have to tell the computer how to check this out.

One solution is to give the computer a list of the 12 acceptable inputs in a DATA statement and then check the input M\$ against each of these to seek a match before going on to the rest of the program. This is done in the program below by lines 60–120 and 300–320. Apart from these additions, the program is the same as the previous one.

```
40 PRINT "INPUT MONTH"
50 INPUT M$
60 RESTORE
70 FOR C=1 TO 12
80 READ T$
90 IF T$=M$ THEN 130
100 NEXT C
110 PRINT M$;"IS NOT A MONTH NAME"
120 END
130 L=LEN(M$)
140 FOR N=1 TO L
150 Q$=MID$(M$,N,1)
160 IF Q$="R" THEN 200
170 NEXT N
180 PRINT "YOU CANNOT EAT PORK IN";M$
190 END
200 PRINT "YOU CAN EAT PORK IN";M$
210 END
300 DATA JANUARY, FEBRUARY, MARCH,
    APRIL
310 DATA MAY, JUNE, JULY, AUGUST,
    SEPTEMBER
320 DATA OCTOBER, NOVEMBER, DECEMBER
```

I leave you to make it work. Carrying on from last month, we will now go on to look at some more string functions.

LEFT\$(STRING,L)

LEFT\$ is similar to MID\$ in that it allows you to extract a substring from the string specified in the brackets, but here the substring will consist of the first L characters of STRING eg.

```
10 A$="TIMOTHY"
20 B$=LEFT$(A$,3)
30 PRINT B$
```

The output from this program segment would be TIM which is a substring (first 3 characters here) of the string TIMOTHY.

RIGHT\$(STRING,L)

This function works the same as the previous one except that it extracts the last L characters from the string in the brackets, eg.

BEGINNING BASIC

```
10 B$=RIGHT$("BULLOCK",4)
20 PRINT B$
```

Here the output would be LOCK.

STR\$(X)

This function converts the numeric value of the contents of the brackets into a string, eg.

```
10 A=126
20 A$=STR$(A + 12)
30 PRINT A$
```

Here the PRINT statement would output a value of 138 for A\$. (This should not be confused with a value 138 assigned to a numeric variable — the 1, 3 and 8 in A\$ are treated purely as characters.)

The contents of the brackets in a STR\$ statement can be any constant, variable or numeric expression.

VAL (STRING)

This function has the opposite effect to the previous function. It converts a string with a numeric value back into numbers which can be assigned to a numeric variable, eg.

```
10 A$="13"
20 B$="15"
30 C=VAL(A$+"."+B$)
40 PRINT C
```

Here the value of C printed will be 13.15 because the + sign in a string expression does not mean add in the normal arithmetic sense, it means that the various strings should be lined up after each other in the order given (this is called concatenation). Similarly, we could have added a line 25 to the above segment as follows :

```
25 C$=A$+"."+B$
```

This would have been quite acceptable and C\$ would have taken the value of 13.15 but this time it would have been a string and not a number.

CHR\$(X)

This function returns the single character string which has X as its ASCII code. The value of X in this function is in decimal and has a range 0-127 (as there are 128 ASCII codes). The variable X in the brackets may be replaced by any constant, variable or numeric expression. For example,

```
10 FOR X = 65 TO 90
20 PRINT CHR$(X);
30 NEXT X
```

This would print out all the letters of the alphabet in order from A to Z as the numbers 65-90 are the decimal equivalents of the ASCII codes for these letters. Similarly, the numbers 0-9 have codes 48-57 as the decimal equivalents of the ASCII codes.

ASC(STRING)

This has the opposite effect of CHR\$ in that it takes the first character (first character only) of the string in the brackets and returns the decimal equivalent of its ASCII code as a number to be assigned to a numeric variable. Eg,

```
10 A$="STRING"
20 A=ASC(A$)
30 PRINT A
```

Here A takes the value 83, which will be printed by line 30, as this is the decimal equivalent of the ASCII code for the letter S.

That completes a rather impressive list of string functions. There are one or two others which can be found on some machines, but they are not really standard and will not be introduced.

Numeric Functions

We will now go on to examine the other big plus of Extended Basic — Extra numeric functions. In all the examples below, the contents of the brackets can be replaced with either a constant, variable or numeric expression.

We have already covered 4 functions in Tiny Basic; these were ABS(X), INT(X), TAB(X) and RND(X). These four functions are still available and join the rest of the list presented below.

LOG(X)

This function returns the log to base e of the contents of the brackets, eg:—

```
10 A=LOG(3)
```

here A takes the value 1.09861.

EXP(X)

This function raises the base e to the power X and is thus the inverse of the LOG(X) function.

```
10 A=EXP(3)
```

here A takes the value 20.0855

SGN(X)

This is the Signum function. If the contents of the brackets have a -ve sign then this function returns a value -1; if the contents are +ve the function returns +1; and if the contents are zero, the function returns zero.

```
10 A=SGN(-12)
```

here A takes the value -1.

SQR(X)

This function returns a value equal to the square root of the contents of the brackets (obviously these contents must not be negative).

BEGINNING BASIC

10 A=SQR(9)

here A takes the value 3.

TAN(X)

This function returns the trigonometric Tangent of the contents of the brackets (most trig functions assume X to be in radians — 1 degree = 0.01745 radians and 1 radian = 57.2957 degrees).

SIN(X) AND COS(X)

These functions return the trig Sine and Cosine respectively (again X assumed to be in radians).

ATN(X)

This function returns the Arctan (the angle in radians whose Tangent is X) of the contents of the brackets.

This ends the arithmetic functions: in addition most machines have two special functions, PEEK (X) and POKE L,C.

PEEK(X)

This function returns a decimal integer in the range 0-255 corresponding to the decimal value of the binary code contained in the computer memory location X. X is also in decimal and can be any constant variable or numeric expression.

POKE L,C

This function is the inverse of the PEEK function. It allows you to enter any 8 bit binary combination into any location of RAM where L is the location number and C is the code to be entered (both L and C are in decimal.)

This is as far as we want to go this month, because there has been quite a lot of new material introduced and you would be well advised to re-read it if you are not familiar with it.

Homework For The Month

There are two good exercises for this month:—

1. Write a short program which will accept a number from 0-255 as input and convert this into a two digit Hexadecimal number in the range 00-FF.
2. Write a short program which will do the reverse of the above — accept a 2-digit Hexadecimal number and convert it to decimal.

And for all you bright boys (or those who don't know about Hexadecimal) you might also like to look at the problem of how you would go about taking a list of numbers in random order and sorting them into numerical order as we shall be moving on to such things from next month.

P. & R. COMPUTER SHOP


AScii Keyboards £40.00
ASR Teletypes From £175.00
KSR Teletypes From £90.00
Fans 4", 5" and 6" From £3.50
Paper Tape Readers From £18.00
Paper Tape Punches From £30.00
VDUs IBM 2260 Monitors including
Keyboards £30.00

Various power supplies and — store cores, test equipment. Plus an assortment of miscellaneous computer equipment

COME AND LOOK AROUND

**Solcott Mill, Goldhanger Road,
Heybridge, Essex. Phone Maldon
57440**

Two Bytes Are Better Than One



THE FULL POWER OF THE 16-BIT TMS 9900 MICROPROCESSOR IS NOW AVAILABLE WITH THE UNIQUE COMBINATION OF RELIABLE HARDWARE AND FAST, EASY TO USE SOFTWARE IN THE TECHNICO SS-16. WITH MINICOMPUTER PERFORMANCE THE TECHNICO 16-BIT MICROCOMPUTERS ARE AVAILABLE FROM THE SINGLE BOARD SUPER STARTER SYSTEM AT UNDER £350 TO THE FULL SS-16 WITH UP TO 65K BYTES OF MEMORY, FULL FLOPPY DISKS, 64 COLOR VIDEO BOARD OPTION, *RS232 AND 20MA CURRENT LOOP ALL COMBINED WITH ONE OF THE INDUSTRY'S FASTEST BASICS AND A FULL ASSEMBLER, EDITOR, LINKING LOADER PACKAGE AT £4700. SYSTEMS ARE AVAILABLE COMPLETELY ASSEMBLED AND TESTED OR IN UNASSEMBLED TEC-KIT FORM. EXPLICIT MANUAL INCLUDED OR AVAILABLE SEPARATELY AT £20. TO LEARN MORE CALL PICO DYTE LTD. 021-440 5631 or 056-45 77019

*INTSC Standard only!

PICO DYTE production in collaboration with Technico International **PICO DYTE** 85 VICEROY CLOSE BRISTOL EDGBASTON BIRMINGHAM B5 7UT



With the promise of hot summer days ahead you will all want to get your hands on one of our Computing Today T shirts. Available at a bargain price of £2 each they are in black cotton with our logo in white on both front and back. We don't guarantee that you will look quite as stunning as our model but it's bound to be a talking point. Order yours today from:

Computing Today,
145 Charing Cross Road,
London WC2H 0EE

Don't forget to give us your size (S, M or L)!

NEW CASIO MODELS

Put most SOLAR watches in the shade!

CASIO 95QS-31B

4 year battery.
1/100 sec. chrono
to six hours.
Dual time
12 or 24 hour.
Stainless steel
encased.
Lightweight.
water resistant
to 66 feet (2 at).
RRP £29.95.

£23.95



CASIO 95 CS-31B

(De-luxe model).
5 year battery.
1/100 sec. chrono
to six hours.
Dual time.
12 or 24 hour.
Solid stainless
steel case.
Water resistant
to 100ft (3 at).
RRP £44.95.

£34.95



Both have new Lithium batteries which outlast most SOLAR watches. Constant LCD display of hours, minutes, seconds, a.m./p.m. and day (12 to 24 hour). Dual time (12 to 24 hour).

Chrono: Net, lap and 1st and 2nd place times.

Automatic day, date, month and year calendar. Mineral glass face. Backlight. High quality s/s bracelets with easily removable links.

CASIO 81CS-36B Alarm/Chrono

Same specification as earlier 46CS-27B plus 5 year Lithium battery. 12 or 24 hour display. Chrono functions as above. 24 hour alarm. Hourly chime facility. Water resistant 100ft. RRP £49.95.

£39.95

LCD PROGRAMMABLES

With non-volatile stores and memories and almost infinite programmability (using FA-1)

CASIO FX-501P

128 steps
11 memories
5 levels (I)
RRP £64.95

£54.95

FX-502P


256 steps
22 memories
10 levels (I)
RRP £84.95

£74.95

FA-1 Adaptor

RRP £24.95

£19.95



51 scientific functions. Conditional jumps, etc. 1300 hours battery life. $\frac{1}{4}'' \times 2\frac{1}{4}'' \times 5\frac{1}{2}''$.

Leatherette wallet. Programme manual.

Optional FA-1 permits programme/data storage on standard cassette tape recorder for re-entry later. Typical storage/re-entry time 9-16 seconds.

Send 25p for illustrated brochures.

Prices include VAT, P & P. Send cheque/P.O. or phone your ACCESS or BARCLAYCARD number to:

TEMPUS

Dept. CT Beaumont Suite 164-167 East Rd
Cambridge CB1 1DB. Tel. 0223 312866

Dear Sir,

Re my letter in your May edition. Now let's get this right, I was not complaining about the Nascom 1 but was trying to warn beginners of the fact that even if they did everything correctly there was still a large probability that the machine would not work. A project as complicated as a Nascom 1 is asking for gremlins (I had many) and you should expect to do some fault finding, hence I will say it again — the novice should seriously consider buying a working model.

The PCB for the Nascom 1 is superb, but the tracks tend to be a little too close in places (and from my experience, letters from Nasfans and personal contacts a common fault seems to be shorting between tracks due to incomplete etching).

I would have no hesitation in recommending a Nascom 1 kit to experienced constructors, or to the beginner who can get in touch with somebody who already owns a working machine. I have no ill feelings about buying my Nascom 1 and after expansion I would not swap it for a Pet nor a TRS-80.

Yours faithfully,
A.R.Ingleson,
B.Tech.

27 Cecil Avenue,
Great Horton,
Bradford,
W.Yorkshire BD7 3BW.

Dear Sir,

Having read the article in your June issue on the S100 bus you seem unaware that an attempt is being made to define a standard for it, in fact some products now being advertised in US magazines do state "to proposed IEEE standard".

I don't know what state things have reached in its establishment, but an article appeared in the May 1979 edition of the IEEE Journal "Computer", should anyone care to follow it up.

Yours faithfully,
David Parkinson.

Well Cottage,
The Street,
Tuddenham,
Ipswich, IP6 9BT.

Dear Sir,

Whilst I very much enjoyed the fission chips wrapped in the last issue, I did not like the silicone they were fried in.

Yours faithfully,
P.Childrens.

60 Lansdowne Hill,
London SE27.

Dear Sir,

Let me first congratulate you on the contents of your magazine, which seems to have the correct balance between reviews and software. This is only slightly spoilt by typographical and programming errors. Talking of which here are a few from your Minefield game by P. Wickett.

Line 9 POKE FF,87:POKE JJ,87

Line 40 IF TIMES > "000100" THEN 200

Line 51 IF C\$ = "1" THEN 520

Lines 1030 to 1044 Ys should be Y\$

Lines 624, 625, 626 & 628 could be condensed to
624 IF PEEK(FF) = 87 THEN 16. 626 IF PEEK(JJ) = 87
THEN 16.

There were no clear screen instructions in the program to remove Text from the playing field, and the game seemed difficult for beginners to win so the minimum number of mines per move was reduced to 1 thus:

Line 0 inserted PRINT "@"

Line 3 changed to PRINT "SET NO. OF MINES PER
MOVE (1-30)"

Line 6 changed to PRINT "@"

The @ Reverse field Heart character is produced when the clear screen (SHIFT and HOME KEYS) command is given inside the inverted commas of a print statement.

When these changes are made the game is very absorbing and will wile away mnay an hour.

Yours sincerely,
Steve Randall.

53 Moresby Avenue,
Surbiton,
Surrey KT5 9DT.

Dear Sir,

I should like to say how much we look forward to receiving the Nascom Package Puzzle each month! June's Education Package is now doing good service in the lunch hour, although Lollipop lady and Mastermind are still in strong demand. For those who have not yet discovered this months deliberate (?) missprints they are:

C65 FE 25
C67 20 F5
C74 CD B8 0D
C7C CD B8 0D
DB2 23

The DAA between lines DBF and DC1 is the subroutine title NOT an address.

Might I suggest that if you include an object code listing as well as the source code listing then it should be easier to spot missprints.

Do all your readers, particularly those very new to their Nascoms, realise that the text has to be keyed in as ASC II codes? It might help if you gave these!!!

I have just received my July Computing Today and from the first five lines of the Nascom Package it looks as if we are in for more fun this month as well.

Yours,
Alec Wood.
Physics Dept.

Wirral Grammar School for Boys,
Wirral,
Merseyside.

Dear Sirs,

As I bought a Compucolor II last March, I was interested to read the review in your June issue (which only recently reached me as I had moved countries).

I was particularly impressed by the glowing account of the 150 page manual since my machine was delivered without one and, a considerable number of transatlantic telephone calls having failed to extract one from the suppliers of the computer, I had to devote about a month of experimentation to writing my own. Thus, though the machine has many capabilities I have yet to fathom, I can state from experience that this computer represents very good value for anyone wanting both disk and colour graphics capability.

It has a good point and a bad point that your review did not mention. The good point is that almost all Basic keywords can be entered with a single key-stroke. Press "control/shift V", for example, and the key-word "PRINT" is entered into the program. This is much quicker than spelling it out manually and avoids the risk of spelling errors. One learns the correct key strokes for the commoner key-words very quickly.

Now for the bad point, the disk drive. For a start this is a stripped down version of the Wangco drive, at least on my machine which has not got the capability to format blank disks. This means you must use preformatted Compucolor disks. Further, this must be almost the slowest, lowest capacity disk drive still on sale. 40 tracks it has, but each track holds ten sectors of only 128 bytes and, as far as I can detect, only one sector is read during each turn of the disk, giving a mean data transfer rate of only 640 bytes per second, much faster than a cassette, but slow by present day disk standards.

Since the Compucolor II seems likely to be a rare beast in the U.K. in the near future, some mutual assistance among users would seem to be in order and I would be prepared to act as a centre in the setting up of a Compucolor users group.

Yours faithfully,
Tom Napier.

217 Clement Rise,
Livingston EH54 6LR.

Dear Sir,

I would be very grateful if an announcement could be published in the next 'Computing Today' to let people know that I do NOT run an Amateur Computing Group, and never have!

This must be due to a misunderstanding arising from a letter to Mike Lord some time last year.

I would also like the error to be corrected at source, so please tell the people from who you get the information of the error.

Thank you in anticipation of your help in lessening the chance of further shocks due to seeing my name in print where not expected!

Yours sincerely,
Nicolas Beard.

Newsagents,
High Street,
Braithwell,
Rotherham,
S.Yorks.

PETALECT

ELECTRONIC SERVICING LTD.

WANTED

Good Homes for Intelligent Pets
THE

PET 2001 Computer from £450 plus VAT



This unbelievably versatile, compact, portable and self-contained unit has many varied applications and offers tremendous benefits in the worlds of

- **BUSINESS and COMMERCE:**

Can be used efficiently for Trend Analysis · Stock Control · Payroll · Invoicing · Inventory Control, etc.

- **SCIENCE and INDUSTRY:**

The 'PET' has a comprehensive set of scientific functions useful to scientists, engineers and industry.

- **EDUCATION:** An ideal tool for teaching and it can be used to keep records, exam results, attendance figures, etc.

- **ENTERTAINMENT:** Games including Backgammon, Noughts and Crosses, Pontoon, Black Jack and Moon Landing

PET COMPATIBLE DUAL FLOPPY DISC NOW AVAILABLE

NEW PETS NOW IN STOCK

We have six years' experience in servicing electronic calculators, mini-computers in S.E. England. 24-hour service contract available at £69.50 per annum. Credit and leasing terms available.

For full details and demonstration contact Peter Watts . . . Now!

PETALECT

ELECTRONIC SERVICING LTD

(Authorised Commodore Pet Dealer) Specialists in Electronic Servicing, Programming, Electronic Design and Prototype Manufacture

**33 PORTUGAL ROAD, WOKING,
SURREY GU21 5JE.**

Tel: Woking (04862) 69032/68497

STRATHAND



APPLE II COMES TO SCOTLAND

Why not call and see the fantastic Apple II the finest micro currently available. Demonstration without obligation.

16K	£830
Disc drive with controller	£425
16K add-on	£90
High-speed serial I/F	£110
Parallel I/F	£110
Comms card	£140
Applesoft firmware card	£110

Coming soon pascal card and new UK colour board

We also have in stock the following top quality items:

Nascom 1, including all available expansion.

Digivision Monitor Kits — If you are thinking seriously about a monitor for your micro we have the best. Beware of cheap imitations which may use T.V. tubes. Our use professional quality tubes which we have on demo. The difference has to be seen to be fully appreciated. Nine and 12 inch in stock now. Price £100 + VAT

High Speed Tape Cassette Interface. Comes complete with instructions showing how to interface to Nascom giving 'normal' and high speed operation. 300, 600, 1200, 2400 baud. At the highest speed this will load our 8K basic in about half a minute. Price (Kit) £17.50 + VAT

8K Tape Basic. The best basic yet written for Nascom. Fully floating decimal point. Complete with all documentation. Price £35.00 + VAT

Brand New Product. Chiptester. Converts Nascom to a super powerful I.C. tester. Plugs in to existing ports. Send now for full details.

Also newly arrived. Totally new games to play on any standard Nascom. Send for full details prices, etc.

STRATHAND

44 ST. ANDREW'S SQ.
GLASGOW G1 5PL
041-552 6731

Tel. order welcome with Access and Barclaycard

Callers welcome



Callers welcome



Now on Telex 777268. 24 Hours Service

SPEECH RECOGNITION

The author and Brian Pay of NPL checking out CT.

Talking to computers; fact or fiction? Hear the word!

It is more than probable that "speech" communication between humans started before the era of cave paintings, unfortunately they did not have tape recorders so the actual dates are no more than an approximation. The word speech is used loosely at this time to mean sounds produced by one individual and understood by another, formal languages must have taken a very long time to evolve. An approximate date for early cave paintings is around 35,000 years ago, so we have some idea of the length of time it has taken for true speech communication to evolve.

Fictitious Beginnings

Because man uses speech for natural communication in preference to all else the science fiction writers simply had men talk to their invention and it understood.

The great divide in speech recognition as it stands today, is can we recognise continuous (conversational) speech rather than single words? On a limited basis the answer is Yes. The days of HAL (2001) are not yet here, but the first barriers have been breached.

Government Research

The National Physical Laboratory at Teddington contains, among other things, a Speech Recognition group headed by Brian Pay. They began investigating the problems of speech recognition in 1967 and after doing a considerable amount of both psychological and physiological research they produced a machine which could distinguish between certain vowel sounds, for example "AA", "EE", "OO" and "OR". This system was designed in hardware and used no computing power at all. By 1972 a system had been produced which used a computer to collate the data and this was given the generic name of SID, Speech Input Device. The first working demonstration of SID used a slide projector which was controlled with one of six phrases such as "Switch On" or "Next Slide Please". For this demonstration however no computer was used, all the recognition being done by sequential logic. This machine was re-activated for the British Genius Exhibition in 1977 and was used by the general public for six months.

Although the design of SID has been changed considerably over the past few years, mainly because of the new technology available, the basic concepts have remained the same. It would take too long to explain the full workings of a SID but the fundamentals are of interest and we will try to give an understanding of these.

Hardware Vs Software

The system that has been devised at the NPL analyses the speech waveform and every 10 mS produces a digital byte



that is fed to a computer. The data reduction process is performed in hardware to enable a high speed of recognition, the software merely collates the data and compares it with its "Library" of words or phrases to produce a match.

The human voice can be broken down into three main sections of interest, i) Voiced sounds, ii) Fricative sounds and iii) Silence. This is a simplified view but will suit our purposes.

Voiced sounds. These are produced by the excitation of the larynx and this causes certain cavities within the head to resonate, see Fig 1. A typical voiced waveform can be seen in Fig 1a. This can be broken down into three main parts, the larynx period, the first formant and the second formant. These formants are of different frequencies and are produced by the positioning of the tongue within the mouth. By moving the tongue around from one vowel sound to another a diphthong is produced, another fundamental voice characteristic. For example in the word "NINE" the diphthong is produced by moving from the vowel sound "AA" to the vowel sound "EE".




Fig.1 The human vocal tract.

Fricatives. A typical fricative waveform can be seen in Fig 1b of the "S" type sound that we find in "Sit" or "Six". Although the tongue and lips are positioned to form cavities within the mouth the larynx is not excited and so there is no repetitive structure to the waveform.

Silence. When gaps of silence occur within a word they carry information to the listener. However in continuous speech there are seldom gaps of silence between words. On the early versions of SID silence was defined as being neither voiced or fricative. Nowadays, however, silence is determined as the continuous background level and this allows the system to operate in such noisy conditions as are found on telephone lines.

The Process Of Processing

On the early SID's no account was taken of bandwidth restrictions (eg: telephone lines) and a high quality dynamic mic was used on the system. An AGC was also used to compensate for any small amplitude variation which occurred between speakers. The first processing that is done on the speech is to discriminate which quality is present. This is done by the VFQ card which measures the relative power (energy) present in two band pass filters, see Fig 2. A certain amount of hysteresis is built in to allow the detection of silence if neither filter contains sufficient energy.

If a voiced sound is detected two more band pass filters are enabled, corresponding to the frequency bands of the first and second formants. Having filtered the speech into

these two bands the result is clipped to produce a digital signal and this is fed into a delay line. Tappings are taken off the delay line and a wave form produced by correlation. This waveform consists of a frequency dependant voltage and is used to switch an op-amp into saturation at a given frequency — SID uses seven of these barriers for each of the two bands, the low range vary from 200 to 800 Hz and the high range vary from 800 to 3 kHz. The outputs of all these barriers are cleaned up to remove pulses of less than 15 mS in duration and "lock-up" logic is used to ensure that when one barrier is asserted all those lower in frequency are also asserted. A block diagram of the system is shown in Fig 3.

We now have a total of 19 "bits" of information, that is three voice qualities and sixteen descriptions. These are reduced by a logic board to eight bits suitable for sending to the computer. A typical display is shown in Fig 4. This is for the word FISHES and has not yet been reduced for transmission.

Software Requirements

Before any attempt is made to match any input pattern with any stored patterns, ie: recognition, the data must be sorted out into the voiced qualities and their descriptions. Because the computer knows that it will receive a byte every 10 mS it can also measure the duration of each voice feature found. Two typical samples of this are shown in Fig 5. They are taken from different speakers and show the utterance "NINE". The letter of the left hand column indicates the




Fig.1a and b Typical speech waveforms, see text for details.




Fig.2 The characteristic of the VFQ detector. Hysteresis is built in to detect silence if neither band is energised.




Fig.3 A block diagram of SID showing the various processing sections described in the text.

SPEECH RECOGNITION




Fig.4 An unreduced output from SID. See text.

quality, the right hand column is the duration in 10's of mS and the centre data is the description of that quality. In the centre of the data we find V4 progressing through V5 and V6. This is a diphthong and is characteristic of the word "NINE". The same information is present in both utterances of the word, despite the fact that the speakers were different.

To complete the recognition the patterns now obtained are matched against a library set of patterns and the best fit is given the highest score, and thus the most probable "recognition". Because of several words are subsets of other words, six and sixteen for example, the utterance six will score a low probable match on sixteen, if sixteen is stored in the same library.

A Flying Start

One of the most impressive demonstrations we saw at the NPL was the "Pilot Cockpit". A suite of programs is run to simulate a cockpit on an aeroplane where the pilot can update various pieces of information. Once the program is running it is listening all the time to the speech input but looking for one specific word, this key word being "START". Under normal conversation conditions nothing happens but when the word is uttered in isolation the machine instantly goes into operation and displays the set of available commands on the VDU. The pilot now has the choice of inspecting and altering one of four items, height, bearing, speed and position. Once again a conversation may be carried on with no result until one of the four keywords is uttered. Up to this point the machine has been taking account of words in isolation but once in the update mode it will accept a numeral string, that is as continuous speech.


The whole system is designed to allow the operator to converse as naturally as possible with the computer, he is not forced to constrain himself to single words or to turn the system on or off when he wants to use it.

At any point in the sequence the machine is only looking for a specific set of words to be spoken, this reduces the storage necessary to an amazing 4K, program and all. The machine will even allow a certain of umming and erring to occur at the command level. The ability to detect key


words embedded in other speech and continuous speech is unique to the NPL's equipment and software techniques.

The Real World

Quite apart from being used in laboratory environment the NPL equipment has been used in anger at a hospital as part



The latest SID, connected up to an LSI 11.



of a medical interviewing system. The machine was designed to recognise the words "Yes", "No" and "Don't know" and all recognition was performed in hardware. The resulting decision was fed, via the telephone networks, to a remote computer which ran the interview program. Despite the use of patients suffering from severe bronchial complaints a recognition rate of 63% was achieved.

The real purpose of the experiment however was *not* to recognise the spoken utterances of the patients but to see if speech recognition was an acceptable alternative to the use of a keyboard terminal that had previously been supplied. The general feeling of the patients was that they found the speech system extremely "useable" and preferable in many ways to the previous system.

Another application of speech recognition that is currently being undertaken is the cockpit situation. Marconi Avionics are developing the NPL system with a specialised vocabulary for use in the cockpits of military aircraft.


One commercially available system has been marketed in the UK by EMI. Developed by Threshold Technology in the States it is similar to the NPL system in that dedicated hardware processing is used before the data is fed into the computer. However, the system does require words to be spoken in total isolation and also has to be trained by each individual speaker. You can, if you want to, go out and buy one today for about £6000. This system is being used by, among others, an Australian slaughterhouse and the German Post Office. About 300 Threshold systems are in use, worldwide.

The obvious advantage that any direct voice input system has over a keyboard is that an operator can use his hands to do the job and report on the progress with his voice. In the slaughterhouse situation the meat inspector can describe the status of the carcass with one word from a choice of perhaps ten and the computer can then "tag" the appropriate carcass with that description and pay the owner as well as arranging for suitable disposal of the meat at the same time.

Both recognition systems that we have described use hardware pre-processing and feed the collected information to a computer for further analysis. Whilst the NPL system is a multi-speaker system it will always produce its best results on individuals that have pre-trained it. The Threshold system however relies totally on being pre-trained by each operator that uses it. The NPL machine will recognise words in its

COMPUTING TODAY 1979

SPEECH RECOGNITION



From left to right:— Three typical processor cards from SID, correlators and barriers, filters and clippers and the VFO discriminator. The right hand photo is of the original SID which was built in 1972.

vocabulary in both isolation and when spoken as part of a sentence or phrase, Threshold relies on isolated utterances for successful operation. It is recognised by both development teams that speech recognition systems will never totally replace key input systems and such wonderful machines as speech input typewriters are many years away. However it has to be accepted that both research teams have produced a device which will recognise human speech. This in itself is a great achievement, it has taken tens of thousands of years to develop speech as a communication medium but only twelve to connect it to a computer.

What The Future Holds

The main task for the next generation of SID's is to undertake the analysis of speech under conditions of both noise and restricted bandwidth. Once success has been achieved in these areas use of remote recognition devices over a public telephone network becomes a reality. After all, we humans can recognise speech under the awful telephone conditions so the development of a machine to do the same should not be too far away. The latest version of NPL's SID is indeed capable of operation on the telephone bandwidth and this is the system that is being exploited by Marconi Avionics for their pilot cockpit system.

There are more speech features to be analysed, plosives, stops and nasals for example. Any recognition system will be able to work better if it has more relevant information, redundancy is very important in speech. Soft-

ware is currently under development to generate vocabularies directly from speech input to allow even more training of the machine than is currently possible. The NPL system is also being switched from a PDP 8f mini computer to an LS1 11 microprocessor, giving an increase in computing power and reduction in physical size at the same time. The immediate aim of both speech recognition development teams is to gain a foothold in the defence market. This highly specialised area requires techniques to get over such problems as stress under battle conditions and high ambient noise as well as rugged electronic design needs. To quote Brian Pay, "When you've solved the defence problem, you've solved the lot."

The Final Word

Any speech recognition system produced under today's technology will never achieve the dizzy heights of HAL. However there are systems being used now that at least have one or both feet on the ladder. Language is no problem, you just change the vocabularies, and it is conceivable that within this authors working life systems will be available so that you can interact with computers from your armchair, through the telephone system.

With information systems being one of today's big developments speech recognition could well be tomorrow's means of controlling them.

The working environment. SID is the lower unit on the left.



Mr. P.J. Marshall



**Driven to despair with TV?
Try our 'Brands' game for
some high speed fun**


This Softspot program has been written in a "Standard BASIC" and should be easily adaptable to run on any machine. No graphics are used in the program, thus making it simpler and faster to run. It should prove easy to modify the basic program to include graphics for PET owners amongst others. The conversational method of programming used requires little explanation and there are some interesting subroutines which can be adapted for other gaming programs.

Fig 1. The program listing for Brands.

```

0005 DIM A$(15)
0010 A$(1)="STRAIGHT SECTION"
0020 A$(2)="MED BEND COMING"
0030 A$(3)="MED RIGHT HANDER"
0040 A$(4)="STRAIGHT"
0050 A$(5)="HAIRPIN COMING UP"
0055 A$(6)="HAIRPIN!!"
0060 A$(7)="STRAIGHTENING"
0070 A$(8)="MED LEFT HANDER"
0080 A$(9)="STRAIGHT"
0090 A$(10)="SHARP RIGHT"
0100 A$(11)="STRAIGHT"
0110 A$(12)="FAST RIGHT NEAR"
0130 A$(13)="FAST RIGHT BEND"
0140 A$(14)="PITS STRAIGHT"
0150 DIM R(5)
0160 DIM S(15)
0170 DATA 196,143,96,78,67
0180 DATA 160,110,51,110,84,42,75,
      120,150,60,120,98,82,160,160
0200 FOR I=1 TO 5
0210 READ R(I)
0229 NEXT I
0230 FOR I=1 TO 15
0240 READ S(I)
0250 NEXT I
0260 Z=0
0261 K=0
0263 I=0
0264 DIGITS= 2
0265 Q5=0
0266 V=20
0267 G=1
0300 PRINT CHR$(26)
0310 PRINT "THIS IS A MOTOR RACING
      GAME WHERE YOU HAVE TO DRIVE
      A FORMULA"
0320 PRINT "ONE RACING CAR FOR TWO
      LAPS ROUND THE SHORT COURSE
      AT BRANDS"
0330 PRINT "HATCH AT EACH STAGE OF
      THE CIRCUIT YOU WILL BE TOLD
      WHAT"
0340 PRINT "THE ROAD IS LIKE AHEAD,
      AND WHAT THE MAXIMUM SPEED
      IS FOR"
0350 PRINT "THAT SECTION"
0360 PRINT
0370 PRINT "ALL YOU HAVE TO DO IS
      SPECIFY THREE THINGS...."
0380 PRINT
0390 PRINT "1)....GEARS ..1 TO 5"
0400 PRINT "2)....BRAKES..0 TO 9"
0410 PRINT "3)....THROTTLE.0 TO 9"
0420 PRINT
0430 PRINT "THE REV LIMIT ON YOUR
      ENGINE IS 10000 R.P.M. YOU MAY
      EXCEED"
0440 PRINT "THIS FIGURE ONLY SIX
      TIMES, THEN YOUR ENGINE BLOWS
      UP"
0450 PRINT "THE SAME THING HAPPENS
      THE FIRST TIME YOU EXCEED
      10000 RPM"
0460 PRINT
0462 PRINT
0463 PRINT "ROLLING START AT 20
      M.P.H."
0464 PRINT
0470 PRINT
0480 PRINT "THE FLAG IS UP....."
0490 PRINT ".....DOWN ....."
      OFF YOU GO !!"
0500 B6=0
0501 PRINT
0510 FOR A1=1 TO 2
0520 PRINT
0530 IF A1=2 PRINT "YOU ARE NOW
      STARTING LAP TWO"
0540 FOR I=1 TO 14
0550 PRINT
0560 PRINT "SECTION ",I
0570 T5=RND(0)
0575 M=S(I)*(I+T5/10)
0580 PRINT A$(1)

```



BRANDS


MAXIMUM SPEED ON THIS SECTION 115.09 M.P.H.
 DRY ROAD .. GET YOUR CLOG DOWN !!
 GEARS.....? 2
 BRAKES.....? 0
 THROTTLE...? 7

GEAR	SPEED	REVS	TIME
2 00	82.14	11746.31	8 01

WATCH YOUR REVS !!

SECTION 3.00
 MED RIGHT HANDER

MAXIMUM SPEED ON THIS SECTION 54.82 M.P.H.



A typical screen display from the game.

```

0590 PRINT
0600 PRINT "MAXIMUM SPEED ON THIS
SECTION ",M,"M.P.H."
0610 IF T5>.87 THEN 640
0620 PRINT "DRY ROAD .. GET YOUR
CLOG DOWN !!"
0630 GOTO 670
0640 PRINT ".....*****
RAIN :::::::::::::::"
0650 PRINT " WATCH YOUR STEP ..
SLIPPERY ROAD AHEAD "
0660 PRINT
0670 INPUT "GEARS.....",G
0675 IF G>5 THEN 670
0680 INPUT "BRAKES.....",B
0690 IF B>9 THEN 680
0695 B6=B6+B
0700 B1=B-(B*B6/200)
0710 INPUT "THROTTLE...",T
0720 IF T>9 THEN 710
0721 R=V*R(G)
0722 IF R>9000 THEN 725
0723 P=R/6000
0724 GOTO 730
0725 P=1.5-(R-9000)/10000
0730 V2=V+(T-1)*(10-G)
      *P/1.65-B1*7.25
0740 IF B>8 THEN IF T5 .87
      THEN 1500
0750 IF V2-5>M THEN 1250
0760 IF V2>M THEN PRINT"WATCH YOUR

```

```

SPEED FANGIO !!"
0770 K=(V+V2)/2
0780 Q=3600/(20*K)
0790 Q5=Q5+Q
0800 R=V2*R(G)
0810 V=V2
0820 PRINT
0830 PRINT "GEAR          SPEED
          REVS          TIME"
0840 PRINT G,TAB(11),V,TAB(22),
      R,TAB(34),Q5
0850 IF R>10000 THEN 900
0860 NEXT I
0870 NEXT A1
0880 GOTO 2000
0900 Z=Z+1
0905 IF R>12000 THEN 1000
0906 PRINT "WATCH YOUR REVS !!"
0907 PRINT
0910 IF Z=2 PRINT "THATS THE
      SECOND TIME"
0920 IF Z=3 PRINT "THATS THE
      THIRD TIME..."
0940 IF Z=4 PRINT"THAT'S THE
      FOURTH TIME...."
0950 IF Z=5 PRINT"THAT'S THE FIFTH
      AND LAST TIME...."
0960 GOTO 860
1000 PRINT "YOU'VE BLOWN UP YOUR
      ENGINE!!!!TOUGH LUCK"
1010 GOTO 2030
1250 IF V2>M+12 THEN 1300
1260 PRINT "YOU HAVE SKIDDED AND
      LOST SPEED"
1270 V2=V2-1.2*(V2-M)
1280 GOTO 770
1300 PRINT "YOU HAVE CRASHED
      AT ",V2+2.2," M.P.H."
1310 IF V2-M>16 THEN 1350
1320 PRINT "CAR DAMAGED...YOU'RE OK"
1330 GOTO 2030
1350 PRINT "SORRY IT WAS FATAL...."
1360 GOTO 2030
1500 PRINT "YOU SLAMMED ON THE
      BRAKES IN THE WET AND
      SPUN OFF !!"
1505 GOTO 1350
2000 PRINT
2010 PRINT "YOU COMPLETED THE COURSE
      IN ",Q5,"SECONDS...WELL DONE!"
2020 PRINT "YOU'RE AVERAGE SPEED
      WAS ",84*60/Q5," M.P.H."
2030 PRINT
2040 INPUT "ANOTHER GO
      (1=YES 2=NO) ",J
2045 RESTORE
2050 IF J=1 THEN 170

```


BRITISH MOTOROLA 6800 SYSTEMS

6800S: 16K Dynamic RAM, 1K Mikbug compatible monitor, room for 8K BASIC in ROM, VDU with u/l case and graphics, CUTS and HI Speed tape interfaces, Single pcb with power supply components. Price of kit from £275 without kdb or £299.00 with keyboard.

Mini 6800 MK2. 1K user RAM, CUTS, VDU with u/l case and graphics with QWERTY keyboard from £152.50 NCU Board. This number cruncher using the MM57109 is supplied with our own Basic style program on tape (3K bytes) that will outperform any of the 8K Basics as a programmable calculator. Suitable for any 6800 system with Mikbug. Kit price £32.00

8K RAM (2114) and 5 or 10K PROM board. This pcb is bus compatible with the above systems and has all the buffering and decoding that you need. PCB only, £13.00

MICROCASE. A big beautiful grey ABS Moulding with heavy aluminium chassis big enough to house a big system. £29.00.

ALL PRICES WITHOUT VAT AND POST. PLEASE SEND S.A.E. FOR LEAFLETS.

HEWART MICROELECTRICS

95 Blakeley Road, Macclesfield, Cheshire.

Complete

TRS 80 and SORCERER

systems with lower case and word processing.

MICROPOLIS disc drives £350

SOFTWARE proper business systems

For information please write:

**EMG Box 118,
30 Heathfield Road,
Croydon, Surrey.**

NEW RANGE OF BUSINESS SOFTWARE ON DISK

MAIL LIST • SALES LEDGER • INVOICING • CURRENT ACCOUNT PACKAGE • VAT AND GENERAL ACCOUNTING • STOCK CONTROL • ESTATE AGENTS PACKAGE

Available for Apple II, PET, and Computhink disk systems. Prices from £30.00 + VAT. For full catalogue of over 80 programs and all details, send s.a.e. to:

Gemsoft, "Alverstone Lodge"
Wych Hill Lane, Woking
Surrey (04862) — 60268

COLOUR MODULATOR

Kit
£9.95
inc. UHF
Modulator

FOR ALL TV GRAPHICS!

Red, Green, Blue inputs (can be mixed)
Coming soon: Nascom Colour Kit, £39.95
inc. Graphics Software

WILLIAM STUART SYSTEMS

Dower House, Billericay Road, Herongate,
Brentwood, Essex.
CM13 3SD. Tel: (0277) 810244
Barclaycard/Access welcome

INTENSIVE WEEKEND COURSES IN

BASIC

including hands-on mini computer operation.

This short intensive course is intended to instruct from minimal knowledge to an operational capability of computer programming in BASIC high level language. The course is fully residential from Friday evening to Sunday afternoon. Option of non-residential weekend, weekday evening and weekday courses available if required.

For further details of dates available, fees, etc.:

Phone (0401) 43139, or write to:
CLEVELAND BUSINESS SERVICES
Cleveland House, ROUTH
Beverley, North Humberside

AD INDEX

	PAGE
ADDA ELECTRONICS	18
AJD DIRECT SUPPLIES	12
A. J. HARDING	24
ANALOG ELECTRONICS	36
BETOS SYSTEMS	28
CHROMASONICS	12
COMP, COMP, COMP	74 & 75
ELECTRONIC BROKERS	10
GP INDUSTRIAL	10
HAL COMPUTERS	6
HAPPY MEMORIES	24
INKRAFT	55
LOTUS SOUND	23 & 55
MICOM	55
MICRODIGITAL	6, 36 & 46
MUSHROOM	12
NEWBEAR	76
NEWTRONICS	6 & 24
NIC MODELS	55
PETALECT	62
PETSOFT	8
PICODYTE	10, 18 & 58
POWERTRAN COMPUTERS	2
P & R COMPUTER SHOP	58
SOFTWARE PUBLISHING CO.	18
STRATHAND	62
TECHNALOGICS	36
TEMPUS	60
TRANSAM	4

THIS SECTION IS A PRE-PAYMENT SERVICE ONLY

MINI-ADS: 31/4" x 21/8", 1-3 £38, 4-11 £36, 12 or more £34 per insertion. CLASSIFIED DISPLAY: 19p per word. Minimum 25 words. Boxed classifieds are £6.33 per col. centimetre. No P.O. Box Numbers can be accepted without full address.

Enquiries to: Advertising Department, 01-437 5982. 25-27 Oxford Street, London W1R 1RF

& CLASSIFIED

THE NEW μ HEX 480 EPROM PROGRAMMER 2704 and 2708

Control programs for Z80, 8080, 6800, 6500. Please state machine. Programs permit programming any length block into the eeprom, so even unexpanded machines can now program eeproms.

Needs only +5V, +12V, -5V. Host computers require a PIO (PIA) complete kit only £35 or ready built and tested £5 extra.

PIO, PIA INTERFACE PANELS

Available for Z80/8080, 6800/6500

THE μ HEX 416 DELUXE EPROM PROGRAMMER

Push Button Selection for 2704, 2708, 2716. Still only £65.

All prices inclusive. SAE for further information about these products.

MICRO HEX COMPUTERS

2 Studley Rise, Trowbridge, Wilts.

GAMES FOR NASCOM

Five new Nascom games

**SHARK HUNT, CASE AND TRAIL,
BULLS AND COWS, FOUR IN A
ROW AND LICE ON CASSETTE.**

All run on minimum Nascom system. All five recorded both sides. Fantastic value complete with printed instruction booklet. £11.50 inc. VAT and postage and packaging.

(Instruction Booklet only £1.00, refunded if games cassette purchased).

STRATHAND



callers welcome



Tel. order welcome with Access and Barclaycard.
Now on Telex 777268, 24 hours service

Super book selection of electronic expertise for computer programming and data processing	
How to Program Microcomputers	£3.95
The 8080A Bugbook	£4.95
Basic Computer Programming	£1.99
Basic Computer Language	£3.95
Microcomputer Primer	£3.49
Understanding Digital Computers	£2.49
Memory Data Book	£3.25
Intel 8080/8085 Programming Manual	£2.95
Intel Memory Design Handbook	£2.95
Intel Data Catalogue	£4.49
Digital Technics Book 1	£5.50
Send Cheques, P.O., to:-	
AUTO AGENCY (Computer Section),	
22 Homefield Avenue,	
Arnold, Notts.	
NG5 8GA.	

FOR SALE, VIM 1 with 4K, £179.00. Tangerine 1648 VDU, £95.00. Star Keyboard, £22.00. Free PSU if above purchased together, excellent condition. Phone McArdie 0751 - 31751.

TRITON COMPUTER complete with 3K RAM, several programs on tape, £300 ono for quick sale. Tel: Trowbridge 62596 (evenings and weekends).

EPROM PROGRAMMING prompt service 2708 (1024 x 8) or 5204 (512 x 8) EPROMS programmed with your Hex listing £13.50 each or your chips erased and programmed £3 each. Special rates for batches. Peter Marlow, "Rosslyn," Moorend Grove, Cheltenham, Glos. GL53 0EX. Phone (0242) 55133 evenings.

FOR SALE, NCR 399, visible record computer, 8K memory any reasonable offer considered. Tel. Leeds 658281.

SUPERBOARD II. Fully cased. 8K RAM: £300. ETI Triton in Verocase. 4K RAM V5.1 Monitor, £300. Tel. Tony 01-998-0475.



JUST COMPARE OUR CASH AND CARRY PRICES!

PET COSTS LESS AT COMP and it's a pedigree

RRP £550

The No. 1 Personal Computer in the U.K. Affordable for the first time user and the professional check out the PET, the world's most popular personal computer.

8K — £499 16K — £590

32K with GREEN SCREEN — £690 Cassette recorder now in stock £55



ADD A PRINTER TO YOUR PET

RS232C I/O CARD

Attach to any RS232 printer, modem, acoustic coupler to your PET. Easy to assemble. £89 in kit form. Add £20 for fully assembled and tested.

PET TO S100 FOR MEMORY EXPANSION

Convert the IEEE 488 bus to the well supported S100 bus. Comes complete.

Connectors and documentation included. Ready assembled and tested. Our price £89.

SOUND BOXES FOR PET

Fully assembled with documentation how to add sound effects to your programs. £14.90

BEST GAME EVER!

Petball — £5 for program

This game will have you and your family in tears for hours! For full effect buy sound box too! Best seller in U.S.A.

NASCOM IMMEDIATE EXPANSION S100 from COMP —strongly recommended

The only available S100 motherboard kit (fully buffered) that plugs directly into your Nascom. Designed for the insertion of S100 boards (e.g. Static RAM, EPROM and discs etc.).

S100 Motherboard/Buffer (Complete kit + documentation)

£47.50

Suitable 8K Static RAM Memory (fully assembled tested and guaranteed)

£125 £110

Buy both and get 2K Tiny Basic On cassette FREE.

MODULATORS UHF Channel 36

Standard 6 meg band width £2.25

High Quality 8 meg band width £4.90 EX-STOCK

UNIVERSAL POWER SUPPLY

Suitable for Nascom I, Nascom II, Superboard and all computers requiring these specifications.

+5V @ 3 amps +12V @ 1 amp —5V @ 500 mills —12v @ 500 mills
Easy to construct — complete with transformer. Our price £24.90

TRANSFORMER

Primary 220V with 2 individual secondaries £5.90

8V —0 —8V @ 1 1/2 amps 16V —0 —16V @ 1/2 amp


HITACHI PRO MONITORS

Superb definition 9" — £132 12" — £210

THE TRS-80 (SPECIAL SCOOP)

Low Priced, Ready to Go!

PLUGS INTO YOUR OWN TV



Use your own cassette

Level-II with 4K RAM

Improved graphics, print formatting, and a faster cassette transfer rate are features of Level-II Basic. £350 + VAT

Level-II with 16K RAM

A combination of 16K RAM and the powerful Level-II BASIC produces a system capable of handling most demands. £399 + VAT

64 chars x 16 lines — double length characters available at a single keystroke giving 32 chars x 16 lines. Super graphics a 2 x 3 cell arrangement. Masses of software available.

World's most popular machine. Fully converted to English Television standard. Rock steady picture — exclusive to COMP.

UK POWER SUPPLY SUPPLIED

KEY BOARD ONLY — Complete with UHF Modulator

RS232C I/O CARD for TRS80

Connect your TRS80 to any RS232 printer. Assembled and tested £55

SOUND BOXES FOR TRS80

Fully assembled with documentation how to add sound effects to your programs. £14.90

ATTENTION ALL NERVOUS TRS80's

Cure the video shakes. Upgrade your video to English Standard. Simple modification. Only £7.50 including easy to follow instructions. Only 15 minutes of your time needed. You owe it to your eyesight. Fitted as standard to all our machines.

NEW! AT LAST 8K BASIC FOR NASCOM 1

COMPLETE ON S100 EPROM BOARD

£160 + VAT EX-STOCK

BEST GAME EVER!

Android Nim — for TRS80.

£5 for program

This game will have you and your family in tears for hours! For full effect buy sound box too! Best seller in U.S.A.

TRS80 TO S100 BUS

for memory expansion £95

TV UHF MODULATOR FOR TRS80

Encased ready to use — £15

ELECTRIC PENCIL

Text Wordprocessing package on cassette £59

Please add VAT to all prices — Delivery at cost, will be advised at time of purchase. Please make cheques and postal orders payable to COMP, or phone your order quoting BARCLAYCARD, ACCESS, DINERS CLUB or AMERICAN EXPRESS number.

OPEN — 10am to 7pm — Monday to Saturday


CREDIT FACILITIES ARRANGED



EUROPE'S FASTEST SELLING ONE BOARD COMPUTER —
JUST CHECK THE SPEC'S.

COMPUKIT UK101

LOW COST SUPERBOARD IN KIT FORM



The
CompuKit
UK101
Character Set

FUNCTIONS
ABS(X) ATN(X) COS(X) EXP(X) FRE(X) INT(X)
LOG(X) PEEK(I) POS(I) RND(X) SGN(X) SIN(X)
SQR(X) TAB(I) TAN(X) USR(I)
STRING FUNCTIONS
ASC(X) CHR\$(I) FRE(X) LEFT\$(X,I) LEN(X) MID\$(X,I,J)
RIGHT\$(X,I) STR\$(X) VAL(X)

The CompuKit UK101 has everything a one board 'superboard' should have.

- ★ Uses ultra-powerful 6502 microprocessor.
- ★ 50Hz Frame refresh for steady clear picture (U.S.A. products with 60Hz frame refresh always results in jittery displays)
- ★ 48 chars by 16 lines — 1K memory mapped video system providing high speed access to screen display enabling animated games and graphs.
- ★ Extensive 256 character set which includes full upper and lower case alphanumerics, Greek symbols for mathematical constants and numerous graphic characters enabling you to form almost any shape you desire anywhere on the screen.
- ★ 8K full Microsoft Basic in ROM compatible with PET APPLE SORCERER hence taking the headache out of programming by using simple English statements. Much faster than currently available personal computers.
- ★ Professional 52 Key keyboard in 3 colours — software polled meaning that all debouncing and key decoding done in software.

FULL CONSTRUCTION DETAILS
IN P.E. AUG 1979 EDITION

Delivery date June 1979
at the 1979 MicroComputer Show
Customer orders in strict rotation only.

COMMANDS
CONT LIST NEW NULL RUN
STATEMENTS
CLEAR DATA DEF DIM END FOR
GOTO GOSUB IF GOTO IF THEN INPUT LET
NEXT ON GOTO ON GOSUB POKE PRINT READ
REM RESTORE RETURN STOP

EXPRESSIONS
OPERATORS
+ , * , / , % , ^ , NOT , AND , OR , > , < , <= , >= , RANGE 10⁻³² to 10⁺³²

VARIABLES
A,B,C...Z and two letter variables
The above can all be subscripted when used in an array. String variables use above names plus \$.e.g. A\$.



- ★ Video output and UHF Highgrade modulator (8Mz Bandwidth) which connects direct to the aerial socket of your T.V. Channel 36 UHF.
- ★ Fully stabilised 5V power supply including transformer on board.
- ★ Standard KANSAS city tape interface providing high reliability program storage — use on any standard domestic tape or cassette recorder.
- ★ 4K user RAM expandable to 8K on board £49 extra.
- ★ 40 line expansion interface socket on board for attachment of extender card containing 24K RAM and disk controller. (Ohio Scientific compatible).
- ★ 6502 machine code accessible through powerful 2K machine code monitor on board.
- ★ High quality thru plated P.C.B. with all I.C.'s mounted on sockets.

A tape of 10 programs on cassette — educational games, etc. will be supplied free of charge with each kit.

Simple Soldering due to clear and concise instructions compiled by Dr. A.A. Berk, BSc, PhD

NO EXTRAS NEEDED JUST HIT
'RETURN' AND GO.

Build, understand, and program your own
computer for only a small outlay.

ONLY £219 + VAT
including RF Modulator & Power supply
Absolutely no extras.

Due to the new prices of TTL this price will be
increased shortly. So order now to beat the
price increases and the rush.

SPECIAL CHARACTERS

- ↵ Erases line being typed, then provides carriage return, line feed
- ← Erases last character typed
- CR Carriage Return — must be at the end of each line.
- Separates statements on a line.
- CONTROL/C Execution or printing of a list is interrupted at the end of a line.
- "BREAK IN LINE XXXX" is printed, indicating line number of next statement to be executed or printed.
- CONTROL/O No outputs occur until return made to command mode. If an Input statement is encountered, either another CONTROL/O is typed, or an error occurs.
- ? Equivalent to PRINT

THE EXIDY SORCERER.

SORCERER COMPUTER SYSTEM

The Sorcerer Computer is a completely assembled and tested computer system. Standard configuration includes 63-key typewriter-style keyboard and 16-key numeric pad, 280 processor, dual cassette I/O with remote computer control at 300 and 1200 baud data rates, RS232 serial I/O for communications, parallel port for direct Centronics printer attachment, 4K ROM operating system, 8K ROM Microsoft BASIC in Rom Pac™ cartridge, composite video of 64 char/line 30 line/ screen, 128 upper/lower case ASCII set and 128 user-defined graphic symbols, operation manual, BASIC programming manual and cassette/video cables, connection for S-100 bus expansion.



LOOK!

- *32K RAM on board
- *RS232 interface
- *8K BASIC ROM
- *CUTS interface
- *4K MONITOR
- *KANSAS CITY interface
- *\$100 BUS
- *User defined graphic symbols
- *280 cpu

16K £860 £725 * 32K £950 £790 * Credit facilities available. * + VAT

IBM GOLF BALL SELECTIVE PRINTER

Refurbished to new specifications.

RS232C serial interface. Comes complete

on stand — floor mounting. Small and compact. Interfaces to Exidy Sorcerer,

TRS80 Apple and ITT 2020, Pet, CompuKit and Nascom.

Complete your word processing system with a
top quality printer for only £990.50.

THE ATARI video computer system



Atari's Video Computer System now offers
more than 1300 different game variations
and options in twenty great Game
Program™ cartridges!

Have fun while you sharpen
your mental and physical
coordination. You can play
rousing, challenging, sophisticated
video games, the games that made
Atari famous.

You'll have thrill after thrill, whether
you're in the thick of a dogfight,
screaming around a racetrack, or
dodging asteroids in an alien
galaxy. With crisp bright color (on
color TV) and incredible, true-to-life
sound effects. With special circuits
to protect your TV.

Cartridges now available

Basic Maths, Airsea Battle, Black
Jack, Breakout, Surround, Spacewar,
Video Olympics, Outlaw, Basketball,
All at £13.90 each.

Years and
years of fun and
satisfaction are
assured

SAVE £30

£169 £138.85

All prices exclude VAT. Our VAT rate is 8%. We will pay any extra.
Please quote this number CT1000 when ordering

COMP

COMPUTER
COMPONENTS

14 STATION ROAD, NEW BARNET, HERTFORDSHIRE

TEL: 01-441 2922 (Sales)

CLOSE TO NEW BARNET BR STATION — MOORGATE LINE

01-449 6596

OPEN — 10am to 7pm — Monday to Saturday

TELEX: 298755

VISIT OUR NEW SHOP AT 1 WALLCOT BUILDINGS, LONDON ROAD, BATH, AVON.

All Products Ex-Stock
Please check availability

(Part of the Compshop Ltd. Group)





NewBear



Introducing **ACORN** the new 6502 based microcomputer on Standard Eurocard Modules.

kit assembled and tested + 15% VAT.
£65.00 £75.00

MEMORIES DOWN IN PRICE 4116 only £8.50

2102-1	£0.85	2708	£6.99
2102L-1	£0.99	SWATBUG	£16.00
2112	£2.25	MC 6803L7 (MIKBUG)	£13.65
2114	£6.99	2716 (Intel Type)	£29.50

WE STOCK

VERO. OK TOOLS. JIM PAK. NASCOM. SYM-1.
 ITHICA AUDIO. 77-68 BEAR BAGS. SORCEROR.
 HORIZON AND MUCH MORE...

INTEGRATED CIRCUITS

Character Generators

74S 262	£13.70
2513 (U)	£6.50
2513 (L)	£6.50
MCM 6571P	£6.71
9368 (7 segment display decoder)	£2.45

UARTS

6402	£4.50
AY-5-1013	£4.50

plus 15% VAT

INTEGRATED CIRCUITS

Microcomputing I.C.'s

MC 6800	£7.15
MC 6821	£4.63
MC 6850	£6.74
MC 6810AP	£3.61
MC6840	£12.72
MC8602P	£2.88
MC 14536P	£3.69
MC3459	£2.43
Z80 CPU 2.5MHz	£8.99
Z80 PIO 2.5MHz	£7.99
Z80 CTC 2.5MHz	£7.99
Z80A CPU 4MHz	£13.99
Z80A PIO 4MHz	£10.00
Z80A CTC 4MHz	£10.00
SC/MP11	£8.88
(INS 8060N)	
INS 8154N	£8.18
8080A	£6.00
6502	£12.00
6522	£6.58
6532	£12.56

NEW

CRYSTALS

100.0	KHz	£3.25
200.0	KHz	£4.20
204.8	KHz	£3.25
1.0	MHz	£3.50
1.008	MHz	£2.80
1.032	MHz	£2.80
2.0	MHz	£2.60
4.0	MHz	£2.60
5.0	MHz	£2.60
10.0	MHz	£2.60
13.478	MHz	£3.25
36.0	MHz	£3.25

plus 15% VAT

2708 PROM PROGRAMMER

FITS ANY 6800 MACHINE KIT ONLY

£35.00
+ 15% VAT

**APPLE II
IN STOCK
AT NEW
LOW PRICES**

GAMES BOOKS

32 Basic Programs for the PET	T. Rugg £9.95
Chess and Computers	D. Levy £7.16
Chess Skill in Man and Machine	P. Frey £11.84
First Book of KIM	£7.00
Game Playing with Basic	D. Spencer £4.20
Game Playing with Computers	D. Spencer £10.20

BOOKS

6502 Applications Book	Sybex	£8.95
Programming a Microcomputer 6502	C. Foster	£7.95
Programming the 6502	Sybex	£7.95
Basic Microprocessors and the 6800	Motorola	£7.20
Peanut Butter and Jelly Guide to Computers	J. Willis	£6.20
6800 Applications Manual	Motorola	£10.50
Interfacing Techniques	Sybex	£7.50
Microprocessors Chips to Systems	Sybex	£7.50
A Consumers Guide to Personal Computers		£5.65
Best of Byte		£8.50
TTL Cookbook		£6.95
Active Filter Cookbook		£7.65
Basic Basic		£4.80
Advanced Basic		£4.00
Assembly Level Programming	Weller	£12.76

TERMS AND CONDITIONS

Minimum official order £10.00
 Postage & packing 30p on Hardware
 Hardware price plus 8% VAT.
 Callers welcome Mon-Sat 9.00-5.30
 but please phone us first on 0635 30505.

Barclaycard &
 Access
 Welcome

ALL MAIL ORDER TO NEWBURY

Newbear Computing Ltd.,
 40 Bartholomew St, Newbury, Berks.
 0635 30505

Visit our Northern office at 2A
 Gatley Rd, Cheadle, Cheshire.
 Tel 061-491-2290

BY
 RETURN
 ORDER
 SERVICE